

Contents

Connections

Playback



Accessories

Accessories	8
Inserting the batteries	9
Operating range of the remote control unit	9
Features	10
High quality sound	10
High performance	11
Easy operation	15
Part names and functions	16
Front panel	16
Display	20
Rear panel	22
Remote control unit	26

Connections

Speaker installation	30
Connecting speakers	37
Before connecting speakers	37
Speaker configuration and "Amp Assign" settings	41
Connecting 5.1-channel speakers	43
Connecting 7.1-channel speakers	44
Connecting 9.1-channel speakers	48
Connecting 11.1-channel speakers	55
Connecting 7.1-channel speakers: Bi-amp connection of front speakers	59
Connecting 7.1-channel speakers: Second pair of front speakers	60
Connecting multi-zone speakers	61
Connecting a TV	64
Connection 1 : TV equipped with an HDMI connector and compatible with the ARC (Audio Return Channel) / eARC (Enhanced Audio Return Channel)	65
Connection 2 : TV equipped with an HDMI connector and incompatible with the ARC (Audio Return Channel) / eARC (Enhanced Audio Return Channel)	67
Connection 3 : TV equipped without an HDMI connector	68

Front panel

Rear panel

2

Remote



Contents Connections Playback		Settings
Connecting a playback device	69	Playing a USB
Connecting a set-top box (Satellite tuner/cable TV)	70	Playing files s
Connecting a DVD player or Blu-ray Disc player	71	Listening to mu
Connecting a video camcorder or game console	72	Playing music
Connecting a turntable	73	Pairing with ot
Connecting a device with a multi-channel output connector	74	Reconnecting
Connecting a USB memory device to the USB port	75	Listening to FM
Connecting an FM/AM antenna	76	Listening to FI
Connecting to a home network (LAN)	78	Tuning in by e
Wired LAN	78	Changing the
Wireless LAN	79	Tuning in to st
Connecting an external control device	80	Preset Memor
REMOTE CONTROL jacks	80	Presetting the
DC OUT jack	81	Listening to pr
Connecting the power cord	82	Specify a nam
		Skipping pres
Playback		Concelling Dr

Playback

Basic operation	84
Turning the power on	84
Selecting the input source	84
Adjusting the volume	85
Turning off the sound temporarily (Muting)	85
Playback a DVD player/Blu-ray Disc player	85

Playing a USB memory device	86
Playing files stored on USB memory devices	87
Listening to music on a Bluetooth device	90
Playing music from Bluetooth device	91
Pairing with other Bluetooth devices	92
Reconnecting to this unit from a Bluetooth device	93
Listening to FM/AM broadcasts	94
Listening to FM/AM broadcasts	95
Tuning in by entering the frequency (Direct Tune)	96
Changing the tune mode (Tune Mode)	97
Tuning in to stations and presetting them automatically (Auto Preset Memory)	97
Presetting the current broadcast station (Preset Memory)	98
Listening to preset stations	98
Specify a name for the preset broadcast station (Preset Name)	99
Skipping preset broadcast stations (Preset Skip)	100
Cancelling Preset Skip	101
Listening to Internet Radio	102
Listening to Internet Radio	103
Playing back files stored on a PC or NAS	104
Playing back files stored on a PC or NAS	105

Tips

Rear panel

3





Appendix

Contents Connections Playback		Settings
Getting the HEOS App	108	Selecting a sound mode
HEOS Account	109	Selecting a sound mode
Playing from streaming music services	110	Direct playback
Listening to the same music in multiple rooms	113	Pure Direct playback
AirPlay function	117	Auto surround playback
Playing songs from your iPhone, iPod touch or iPad	118	Description of sound mo
Playing iTunes music with this unit	118	Sound mode that can be
Perform iTunes playback operations with the remote control unit		HDMI Control function
of this unit	119	Setting procedure
Play a song from your iPhone, iPod touch or iPad on multiple synced devices (AirPlay 2)	120	Smart Menu function
Spotify Connect function	121	Sleep timer function
Playing Spotify music with this unit	121	Using the sleep timer
Convenience functions	122	Smart select function
Adding to HEOS Favorites	123	Calling up the settings
Plaving back HEOS Favorites	123	Changing the settings
Deleting a HEOS Favorites	120	Panel lock function
Adjusting the volume of each channel to match the input source	127	Disabling all key button
(Channel Level Adjust)	125	Disabling all button oper
Adjusting the tone (Tone)	126	Canceling the Panel loc
Displaying your desired video during audio playback (Video		Remote lock function
Select)	127	Disabling the sensor fun
Adjusting the picture quality for your viewing environment (Picture	128	Enabling the remote ser
Mode)	128	Web control function
Playing the same music in all zones (All Zone Stereo)	129	Controlling the unit from

Selecting a sound mode	130
Selecting a sound mode	131
Direct playback	132
Pure Direct playback	132
Auto surround playback	133
Description of sound mode types	134
Sound mode that can be selected for each input signal	138
HDMI Control function	142
Setting procedure	142
Smart Menu function	143
Sleep timer function	145
Using the sleep timer	146
Smart select function	147
Calling up the settings	148
Changing the settings	149
Panel lock function	150
Disabling all key button operations	150
Disabling all button operations except VOLUME	150
Canceling the Panel lock function	151
Remote lock function	152
Disabling the sensor function of the remote control unit	152
Enabling the remote sensor function	152
Web control function	153
Controlling the unit from a web control	153
Playback in ZONE2 (Another room)	155
Connecting ZONE2	155
Playback in ZONE2	157

Tips

Appendix

Rear panel

4

Remote

Settings		Speakers	194
U	450	Audyssey® Setup	194
Menu map	159	Procedure for speaker settings (Audyssey [®] Setup)	196
Menu operations	163	Error messages	202
Audio	164	Retrieving Audyssey [®] Setup settings	204
Center Level Adjust	164	Manual Setup	205
Subwoofer Level Adjust	164	Amp Assign	205
Surround Parameter	165	Speaker Config.	211
M-DAX	168	Distances	215
Audio Delay	169	Levels	217
Volume	170	Crossovers	218
Audyssey®	171	Bass	219
Graphic EQ	174	Front Speaker	220
Video	176	Network	221
Picture Adjust	176	Information	221
HDMI Setup	178	Connection	221
Output Settings	183	Wi-Fi Setup	222
On Screen Display	187	Settings	224
4K Signal Format	188	Network Control	225
TV Format	189	Friendly Name	226
Inputs	190	Diagnostics	226
Input Assign	190	Diagnosilos	
Source Rename	192		
Hide Sources	192		
Source Level	193		
Input Select	193		





Contents

Connections

Playback

Settings

Tips

HEOS Account	228
You have not signed in	228
You have already signed in	228
General	229
Language	229
ECO	229
ZONE2 Setup	233
Zone Rename	235
Smart Select Names	235
Trigger Out	236
Front Display	236
Firmware	237
Information	240
Usage Data	241
Save & Load	242
Setup Lock	242
Reset	243
Limiting the operating zone with the remote control	244

Tips	
Tips	246
Troubleshooting	248
Power does not turn on / Power is turned off	249
Operations cannot be performed through the remote control unit	250
Display on this unit shows nothing	250
No sound comes out	251
Desired sound does not come out	252
Sound is interrupted or noise occurs	255
No video is shown on the TV	256
The menu screen is not displayed on the TV	258
The color of the menu screen and operations content displayed on the television is different from normal	258
AirPlay cannot be played back	259
USB memory devices cannot be played back	260
Bluetooth cannot be played back	261
The Internet radio cannot be played back	262
Music files on PC or NAS cannot be played back	263
Various online services cannot be played	264
The HDMI Control function does not work	264
Cannot connect to a wireless LAN network	265
When using HDMI ZONE2, the devices does not function properly	266
Update/upgrade error messages	267
Resetting factory settings	268
Resetting network settings	269

Rear panel

6

Remote



С	11	-1	11	

Appendix

About HDMI	270
Video conversion function	273
Playing back a USB memory devices	275
Playing back a Bluetooth device	276
Playing back a file saved on a PC or NAS	277
Playing back Internet Radio	278
Personal memory plus function	278
Last function memory	278
Sound modes and channel output	279
Sound modes and surround parameters	281
Types of input signals, and corresponding sound modes	284
Explanation of terms	287
Trademark information	296
Specifications	298
Index	304
License	307









Thank you for purchasing this Marantz product.

To ensure proper operation, please read this owner's manual carefully before using the product.

After reading this manual, be sure to keep it for future reference.

Accessories

Check that the following parts are supplied with the product.

Quick Start Guide	Safety Instructions	Notes on radio	Warranty (for USA/for CANADA)	Cable labels
Power cord	FM indoor antenna	AM loop antenna	Sound calibration microphone	Sound calibration microphone stand
Remote control unit (RC035SR)	R03/AAA batteries	External antennas for Bluetooth/wireless connectivity		





Playback


Settings

Inserting the batteries

Remove the rear lid in the direction of the arrow and remove it.



2 Insert two batteries correctly into the battery compartment as indicated.




3 Put the rear cover back on.

NOTE

- To prevent damage or leakage of battery fluid:
 - Do not use a new battery together with an old one.
 - Do not use two different types of batteries.
- Remove the batteries from the remote control unit if it will not be in use for long periods.
- If the battery fluid should leak, carefully wipe the fluid off the inside of the battery compartment and insert new batteries.

Operating range of the remote control unit

Point the remote control unit at the remote sensor when operating it.







Features

High quality sound

 With discrete circuit technology, the power amplifier provides identical quality for all 9-channels (150 Watts x 9-channels) For optimum realism and stunning dynamic range, the power amplifier section features discrete power devices (not integrated circuitry). By using high current, high power discrete power devices, the amplifier is able to easily drive high quality speakers.

· Current feedback amplifier

This unit uses a high-speed current feedback amplifier circuit for its preamplifier so that signals from a Blu-ray Disc player and other equipment that support high-definition audio formats can be amplified with high fidelity. The high-speed current feedback amplifier also reproduces a natural sound space.

• Dolby Atmos (12 p. 288)

This unit is equipped with a decoder that supports Dolby Atmos audio format. The placement or movement of sound is accurately reproduced by the addition of overhead speakers, enabling you to experience an incredibly natural and realistic surround sound field.

• DTS:X (@<u>p. 290</u>)

This unit is equipped with the DTS:X decoder technology. DTS:X brings the home theater experience to new heights with its immersive object based audio technology which removes the bounds of channels. The flexibility of objects allows for sound to be scaled large or small and moved around the room with greater accuracy than ever before leading to a richer immersive audio experience.

• DTS Virtual:X (2 p. 291)

DTS Virtual:X technology features DTS's proprietary virtual height and virtual surround processing to deliver an immersive sound experience from any type of input source (stereo to 7.1.4 channel) and speaker configuration.

* DTS Virtual:X is not for use when Height speakers are connected.

Audyssey LFC[™] (Low Frequency Containment) (Pp <u>p. 173</u>)

Audyssey LFC[™] solves the problem of low frequency sounds disturbing people in neighboring rooms or apartments. Audyssey LFC[™] dynamically monitors the audio content and removes the low frequencies that pass through walls, floors and ceilings. It then applies psychoacoustic processing to restore the perception of low bass for listeners in the room. The result is great sound that no longer disturbs the neighbors.

Discrete subwoofers and Audyssey Sub EQ HT[™] (12 p. 195)

The unit has two subwoofer output capability and can adjust the level and delay for each subwoofer individually.

Audyssey Sub EQ HT[™] makes the integration seamless by first compensating for any level and delay differences between the two subwoofers and then applying Audyssey MultEQ[®] XT32 to both subwoofers together for improved deep bass response and detail.

Front panel

Remote



Contents Connections Playback	Settings Tips Appendix
High performance	 Digital video processor upscales analog video signals (SD resolution) to HD (720p/1080p) and 4K (19 p. 185)
• 4K 60Hz input/output supported 4K 60p 4:4:4	4K 4K Up to 1080p 4K Up scaling

When 4K Ultra HD (High Definition) is used, an input/output speed of 60 frames per second (60p) is achieved for video signals. When connected to 4K Ultra HD and 60p video signal input compatible TV, you can enjoy the sense of realism only available from high-definition images, even when viewing fast-moving video.

This unit also supports image processing for 4K 60p, 4:4:4 and 24-bit videos. By processing the video at the original resolution, this unit lets you enjoy flawless, high-definition picture quality.

This unit also supports HDR (High Dynamic Range) and BT.2020 wide color gamut.

HDCP 2.2

This unit is compatible with HDCP 2.2 copyright protection standard.

This unit is equipped with a 4K video upscaling function that allows analog video or SD (Standard Definition) video to be output via HDMI at 4K (3840×2160 pixels) resolution. This function enables the device to be connected to a TV using a single HDMI cable, and produces high definition images for any video source.

• Equipped with HDMI ZONE2 output (Pp. 155)


The ZONE2 multi-room output includes an HDMI output that lets you enjoy a different A/V source in that room, with another program playing in the main room.







 HDMI connections enable connection to various digital AV devices (8 inputs, 3 outputs)




For connection to a broad range of digital sources, this unit features 8 HDMI inputs, including 1 on the front panel that lets you quickly and conveniently connect a camcorder, game console or other HDMI-equipped device. There are dual HDMI outputs for the main room, and a third HDMI output for ZONE2.

· eARC (Enhanced Audio Return Channel) function compatibility

The eARC function is compatible with conventional ARC functioncompatible audio formats in addition to multichannel linear PCM, Dolby TrueHD, Dolby Atmos, DTS-HD Master Audio, DTS:X and other audio formats a conventional ARC function cannot transmit.

Additionally, connecting to an eARC function-compatible television enables enjoyment of higher-quality surround playback of the audio content played from your television. The device is equipped with a AirPlay[®] function in addition to network functions such as Internet radio etc. (197 p. 117)



You can enjoy a wide variety of content, including listening to Internet Radio, playing audio files stored on your PC.


This unit also supports Apple AirPlay which lets you stream your music library from an iPhone[®], iPad[®], iPod touch[®] or iTunes[®].

• Supports AirPlay 2[®] wireless audio

Sync multiple AirPlay 2 compatible devices/speakers for simultaneous playback.

This unit supports AirPlay 2 and requires iOS 11.4 or later.







You can enjoy music simply by connecting wirelessly with your smartphone, tablet, PC, etc.

You can select and play back the respective inputs in MAIN ZONE and ZONE2.

In addition, when the All Zone Stereo function is used, the music being played back in MAIN ZONE can be enjoyed in all the zones at the same time. This is useful when you want to let the BGM propagate throughout the whole house.

· Energy-saving design

This unit is equipped with an ECO Mode function that allows you to enjoy music and movies while reducing the power consumption during use, and also an auto-standby function that automatically turns off the power supply when the unit is not in use. This helps reduce unnecessary power use.





 Compatible with the "Marantz 2016 AVR Remote" App* for performing basic operations of the unit with an iPad, iPhone or Android[™] devices (Google, Amazon Kindle Fire)



Along with many new features, the graphics and user interface have been completely overhauled. The new app gives you full control of the AVR as well as access to its setup menu for detailed adjustments from your phones or tablets. "Marantz 2016 AVR Remote" App also gives you quick access to the receiver's status display, option menus, Marantz Blu-ray Disc player control, and online owner's manual for your convenience.

* Download the appropriate "Marantz 2016 AVR Remote" App for your iOS or Android devices. This unit needs to be connected to the same LAN or Wi-Fi (wireless LAN) network that the iPhone or iPod touch is connected to. HEOS provides streaming music from your favorite online music sources





HEOS wireless multi-room sound system that enables you to enjoy your favorite music anywhere and everywhere around your home. By utilizing your existing home network and the HEOS App (available for iOS, Android and Amazon devices), you can explore, browse, and play music from your own music library or from many online streaming music services.

When multiple HEOS devices are connected to the same network, HEOS devices can be grouped to play back the same music on all devices simultaneously, or different music can be played on each separate HEOS device.

Front panel





Easy operation

• "Setup Assistant" provides easy-to-follow setup instructions First select the language when prompted. Then simply follow the instructions displayed on the TV screen to set up the speakers, network, etc.

• Easy to use Graphical User Interface

This unit is equipped with a Graphical User Interface for improved operability.

Front panel








Contents	nections Playback	Settings	Tips	Appendix
----------	-------------------	----------	------	----------

Part names and functions

Front panel



For details, see the next page.




Contents Connections Playback	Settings Tips Appendix
Power operation button (Å)	 (i) INPUT SELECTOR knob This selects the input source. (1) p. 84) (i) Display This displays various pieces of information. (1) p. 20) (i) Remote control sensor This receives signals from the remote control unit. (1) p. 9) (i) VOLUME knob This adjusts the volume level. (1) p. 85) (i) Door When you are using buttons and/or connectors behind the door, press the bottom of the door to open it. Be careful not to catch your fingers when closing the door.
Used to turn the power of the MAIN ZONE (room where this unit is located) on/off (standby). ($\mathfrak{P} \underline{p} . 84$)	


2 Power indicator

This is lit as follows according to the power status:

- Off: Power on
- Red: Normal standby
- Orange:
 - When "HDMI Pass Through" is set to "On" (2 p. 178)
 - When "HDMI Control" is set to "On" (maintoing p. 180)
 - When "Network Control" is set to "Always On" (2) p. 225)







PURE DIRECT button

This switches the sound mode between Direct, Pure Direct and Auto surround.

- "Direct playback" (Direct playback")

PURE DIRECT indicator

This lights when the "Pure Direct" mode is selected as the sound mode. (@p. 132)

This switches the M-DAX mode. (Pp. 168)

This lights when the M-DAX mode is selected. (127 p. 168)

This turns the power of ZONE2 (another room) on/off. (127 p. 157)

This selects the input source for ZONE2. (127 p. 157)

These select preset broadcast stations. (12 p. 98)

Each press of this switches the brightness of the display. (127 p. 236)

Each press of this switches the status information that is shown on the display.

SOUND MODE button

Switching the sound mode. (P p. 130)



SETUP MIC jack

This is used to connect the supplied Sound calibration microphone. ($(\underline{\mathcal{D}} p. 197)$)

🚯 USB port (•<->


This is used to connect USB storages (such as USB memory devices). ($\mathbb{E} p. 75$)

AUX1-HDMI connector

This is used to connect HDMI output compatible devices such as video camcorders and game consoles. ($\mathbb{E}_{p.72}^{-}$, 72)

AUX1 INPUT connectors

Used to connect analog output compatible devices such as video camcorders and game consoles. (12) p. 72)



Headphones jack (PHONES)

This is used to connect headphones.

When the headphones are plugged into this jack, audio will no longer be output from the connected speakers or from the PRE OUT connectors.

NOTE

• To prevent hearing loss, do not raise the volume level excessively when using headphones.

Front panel










Display

The input source name, sound mode, setting values and other information are displayed here.

Standard display



Volume indicator


Input source indicator

The currently selected input source name is displayed.

If the input source name has been changed using "Source Rename" in the menu, the input source name after the change is displayed. (ICP $\underline{p},\underline{192})$

Tuner display

These light up according to the reception conditions when the input source is set to "Tuner".




- 3 Lights up when the broadcast is properly tuned in.
- () In the FM mode, this lights up when receiving stereo broadcasts.



20

Remote





() This lights when the sleep mode is selected. (1) p. 145)

(@p. 157)










Playback

Rear panel




For details, see the next page.



Contents Connections


Playback



Bluetooth/wireless LAN antenna connectors

Used to connect the included external antennas for Bluetooth/wireless connectivity when connecting to a network via wireless LAN, or when connecting to a handheld device via Bluetooth. (IPp. 79)

- ① Place the external antennas for Bluetooth/wireless connectivity evenly over the screw terminal of rear.
- (2) Turn clockwise until the antennas is fully connected.
- (3) Rotate the antenna upwards for best reception.



OC OUT jack

Used to connect devices equipped with the trigger function. ($(\ensuremath{\mathbb{CP}}\xspace, 81)$

Digital audio connectors (DIGITAL AUDIO)

Used to connect devices equipped with digital audio connectors.

- "Connection 2 : TV equipped with an HDMI connector and incompatible with the ARC (Audio Return Channel) / eARC (Enhanced Audio Return Channel)" (2 p. 67)
- "Connection 3 : TV equipped without an HDMI connector" (<u>P. 68</u>)
- "Connecting a set-top box (Satellite tuner/cable TV)" (p. 70)
- "Connecting a DVD player or Blu-ray Disc player" (2 p. 71)

RS-232C connector

Used to connect home automation controller devices fitted with RS-232C connectors. Consult the owner's manual of the home automation controller for more information about serial control of this unit.

Perform the operation below beforehand.

- 1 Turn on the power of this unit.
- (2) Turn off the power of this unit from the external controller.
- (3) Check that the unit is in the standby mode.





Contents Connections Playback	Settings Tips Appendix
	 Video connectors (VIDEO) Used to connect devices equipped with video connectors. "Connection 3 : TV equipped without an HDMI connector" (<u>P. 68</u>) "Connecting a set-top box (Satellite tuner/cable TV)" (<u>P. 70</u>) "Connecting a DVD player or Blu-ray Disc player" (<u>P. 71</u>) (IDMI connectors Used to connect devices equipped with HDMI connectors. "Connection 1 : TV equipped with an HDMI connector and compatible with the ARC (Audio Return Channel) / eARC (Enhanced Audio Return Channel)" (<u>P. 65</u>)

G FLASHER IN jack

Used when using a control BOX or other such control devices to control this unit.

6 SIGNAL GND terminal

Used to connect a ground wire for the turntable. (12 p. 73)

NETWORK connector

Used to connect to a LAN cable when connecting to a wired LAN network. (10 p. 78)

REMOTE CONTROL jacks

Used to connect infrared receivers/transmitters in order to operate this unit and external devices from a different room. (1 p. 80)


- · "Connection 2 : TV equipped with an HDMI connector and incompatible with the ARC (Audio Return Channel) / eARC (Enhanced Audio Return Channel)" (12 p. 67)
- "Connecting a set-top box (Satellite tuner/cable TV)" (2 p. 70)
- "Connecting a DVD player or Blu-ray Disc player" (P p. 71)

AC inlet (AC IN)

Used to connect the power cord. (12 p. 82)

Contents

Playback



FM/AM antenna terminals (ANTENNA)

Used to connect FM antennas and AM loop antennas. (12 p. 76)

Analog audio connectors (AUDIO)

Used to connect devices equipped with analog audio connectors.

- "Connecting a set-top box (Satellite tuner/cable TV)" (p. 70)
- "Connecting a DVD player or Blu-ray Disc player" (1 p. 71)
- "Connecting a turntable" (m p. 73)

7.1-channel input connectors (7.1CH IN)

Used to connect to a device that has multi-channel audio output connectors. ($\underline{r_{T}}$ <u>p. 74</u>)

Speaker terminals (SPEAKERS)

Used to connect speakers. (Pp. 37)

PRE OUT connectors

Used to connect a subwoofer with built-in amplifier or an external power amplifier.

- "Connecting the subwoofer" (2 p. 38)
- "Connecting ZONE2" (2 p. 155)

Component video connectors (COMPONENT VIDEO)

Used to connect devices equipped with component video connectors.

- "Connection 3 : TV equipped without an HDMI connector" (<u>P. p. 68</u>)
- "Connecting a set-top box (Satellite tuner/cable TV)" (p. 70)
- "Connecting a DVD player or Blu-ray Disc player" (
 p. 71)

NOTE


• Do not touch the inner pins of the connectors on the rear panel. Electrostatic discharge may cause permanent damage to the unit.

Front panel





Remote control unit



O ZONE SELECT buttons

These switch the zone (MAIN ZONE, ZONE2) that is operated through the remote control unit.

- "Playback in ZONE2" (2 <u>p. 157</u>)
- "Menu operations" (m p. 163)

Input source select buttons

These selects the input source.

- "Selecting the input source" (2 p. 84)
- "Playback in ZONE2" (2 <u>p. 157</u>)

③ Channel/page search buttons (CH/PAGE ▲▼)

These select radio stations registered to presets or switch pages. ($(\underline{\mathbb{F}}_{p.98}^{-})$)

MUTE button (◀×)

This mutes the output audio.

- "Turning off the sound temporarily (Muting)" (2 p. 85)
- "Turning off the sound temporarily (Muting) (ZONE2)" (<u>P. 158</u>)

(Information button (INFO)

This displays the status information on the TV screen. (12 p. 241)

6 Cursor buttons ($\Delta \nabla \triangleleft \triangleright$)

These select items.





Contents	Connections Playback	C Settings Tips Appendix
		 () BACK button This returns to the previous screen. () System buttons These perform playback related operations. Tuning up / Tuning down buttons (TUNE +, -) These select either FM broadcast or AM broadcast. (☞ p. 95) () SMART SELECT buttons (1 - 4) These call up settings registered to each button, such as input source, volume level and sound mode settings. (☞ p. 147) () SOUND MODE buttons These select the sound mode. (☞ p. 130) () Remote control signal transmitter This transmits signals from the remote control unit. (☞ p. 9) () SLEEP button This sets the sleep timer. (☞ p. 145)



MOVIE

PURE

D

Remote



or		

POWER button (位)

This turns the power on/off.

- "Turning the power on" (main the power on" (main the power on the po
- "Playback in ZONE2" (m <u>p. 157</u>)

❶ ECO Mode button (♥)

This switches to ECO Mode. (2) p. 229)

WOLUME buttons (▲▼)

These adjusts the volume level.

- "Adjusting the volume" (main p. 85)
- "Adjusting the volume (ZONE2)" (2 p. 158)

OPTION button


This displays the option menu on the TV screen.

ENTER button

This determines the selection.

SETUP button

This displays the menu on the TV screen. (p. 163)



Display





Front panel

Contents


Speaker installation	30
Connecting speakers	37
Connecting a TV	64
Connecting a playback device	69
Connecting a USB memory device to the USB port	75
Connecting an FM/AM antenna	76
Connecting to a home network (LAN)	78
Connecting an external control device	80
Connecting the power cord	82

NOTE

- Do not plug in the power cord until all connections have been completed. However, when the "Setup Assistant" is running, follow the instructions in the "Setup Assistant" (page 9 in the separate "Quick Start Guide") screen for making connections. (During "Setup Assistant" operation, the input/output connectors do not conduct current.)
- Do not bundle power cords together with connection cables. Doing so can result in noise.

Cables used for connections


Provide necessary cables according to the devices you want to connect.





Speaker installation

Determine the speaker system depending on the number of speakers you are using and install each speaker and subwoofer in the room. Speaker installation is explained using this example of a typical installation.




Place the FRONT left and right speakers an equal distance from the main listening position. The distance between each speaker and your TV should also be the same.
Place the CENTER speaker in between the front speakers and above or below your TV.
Place the SURROUND left and right speakers an equal distance to the left and right sides of the main listening position. If you don't have surround back speakers, move the surround speakers slightly behind your listening position.
Place the SURROUND BACK left and right speakers an equal distance from the main listening position and directly behind the main listening position. When using a single surround back speaker (SB), place it directly behind the listening position.
Place the SUBWOOFER at a convenient location near the front speakers. If you have two subwoofers, place them asymmetrically across the front of your room.

Front panel



Contents

Playback



FHL/FHR (Front height speaker left/right):	Place the FRONT HEIGHT left and right speakers directly above the front speakers. Mount them as close to the ceiling as possible and aim them towards the main listening position.
TFL/TFR (Top front speaker left/right):	Mount the TOP FRONT left and right speakers on the ceiling slightly in front of your main listening position and aligned with the left and right front speakers.
TML/TMR (Top middle speaker left/right):	Mount the TOP MIDDLE left and right speakers directly above the main listening position and aligned with the left and right front speakers.
TRL/TRR (Top rear speaker left/right):	Mount the TOP REAR left and right speakers on the ceiling slightly behind your main listening position and aligned with the left and right front speakers.
RHL/RHR (Rear height speaker left/right):	Place the REAR HEIGHT left and right speakers directly behind the main listening position. Mount them as close to the ceiling as possible and aligned with the left and right front speakers.


Front panel



31

Remote






FDL/FDR (Front Dolby speaker left/right):	Place the FRONT Dolby Atmos Enabled speaker on the front speaker. For a Dolby Atmos Enabled integrated with a front speaker, place the Dolby Atmos Enabled speaker instead of the front speaker.
SDL/SDR (Surround Dolby speaker left/right):	Place the SURROUND Dolby Atmos Enabled speaker on the surround speaker. For a Dolby Atmos Enabled speaker integrated with a surround speaker, place the Dolby Atmos Enabled speaker instead of the surround speaker.
BDL/BDR (Back Dolby speaker left/right):	Place the BACK Dolby Atmos Enabled speaker on the surround back speaker. For a Dolby Atmos Enabled speaker integrated with a surround back speaker, place the Dolby Atmos Enabled speaker instead of the surround back speaker.

About Dolby Atmos Enabled speakers

Dolby Atmos Enabled speakers reflect the sound off the ceiling to allow the sound to come from over your head by using a special upwardpointing speaker that is placed on the floor.

You can enjoy the Dolby Atmos 3D sound even in an environment where speakers cannot be installed on the ceiling.




Front panel






- This unit is compatible with Dolby Atmos and DTS:X which offers an even wider and deeper surround sensation.
- Dolby Atmos is not supported in a 5.1-channel or less speaker configuration.
- DTS:X can be selected regardless of the speaker configuration.
- Use the illustration below as a guide for how high each speaker should be installed. The height does not need to be exactly the same.














When using a single surround back speaker, place it directly behind the listening position.












Layout including height speakers and ceiling speakers


Height speaker layout example

Combination of 5.1-channel layout and front height/rear height speakers.

Ceiling speaker layout example

Combination of 5.1-channel layout and top front/top rear speakers.








Dolby Atmos Enabled speaker layout example

Combination of 5.1-channel layout and front Dolby/surround Dolby speakers.





Connecting speakers

Here we connect the speakers in the room to this unit.

Before connecting speakers

NOTE

- Disconnect this unit's power plug from the power outlet before connecting the speakers. Also, turn off the subwoofer.
- Connect so that the speaker cable core wires do not protrude from the speaker terminal. The protection circuit may be activated if the core wires touch the rear panel or if the + and - sides touch each other. ("Protection circuit" (127 p. 295))
- Never touch the speaker terminals while the power cord is connected. Doing so could result in electric shock. When the "Setup Assistant" (page 9 in the separate "Quick Start Guide") is running, follow the instructions in the "Setup Assistant" screen for making connections. (Power is not supplied to the speaker terminals while the "Setup Assistant" is running.)
- Use speakers with an impedance of 4 16 Ω /ohms.

NOTE

- Carry out the following settings when using a speaker with an impedance of 4 6 $\Omega/ohms.$
 - 1. Press and hold the main unit's ZONE2 SOURCE and STATUS at the same time for at least 3 seconds.

"Video Format < NTSC>" appears on the display.

- 2. Press DIMMER on the main unit three times.
 - "Sp.Imp. <8ohms>" appears on the display.
- 3. Press TUNER PRESET CH + or TUNER PRESET CH on the main unit to select the impedance.

8ohms (Default):	Select when the impedance for all of the connected speakers is 8 Ω /ohms or over.
6ohms:	Select when the impedance for any of the connected speakers is 6 Ω /ohms.
4ohms:	Select when the impedance for any of the connected speakers is 4 Ω /ohms.

4. Press the main unit's STATUS to complete the setting.

Rear panel







Connecting the speaker cables

Carefully check the left (L) and right (R) channels and + (red) and – (black) polarities on the speakers being connected to this unit, and be sure to connect the channels and polarities correctly.

Peel off about 3/8 inch (10 mm) of sheathing from the tip of the speaker cable, then either twist the core wire tightly or terminate it.



Turn the speaker terminal counterclockwise to loosen it.



3 Insert the speaker cable's core wire to the hilt into the speaker terminal.



4 Turn the speaker terminal clockwise to tighten it.



Front panel

Remote






Connecting the subwoofer

Use a subwoofer cable to connect the subwoofer. Two subwoofers can be connected to this unit.

Tips

To use two subwoofers, set "Subwoofer" to "2 spkrs" in the "Speaker Config." setting. ($\bigcirc p.212$)

The level and distance can be set separately for Subwoofer 1 and Subwoofer 2.



About the cable labels (supplied) for channel identification

The channel display section for speaker terminals on the rear panel is color-coded for each channel to be identifiable.

Attach the cable label corresponding to each speaker to each speaker cable.

This makes it easy to connect the correct cable to the speaker terminals on the rear panel.

Speaker	Color				
FRONT L	White				
FRONT R	Red				
CENTER	Green				
SURROUND L	Light Blue				
SURROUND R	Blue				
SURROUND BACK L	Beige				
SURROUND BACK R	Brown				
FRONT HEIGHT L	Light Yellow				
FRONT HEIGHT R	Yellow				
TOP FRONT L	Light Yellow				
TOP FRONT R	Yellow				
TOP MIDDLE L	Light Purple				
TOP MIDDLE R	Purple				

Speaker	Color
TOP REAR L	Light Purple
TOP REAR R	Purple
REAR HEIGHT L	Light Purple
REAR HEIGHT R	Purple
FRONT DOLBY L	Light Yellow
FRONT DOLBY R	Yellow
SURROUND DOLBY L	Light Purple
SURROUND DOLBY R	Purple
BACK DOLBY L	Light Purple
BACK DOLBY R	Purple
SUBWOOFER 1	Black
SUBWOOFER 2	Black

Front panel




Attach the cable label for each channel to its speaker cable as shown in the diagram.

Refer to the table and attach the label to each speaker cable.

Then, make connection so that the color of the speaker terminal matches that of the cable label.

[How to attach the cable labels]











Speaker configuration and "Amp Assign" settings

This unit has a built-in 9-channel power amplifier. In addition to the basic 5.1-channel system, a variety of speaker systems can be configured by changing the "Amp Assign" settings to suit the application, such as 7.1-channel systems, bi-amp connections and 2-channel systems for multi-zone playback. (IPP p. 205)

Perform "Amp Assign" settings to suit the number of rooms and speaker configuration to be installed. (1 p. 205)

Playback speaker in each zone	"Amp Assign" settings	Connection	
MAIN ZONE	ZONE2	Amp Assign Settings	page
5.1-channel playback		Can be set in all "Amp Assign" modes.	<u>43</u>
7.1-channel playback		7.1ch + ZONE2 (Default)	44
9.1-channel playback		9.1ch	<u>48</u>
11.1-channel playback		11.1ch	<u>55</u>
7.1-channel playback (bi-amp connection of front speakers)		7.1ch (Bi-Amp)	<u>59</u>
Second front speakers		7.1ch + Front B	<u>60</u>
7.1-channel playback	2-channel (Speaker out)	7.1ch + ZONE2 (Default)	<u>61</u>
5.1-channel playback (bi-amp connection of front speakers)	2-channel (Speaker out)	5.1ch (Bi-Amp) + ZONE2	<u>62</u>

The sound mode that can be selected varies according to the speaker configuration. See "Sound modes and channel output" (127 p. 279) for the sound modes that are supported.


The following pages provide basic connection examples.





• In addition to the connections described in <u>p.43</u> - <u>62</u>, this unit allows for various speaker connections with the "Amp Assign" setting.

Also refer to the menu screen in "View Terminal Config." on the "Amp Assign" setting screen, which shows how to make connections in your environment.















Connecting 5.1-channel speakers

This serves as a basic 5.1-channel surround system.















Connecting 7.1-channel speakers

Example connections when using surround back speakers

This 7.1-channel surround system is the same as a basic 5.1-channel system but with surround back speakers.



• Set "Floor" - "Layout" to "5ch & SB" in the menu when connecting in this configuration. (12) p. 207)



• When using a single surround back speaker, connect it to the SURROUND BACK L terminal.

Front panel











Example connections when using ceiling speakers

This 7.1-channel surround system is the same as a basic 5.1-channel system but with ceiling speakers.






- Set "Floor" "Layout" to "5ch" and "Height Sp" to "2ch" in the menu when connecting in this configuration. (127 p. 207)
- The top front or top rear speakers can be connected instead of the top middle speakers. In this case, set the ceiling speakers to be connected under "Height" "Layout" in the menu. (127 p. 209)






Example connections when using height speakers

This 7.1-channel surround system is the same as a basic 5.1-channel system but with front height speakers.






- Set "Floor" "Layout" to "5ch" and "Height Sp" to "2ch" in the menu when connecting in this configuration. (1) p. 207)
- The rear height speakers can be connected instead of the front height speakers. In this case, set the height speakers to be connected under "Height" "Layout" in the menu. (127 p. 209)





Example connections when using Dolby Atmos Enabled speakers

This 7.1-channel surround system is the same as a basic 5.1-channel system but with front Dolby speakers.



- Set "Floor" "Layout" to "5ch" and "Dolby Sp" to "2ch" in the menu when connecting in this configuration. (12 p. 207)
- The surround Dolby speakers can be connected instead of the front Dolby speakers. In this case, set the Dolby Atmos Enabled speakers to be connected under "Height" -"Layout" in the menu. (P p. 209)










Connecting 9.1-channel speakers


This system, which is based on a 5.1-channel system, plays back up to 9.1-channels at the same time.

You can connect speakers for up to 11-channels for MAIN ZONE. When you connect speakers for 10 or more channels, the output speakers automatically switch according to the input signal and sound mode.

Example connection when using one set of ceiling speakers



• Set "Height" - "Height Sp" to "2ch" in the menu when connecting in this configuration. (127 p. 208)



* The top front or top rear speakers can be connected instead of the top middle speakers. In this case, set the ceiling speakers to be connected under "Height" -"Layout" in the menu. (IPP p. 209)

Front panel













Example connection when using two sets of ceiling speakers





* You can change the combination of the HEIGHT1 and HEIGHT2 channels in the settings. (127 p. 54)

• Set "Height" - "Height Sp" to "4ch" in the menu when connecting in this configuration. (IPp . 207)


Front panel








Example connection when using one set of height speakers



 Set "Height" - "Height Sp" to "2ch" in the menu when connecting in this configuration. (<u>Pp. 208</u>)



* The rear height speakers can be connected instead of the front height speakers. In this case, set the height speakers to be connected under "Height" - "Layout" in the menu. (127 p. 209)











Example connection when using two sets of height speakers





* You can change the combination of the HEIGHT1 and HEIGHT2 channels in the settings. (2 p. 54)

 Set "Height" - "Height Sp" to "4ch" in the menu when connecting in this configuration. (<u>Pp. 207</u>)

Front panel













Example connection when using one set of Dolby Atmos Enabled speakers



• Set "Height" - "Dolby Sp" to "2ch" in the menu when connecting in this configuration. (127 p. 208)



* The surround Dolby or back Dolby speakers can be connected instead of the front Dolby speakers. In this case, set the Dolby Atmos Enabled speakers to be connected under "Height" - "Layout" in the menu. (127 p. 209)



52

Remote









53

Remote

Rear panel

Example connection when using two sets of Dolby Atmos Enabled speakers





* You can change the combination of the HEIGHT1 and HEIGHT2 channels in the settings. (127 p. 54)

Index

Front panel

 Set "Height" - "Dolby Sp" to "4ch" in the menu when connecting in this configuration. (<u>Pp. 207</u>)

Display

Tips

Channels output from the HEIGHT1 and HEIGHT2 speaker terminals can be changed to the following patterns according to the speaker systems being used.

Set this from "Amp Assign" in the menu. (m p. 205)

Combination of height speakers to be used		Connected	Connected terminals			
Number of height/ ceiling speakers	Number of Dolby Speakers	Combination pattern	HEIGHT1 SPEAKER	HEIGHT2 SPEAKER		
2 speakers None	Front Height	Front Height	-			
	Top Front	Top Front	-			
	2 speakers None	Top Middle	Top Middle	-		
	Top Rear	Top Rear	-			
		Rear Height	Rear Height	-		
	Front Dolby	Front Dolby	-			
None	2 speakers	Surround Dolby	Surround Dolby	-		
		Back Dolby	Back Dolby	-		
		Front Height & Top Middle	Front Height	Top Middle		
	Front Height & Top Rear	Front Height	Top Rear			
1 anaakara	Nono	Front Height & Rear Height	Front Height	Rear Height		
4 speakers None	Top Front & Top Rear	Top Front	Top Rear			
		Top Front & Rear Height	Top Front	Rear Height		
	Top Middle & Rear Height	Top Middle	Rear Height			
2 speakers 2 speakers		Front Dolby & Top Rear	Front Dolby	Top Rear		
	0 an a share	Front Dolby & Rear Height	Front Dolby	Rear Height		
	Front Height & Surr. Dolby	Front Height	Surround Dolby			
	Top Front & Surr. Dolby	Top Front	Surround Dolby			
None	4 speakers	Front Dolby & Surround Dolby	Front Dolby	Surround Dolby		






Connecting 11.1-channel speakers


This system, which is based on a 5.1-channel system, plays back up to 11.1-channels at the same time. You can connect speakers for 11-channels for MAIN ZONE by using an external power amplifier.

Example connection when using two sets of ceiling speakers



 Set "Height" - "Height Sp" to "4ch" in the menu when connecting in this configuration. (<u>Pp. 208</u>)

Display



* You can change the combination of the HEIGHT1 and HEIGHT2 channels in the settings. (127 p. 58)





Rear panel











Example connection when using two sets of height speakers



• Set "Height" - "Height Sp" to "4ch" in the menu when connecting in this configuration. (129 p. 208)




* You can change the combination of the HEIGHT1 and HEIGHT2 channels in the settings. (127 p. 58)








Example connection when using two sets of Dolby Atmos Enabled speakers



• Set "Height" - "Dolby Sp" to "4ch" in the menu when connecting in this configuration. (127 p. 208)



* You can change the combination of the HEIGHT1 and HEIGHT2 channels in the settings. (137 p. 58)







Playback

Tips

The combination of the HEIGHT1 and HEIGHT2 channels can be changed to the following patterns according to the speaker system being used. Set this from "Amp Assign" in the menu. (127 p. 205)

Combination of height speakers to be used		Connected terminals			
Number of height/ ceiling speakersNumber of DolbySpeakersSpeakers		Combination pattern	HEIGHT1 SPEAKER	HEIGHT2 PRE OUT	
		Front Height	Front Height	-	
		Top Front	Top Front	-	
2 speakers	None	Top Middle	Top Middle	-	
		Top Rear	Top Rear	-	
		Rear Height	Rear Height	-	
		Front Height & Top Middle	Front Height	Top Middle	
		Front Height & Top Rear	Front Height	Top Rear	
4	Nama	Front Height & Rear Height	Front Height	Rear Height	
4 speakers	None	Top Front & Top Rear	Top Front	Top Rear	
		Top Front & Rear Height	Top Front	Rear Height	
		Top Middle & Rear Height	Top Middle	Rear Height	
		Front Dolby	Front Dolby	-	
None	2 speakers	Surround Dolby	Surround Dolby	-	
		Back Dolby	Back Dolby	-	
		Front Dolby & Top Rear	Front Dolby	Top Rear	
		Front Dolby & Rear Height	Front Dolby	Rear Height	
0 an ackara	0 anaskara	Front Height & Surr. Dolby	Front Height	Surround Dolby	
2 speakers	2 speakers	Front Height & Back Dolby	Front Height	Back Dolby	
		Top Front & Surround Dolby	Top Front	Surround Dolby	
		Top Front & Back Dolby	Top Front	Back Dolby	
None	4 analysis	Front Dolby & Surround Dolby	Front Dolby	Surround Dolby	
NONE	4 speakers	Front Dolby & Back Dolby	Front Dolby	Back Dolby	



Rear panel

Remote



Contents


Playback

Appendix

Connecting 7.1-channel speakers: Bi-amp connection of front speakers


This system plays back 7.1-channels. You can use the bi-amp connection for front speakers. Bi-amp connection is a method to connect separate amplifiers to the tweeter terminal and woofer terminal of a speaker that supports bi-amplification. This connection enables back EMF (power returned without being output) from the woofer to flow into the tweeter without affecting the sound quality, producing a higher sound quality.

You can connect speakers for up to 9-channels for MAIN ZONE. When you connect speakers for 8 or more channels, the output speakers automatically switch according to the input signal and sound mode.



NOTE

 When making bi-amp connections, be sure to remove the short-circuiting plate or wire between the speaker's woofer and tweeter terminals.



* The height speakers, ceiling speakers and Dolby Atmos Enabled speakers can be connected to the HEIGHT1 speaker terminals. Set the speaker to be connected from "Height" - "Layout" in the menu. ((Pp. 209)



Rear panel

59

Remote







Connecting 7.1-channel speakers: Second pair of front speakers

This system enables switching playback between front speakers A and B as desired.

You can connect speakers for up to 9-channels for MAIN ZONE. When you connect speakers for 8 or more channels, the output speakers automatically switch according to the input signal and sound mode.





* The height speakers, ceiling speakers and Dolby Atmos Enabled speakers can be connected to the HEIGHT1 speaker terminals. Set the speaker to be connected from "Height" - "Layout" in the menu. ((Pp. 209)







Connecting multi-zone speakers

7.1-channel playback (MAIN ZONE) + 2-channel playback (ZONE2)

This type of configuration plays back 7.1-channels in MAIN ZONE and 2-channels in ZONE2.

You can connect speakers for up to 9-channels for MAIN ZONE. When you connect speakers for 8 or more channels, the output speakers automatically switch according to the input signal and sound mode.





* The height speakers, ceiling speakers and Dolby Atmos Enabled speakers can be connected to the HEIGHT1 speaker terminals. Set the speaker to be connected from "Height" - "Layout" in the menu. (() 100 p. 209)



61

Remote


Index






5.1-channel playback (bi-amp connection of front speakers: MAIN ZONE) + 2-channel playback (ZONE2)

This type of configuration plays back 5.1-channels in MAIN ZONE and 2-channels in ZONE2. You can use the bi-amp connection for front speakers in MAIN ZONE.












Connecting an external power amplifier

You can use this unit as a pre-amp by connecting an external power amplifier to the PRE OUT connectors. By adding a power amplifier to each channel, the realness of the sound can be further enhanced.

Select the terminal to use and connect the device.



• When using just one surround back speaker, connect it to the left channel (L) terminal.



63

Remote






Contents Connection	ns	Playback	Settings	\setminus	Tips	\bigvee	Appendix	
---------------------	----	----------	----------	-------------	------	-----------	----------	--

Connecting a TV

Connect a TV to this unit so that the input video is output to the TV. You can also enjoy audio from the TV on this unit.

How to connect a TV depends on the connectors and functions equipped on the TV.

ARC (Audio Return Channel) / eARC (Enhanced Audio Return Channel) function plays TV audio on this unit by sending the TV audio signal to this unit via HDMI cable.



"Connection 1 : TV equipped with an HDMI"Connection 2 : TV equipped with an HDMI"Connection 3 : TV equipped without
an HDMI connector" (IF p. 68)Return Channel) / eARC (Enhanced AudioReturn Channel) / eARC (Enhanced Audio Return
Channel)" (IF p. 65)Return Channel)" (IF p. 67)Channel)" (IF p. 67)






Front panel

Connection 1 : TV equipped with an HDMI connector and compatible with the ARC (Audio Return Channel) / eARC (Enhanced Audio Return Channel)

Use an HDMI cable to connect a TV that is compatible with the ARC / eARC function to this unit.

Set "HDMI Control" to "On" or "ARC" to "On" when using a TV that supports the ARC function. (12 p. 180)

Using an eARC function-compatible television enables audio playback from the speaker connected to this unit, regardless of "HDMI Control" and "ARC" settings in the menu.



- When using the ARC / eARC function, connect to the HDMI MONITOR 1 connector.
- eARC function settings may be required depending on the eARC function-compatible television you are using. Make sure eARC is set to on if this setting exists on your television. For more information, check your television's owner's manual.
- When an ARC and an eARC function-compatible televisions are connected, the eARC function-compatible television is prioritized.
- Use a "High Speed HDMI Cable with Ethernet" when using an ARC / eARC function-compatible television.






(Audio Return Channel) / eARC (Enhanced Audio Return Channel)

Use an HDMI cable to connect the TV to this unit.

To listen to audio from TV on this unit, use an optical cable to connect the TV to this unit.



Front panel






Connection 3 : TV equipped without an HDMI connector

Use a component video or a video cable to connect the TV to this unit.

To listen to audio from TV on this unit, use an optical cable to connect the TV to this unit.







Tips

Connecting a playback device

This unit is equipped with three types of video input connectors (HDMI, component video and composite video) and three types of audio input connectors (HDMI, digital audio and audio).

Select input connectors on this unit according to the connectors equipped on the device you want to connect.

If the device connected to this unit is equipped with an HDMI connector, it is recommended to use HDMI connections.

In the HDMI connection, audio and video signals can be transmitted through a single HDMI cable.

- "Connecting a set-top box (Satellite tuner/cable TV)" (p. 70)
- "Connecting a DVD player or Blu-ray Disc player" (1 p. 71)
- "Connecting a video camcorder or game console" (p. 72)
- "Connecting a turntable" (2 p. 73)
- "Connecting a device with a multi-channel output connector" (p. 74)

- Connect devices to this unit as indicated by the input sources printed on the audio/video input connectors of this unit.
- The source that is assigned to the HDMI IN, DIGITAL AUDIO IN, COMPONENT VIDEO IN, VIDEO IN and AUDIO IN connectors can be changed. See "Input Assign" on how to change the input source assigned to the input connectors. (127 p. 190)
- To play back audio signals that are input to this unit on a TV connected via HDMI, set in the menu "HDMI Audio Out" to "TV". (127 p. 178)
- To enjoy content that is copyright protected by HDCP 2.2, use a playback device and TV compatible with HDCP 2.2 only.






Connecting a set-top box (Satellite tuner/cable TV)

This explanation uses the connection with a satellite tuner/cable TV STB as an example.

Select the input connectors on this unit to match the connectors on the device that you want to connect to.












Connecting a DVD player or Blu-ray Disc player

This explanation uses the connection with a DVD player or Blu-ray Disc player as an example.


Select the input connectors on this unit to match the connectors on the device that you want to connect to.





Connecting a video camcorder or game console

This explanation uses the connection with a video camcorders as an example. Connect a playback device to this unit, such as a video camcorder or game console.










Connecting a turntable

This unit is compatible with turntables equipped with a moving magnet (MM) phono cartridge. When you connect to a turntable with a low output moving coil (MC) cartridge, use a commercially available MC head amp or a step-up transformer.


If you set this unit's input source to "Phono" and you accidentally increase the volume without having a turntable connected, you may hear a hum noise from the speakers.



	Contents	\checkmark	Connections		Playback	\bigvee	Settings	\bigvee	Tips	\bigvee	Appendix	\backslash
--	----------	--------------	-------------	--	----------	-----------	----------	-----------	------	-----------	----------	--------------

Connecting a device with a multi-channel output connector

You can connect this unit to an external device fitted with multi-channel sound audio output connectors to enjoy music and video. To play analog signals input from 7.1CH IN connectors, set "Input Mode" to "7.1CH IN". (127 p. 193)










Connecting a USB memory device to the USB port

For operating instructions see "Playing a USB memory device" (p. 86).



Ó

• Marantz does not guarantee that all USB memory devices will operate or receive power. When using a portable USB hard disk drive (HDD) which came with an AC adapter, use that device's supplied AC adapter.

NOTE

- USB memory devices will not work via a USB hub.
- It is not possible to use this unit by connecting the unit's USB port to a PC via a USB cable.
- Do not use an extension cable when connecting a USB memory device. This may cause radio interference with other devices.


Connecting an FM/AM antenna

Connect the antenna, tune in to a broadcast and then move the antenna to the location where there is least noise. Then use tape, etc. to fix the antenna in this location. ("Listening to FM/AM broadcasts" (P p. 94))

 If you are unable to receive a good broadcast signal, we recommend installing an outdoor antenna. For details, inquire at the retail store where you purchased the unit.

NOTE

Make sure the AM loop antenna lead terminals do not touch metal parts of the panel.



Front panel



Using the AM loop antenna

Suspending on a wall

Suspend directly on a wall without assembling.



Nail, tack, etc.


Standing alone


Use the procedure shown above to assemble.

When assembling, refer to "AM loop antenna assembly".

AM loop antenna assembly

- **1** Put the stand section through the bottom of the loop antenna from the rear and bend it forward.
- 2 Insert the projecting part into the square hole in the stand.













Connecting to a home network (LAN)


This unit can connect to a network using a wired LAN or wireless LAN. You can connect this unit to your home network (LAN) to enable various types of playback and operations as described below.

- Playback of network audio such as Internet Radio and from your media server(s)
- · Playback of streaming music services
- Using the Apple AirPlay function
- · Operation on this unit via the network
- · Operation with the HEOS wireless multi-room sound system
- Firmware Update

For connections to the Internet, contact an ISP (Internet Service Provider) or a computer shop.

Wired LAN

To make connections via wired LAN, use a LAN cable to connect the router to this unit as shown in the figure below.




Front panel



Wireless LAN

When connecting to the network via wireless LAN, connect the external antennas for Bluetooth/wireless connectivity connection to the rear panel and stand them upright.

See "Wi-Fi Setup" on how to connect to a wireless LAN router. ($(\underline{\mathbb{CP}\ p.\ 222})$



- When using this unit, we recommend you use a router equipped with the following functions:
 - Built-in DHCP server This function automatically assigns IP addresses on the LAN.
 - Built-in 100BASE-TX switch When connecting multiple devices, we recommend a switching hub with a speed of 100 Mbps or greater.
- Only use a shielded STP or ScTP LAN cable (readily available at electronics stores). (CAT-5 or greater recommended)
- The normal shielded-type LAN cable is recommended. If a flat-type cable or unshielded-type cable is used, other devices could be affected by noise.
- When using this unit connected to a network with no DHCP function, configure the IP address, etc. in "Network". (Pp. 221)

NOTE

- The types of routers that can be used depend on the ISP. Contact your ISP or a computer shop for details.
- This unit is not compatible with PPPoE. A PPPoE compatible router is required if your contracted line is not set using PPPoE.
- Do not connect a NETWORK connector directly to the LAN port / Ethernet connector on your computer.
- Various online services may be discontinued without prior notice.

Front panel






Connecting an external control device

REMOTE CONTROL jacks

Performing operations by RC on this unit without visual contact

You can connect an external IR receiver to the REMOTE CONTROL connectors to perform operations on this unit with the supplied remote control unit without visual contact. This might be necessary if the unit is hidden in a cupboard or corner, so you can't directly point with the remote control unit to the device.

To do this, disable the remote control signal receiving function ("Remote lock function" ((2) <u>p. 152</u>)).




NOTE

• When the remote control signal receiving function is disabled, you can not perform operations with the remote control unit.

Remotely connecting Marantz devices

When you are using a Marantz device other than this unit that supports remote connection, you can transmit remote control signals just by connecting the device to the REMOTE CONTROL IN/OUT connector with a monaural cable.

Set the remote control switch located on the rear panel of the connected audio component to "EXTERNAL" or "EXT." to use this feature.






Rear panel







When a device with DC IN jack is connected, the connected device's power on/standby can be controlled through linked operation to this unit. The DC OUT jack outputs a maximum 12 V DC/150 mA electrical signal.




NOTE

- Use a monaural mini-plug cable for connecting the DC OUT jack. Do not use a stereo mini-plug cable.
- If the permissible trigger input level for the connected device is larger than 12 V DC/150 mA, or has shorted, the DC OUT jack cannot be used. In this case, turn off the power to the unit, and disconnect it.



Connecting the power cord

After completing all the connections, insert the power plug into the power outlet.





Contents

Contents

Basic operation

Turning the power on	84
Selecting the input source	84
Adjusting the volume	85
Turning off the sound temporarily (Muting)	85
Selecting a sound mode	130

Playback a device

Playing a DVD player/Blu-ray Disc player	85
Playing a USB memory device	86
Listening to music on a Bluetooth device	90
Listening to FM/AM broadcasts	94

Playback network audio/service

Listening to Internet Radio	102
Playing back files stored on a PC or NAS	104
Getting the HEOS App	108
AirPlay function	117
Spotify Connect function	121

Tips

Convenience functions

Convenience functions	122
HDMI Control function	142
Smart Menu function	143
Sleep timer function	145
Smart select function	147
Panel lock function	150
Remote lock function	152

Other functions


Web control function	153
Playback in ZONE2 (Another room)	155







Basic operation



Turning the power on

Press POWER 🕁 to turn on power to the unit.

• You can press the input source select button when the unit is in standby mode to turn on the power.

- You can also switch the power to standby by pressing $\ensuremath{\textcircled{}}$ on the main unit.

Selecting the input source

Press the input source select button to be played back. The desired input source can be selected directly.



 You can also select the input source by turning INPUT SELECTOR on the main unit.

Front panel



Adjusting the volume

- Use VOLUME **I** to adjust the volume.
- The variable range differs according to the input signal and channel level setting.
- You can also adjust the master volume by turning VOLUME on the main unit.

Turning off the sound temporarily (Muting)

Press MUTE **4**X.

- "MUTE" appears on the display.
- ◀× appears on the TV screen.

- The sound is reduced to the level set at "Mute Level" in the menu. (p. 170)
- To cancel mute, either adjust the sound volume or press MUTE dX again.

Playback a DVD player/Blu-ray Disc player

Tips

The following describes the procedure for playing DVD player/Blu-ray Disc player.


Prepare for playback.

Turn on the power of the TV, subwoofer and player.
 Change the TV input to the input of this unit.

- 2 Press POWER (b) to turn on power to the unit.
- **3** Press DVD or Blu-ray to switch an input source for a player used for playback.
- **4** Play the DVD player or Blu-ray Disc player.
- Surround playback (P <u>p. 130</u>)

Front panel





Playing files stored on USB memory devices

- **1** Insert a FAT32 formatted USB memory device into the USB port.
- **2** Press USB to switch the input source to "USB".
- **3** Select the name of this unit.

4 Browse the music on your USB memory device and select something to play.

Tips

Ó

• When you select something to play you will be asked how you want to queue up your music.

Play Now:	Inserts the item into the queue after the currently playing track and plays the selected item immediately.
Play Now & Replace Queue:	Clears the queue and plays the selected item immediately.
Play Next:	Inserts the item into the queue after the current song and plays it when the current song ends.
Add to End of Queue:	Adds the item to the end of the queue.

Naure 01	
Play Now	1
Play Now & Replace Queue	rtists
Play Next	rtists
Add to End of Queue	rtists
Cancel	rtists
Nature Variou	

Front panel





Contents Connections Playback Settings Tips

Playback starts.



Operation buttons	Function
►/II	Playback / Pause
	Skip to previous track / Skip to next track
CH/PAGE ▲ ▼	Switch to the previous page/next page in the list display

When an MP3 music file includes album art data, the album art can be displayed while playing the file.

NOTE

 Note that Marantz will accept no responsibility whatsoever for any problems arising with the data on a USB memory device when using this unit in conjunction with the USB memory device.

Front panel



88





Appendix

Operations accessible through the option menu

- "Adjusting the volume of each channel to match the input source (Channel Level Adjust)" ($\fbox{p. 125}$)
- "Adjusting the tone (Tone)" (main p. 126)
- "Displaying your desired video during audio playback (Video Select)" (27 p. 127)
- "Playing the same music in all zones (All Zone Stereo)" (127 p. 129)










Playback

Settings

Listening to music on a Bluetooth device



Music files stored on Bluetooth devices such as smartphones, digital music players, etc. can be enjoyed on this unit by pairing and connecting this unit with the Bluetooth device.

Communication is possible up to a range of about 98.4 ft/30 m.

NOTE

 To play back music from a Bluetooth device, the Bluetooth device needs to support the A2DP profile.





Playing music from Bluetooth device

In order to enjoy music from a Bluetooth device on this unit, the Bluetooth device must first be paired with this unit.

Once the Bluetooth device has been paired, it does not need to be paired again.

Prepare for playback.

- Connect the supplied external antennas for Bluetooth/wireless connectivity to the Bluetooth/wireless LAN antenna connectors on the rear panel. (<u>Pp. 23</u>)
- (2) Press POWER (1) to turn on power to the unit.

2 Press Bluetooth.

When using for the first time, the unit will go into the pairing mode automatically and "Pairing..." will appear on the display of the unit.

3 Activate the Bluetooth settings on your mobile device.

4 Select this unit when its name appears in the list of devices displayed on the screen of the Bluetooth device.

Tips

Connect to the Bluetooth device while "Pairing" is being displayed on the display of the unit.

Perform the connection with the Bluetooth device close to the unit (about 3.3 ft/1 m).

5 Play music using any app on your Bluetooth device.

- The Bluetooth device can also be operated with the remote control of this unit.
- The next time the Bluetooth button is pressed on the remote control unit, this unit automatically connects to the last Bluetooth device that was connected.

Operation buttons	Function		
►/II	Playback / Pause		
	Skip to previous track / Skip to next track		

(





[•] Press STATUS on this unit during playback to switch the display between Title name, Artist name, Album name, etc.

Pairing with other Bluetooth devices

Pair a Bluetooth device with this unit.

- Activate the Bluetooth settings on your mobile device.
- **2** Press and hold Bluetooth on the remote control unit for at least 3 seconds.

This unit will go into the pairing mode.

3 Select this unit when its name appears in the list of devices displayed on the screen of the Bluetooth device.

- This unit can be paired with a maximum of 8 Bluetooth devices. When a 9th Bluetooth device is paired, it will be registered in place of the oldest registered device.
- You can also enter pairing mode by pressing the OPTION button when the Bluetooth playback screen is displayed and selecting "Pairing Mode" from the displayed option menu.

NOTE

- To operate the Bluetooth device with the remote control of this unit, the Bluetooth device needs to support the AVRCP profile.
- The remote control of this unit is not guaranteed to work with all Bluetooth devices.
- Depending on the type of Bluetooth device, this unit outputs audio that is coupled to the volume setting on the Bluetooth device.

Operations accessible through the option menu

- "Pairing with other Bluetooth devices" (12 p. 92)
- "Adjusting the volume of each channel to match the input source (Channel Level Adjust)" (127 p. 125)
- "Adjusting the tone (Tone)" (2 p. 126)
- "Displaying your desired video during audio playback (Video Select)" (<u>P. 127</u>)
- "Playing the same music in all zones (All Zone Stereo)" (p. 129)

Front panel





Reconnecting to this unit from a Bluetooth device

After pairing is completed, the Bluetooth device can be connected without performing any operations on this unit.


This operation also needs to be performed when switching the Bluetooth device for playback.

- **1** If a Bluetooth device is currently connected, deactivate the Bluetooth setting of that device to disconnect it.
- 2 Activate the Bluetooth setting of the Bluetooth device to be connected.
- **3** Select this unit from the Bluetooth device list on your Bluetooth device.
- **4** Play music using any app on your Bluetooth device.

- The screen automatically switches to the "Bluetooth" playback screen if a Bluetooth device is connected while the power of this unit is on.
- When the "Network Control" setting of this unit is set to "Always On" and a Bluetooth device is connected with the unit in the standby state, the power of the unit will be turned on automatically. (127 p. 225)

Front panel





Listening to FM/AM broadcasts

- Connect the antenna. ("Connecting an FM/AM antenna" (pp. 76))
- **2** Press TUNER to switch the input source to "Tuner".



9210MHz

[TV screen]

Use $\triangleleft \triangleright$ to select "FM" or "AM", then press ENTER.

Tips

FM:	When listening to an FM broadcast.
AM:	When listening to an AM broadcast.

6 Press TUNE + or TUNE - to select the station you want listen to.

Scanning is performed until it finds an available radio station. When it finds a radio station, it stops the scan automatically and tunes in.

5

• The modes for receiving FM broadcasts consists of "Auto" mode that automatically searches available broadcast stations and "Manual" mode that lets you tune in using buttons to change the frequency. The default setting is "Auto". You can also use "Direct Tune" to tune in by entering the frequency directly.

In "Auto" mode, you cannot tune in to radio stations if the reception is not good. If this is the case, then use the "Manual" mode or "Direct Tune" mode to tune in.

Operation buttons	Function
TUNE +, -	Selects the radio station (up/down)
CH/PAGE	Selects preset radio stations
$\Delta \nabla$	Selects the radio station (up/down)
$\triangleleft \triangleright$	Selects preset radio stations

3 Press OPTION.

The option menu screen is displayed.

4 Use $\Delta \nabla$ to select "FM/AM", then press ENTER.

This displays the reception band input screen.







Contents

Operations accessible through the option menu

- "Tuning in by entering the frequency (Direct Tune)" (p. 96)
- "Changing the tune mode (Tune Mode)" (2 p. 97)
- "Tuning in to stations and presetting them automatically (Auto Preset Memory)" ($\underline{\mathbb{CP}}$ <u>p. 97</u>)
- "Presetting the current broadcast station (Preset Memory)" (Pp. 98)
- "Specify a name for the preset broadcast station (Preset Name)" (12 p. 99)
- "Skipping preset broadcast stations (Preset Skip)" (12 p. 100)
- "Adjusting the volume of each channel to match the input source (Channel Level Adjust)" ($\underline{rr} p. 125$)
- "Adjusting the tone (Tone)" (m p. 126)
- "Displaying your desired video during audio playback (Video Select)" (<u>P. 127</u>)
- "Playing the same music in all zones (All Zone Stereo)" (p. 129)

Tuning in by entering the frequency (Direct Tune)

You can enter the receiving frequency directly to tune in.

- **Press OPTION when the input source is "Tuner".** The option menu screen is displayed.
- **3** Use $\Delta \nabla$ to select a number, then press \triangleright .
 - If ⊲ is pressed, the immediately preceding input is cancelled.
- **4** Repeat step 3 and enter the frequency of the radio station you want to hear.

5 When setting is completed, press ENTER.

The preset frequency is tuned in.

Changing the tune mode (Tune Mode)

You can change the mode for tuning into FM and AM broadcasts. If you cannot tune in automatically with "Auto" mode, change the mode to "Manual" and tune in manually.

1 Press OPTION when the input source is "Tuner".

The option menu screen is displayed.

- **2** Use $\Delta \nabla$ to select "Tune Mode", then press ENTER.
- **3** Use $\triangleleft \triangleright$ to select the tune mode, then press ENTER.

Auto:	Automatically search for and tune to a receivable radio station.
Manual:	Manually change the frequency one step at a time each time the button is pressed.

Tuning in to stations and presetting them automatically (Auto Preset Memory)

A maximum of 56 radio stations can be automatically preset.

- **1 Press OPTION when the input source is "Tuner".** The option menu screen is displayed.

3 Press ENTER.

The unit starts to tune in to radio stations automatically and preset them.

• When presetting is completed, "Completed" is displayed for about 5 seconds and the option menu screen turns off.

• The preset memory is overwritten.



Settings

Presetting the current broadcast station (Preset Memory)

Your favorite broadcast stations can be preset so that you can tune them in easily.

Up to 56 stations can be preset.

- Tune in the broadcast station you want to preset. ("Listening to FM/AM broadcasts" (<u>P. 95</u>))
- 2 Press OPTION.

The option menu screen is displayed.

- 3 Use △▽ to select "Preset Memory", then press ENTER. The list of already preset channels is displayed.
- 4 Use $\Delta \nabla$ to select the channel you want to preset, then press ENTER.

The current broadcast station that is preset.

• To preset other stations, repeat steps 1 to 4.

Channel	Default settings
1 – 8	92.10 / 92.30 / 92.50 / 92.70 / 93.10 / 93.50 / 93.70 / 94.10 MHz
9 – 16	94.30 / 94.50 / 94.70 / 94.90 / 95.10 / 95.30 / 95.50 / 95.70 MHz
17 – 24	98.10 / 98.30 / 98.50 / 98.70 / 98.90 / 99.10 / 100.10 / 100.30 MHz
25 – 32	100.50 / 100.70 / 100.90 / 101.10 / 101.30 / 101.50 / 101.70 / 101.90 MHz
33 – 40	103.10 / 103.30 / 103.50 / 103.70 / 103.90 / 104.10 / 104.30 / 104.50 MHz
41 – 48	104.70 / 104.90 / 105.10 / 105.30 / 105.50 / 105.70 / 105.90 / 106.10 MHz
49 – 56	106.30 / 106.50 / 106.70 / 106.90 / 107.10 / 107.30 / 107.50 / 107.90 MHz

Listening to preset stations

1 Use CH/PAGE ▲▼ to select the desired preset channel.

6

 You can also select preset broadcast stations by pressing TUNER PRESET CH + or TUNER PRESET CH – on the main unit.







5

Specify a name for the preset broadcast station (Preset Name)

You can set the name to the preset broadcast station or change it. Up to 8 characters can be input.

- **1** Press OPTION when the input source is "Tuner". The option menu screen is displayed.
- 2 Use △▽ to select "Preset Name", then press ENTER. The "Preset Name" screen is displayed.
- **3** Use $\triangleleft \triangleright$ to select the group of the broadcast station you want to name.
- 4 Use $\Delta \nabla$ to select the broadcast station you want to name, then press ENTER.

Use $\Delta \nabla$ to select a name label, then press ENTER.

The screen that lets you edit the Preset Name is displayed.

- If you select "Set Defaults", then the unit returns to displaying the frequency.
- 6 Enter the characters, then press "OK".
- **7** Press OPTION to return to the previous screen.







Skipping preset broadcast stations (Preset Skip)

Perform auto preset memory to save all the broadcasting stations that can be received in the memory. Selecting a broadcast station becomes easier by skipping unnecessary memories.

- **1** Press OPTION when the input source is "Tuner". The option menu screen is displayed.
- $\label{eq:linear} 2 \quad \text{Use } \Delta \nabla \text{ to select "Preset Skip", then press ENTER.}$

The "Preset Skip" screen is displayed.

3 D To set the stations you want to skip by groups

- () Use $\triangleleft \triangleright$ to select the group of broadcast stations you want to skip.
- ② Press △ to select "Set No.* * to Skip", then press ENTER. Skip all the broadcast stations that are included in the selected group "*-*".
 - (* is the selected group number.)

To set the stations you want to skip by stations

- Use < ▷ to select the group of broadcast stations you want to skip.
- (2) Use $\Delta \nabla$ to select the broadcast station you want to skip.
- (3) Use $\triangleleft \triangleright$ to select "Skip".

The station you selected is not displayed.

4 Press OPTION to return to the previous screen.







- 1 While the "Preset Skip" screen is displayed, use ⊲ ▷ to select a group containing a broadcast station to cancel the skip for.
- $\label{eq:loss_loss} 2 \quad \text{Use } \triangle \nabla \text{ to select a broadcast station to cancel the skip} \\ \text{for.}$
- **3** Use $\triangleleft \triangleright$ to select "On".

The skip is cancelled.

NOTE


• "Preset Skip" cannot be cancelled for groups.











Listening to Internet Radio

Press INTERNET RADIO.

 You can also press ^t
 (HEOS Music). Use △∇ to select "TuneIn Internet Radio", then press ENTER.

2 Select the station you want to play.

Operation buttons	Function
►/II*	Playback / Pause
*	Skip to previous track / Skip to next track
CH/PAGE ▲ ▼	Switch to the previous page/next page in the list display

* Enabled when playing Podcasts.

• The display switches between track title and radio station name etc. each time the main unit's STATUS is pressed.


NOTE

• The radio station database service may be suspended or be otherwise unavailable without notice.

Operations accessible through the option menu

- "Adding to HEOS Favorites" (
 <u>p. 123</u>)
- "Adjusting the volume of each channel to match the input source (Channel Level Adjust)" (127 p. 125)
- "Adjusting the tone (Tone)" (2 p. 126)
- "Displaying your desired video during audio playback (Video Select)" (<u>P. 127</u>)
- "Playing the same music in all zones (All Zone Stereo)" (
 p. 129)

Front panel



Playing back files stored on a PC or NAS

Use this procedure to play music files or playlists stored on DLNA files servers on your local network.

Press 🕸 (HEOS Music).

- 2
- Use $\Delta \nabla$ to select "Music Servers", then press ENTER.



3 Select the name of your networked PC or NAS (Network Attached Storage) server.

4 Browse the music on your PC/NAS and select something to play.

Tips

• When you select something to play you will be asked how you want to queue up your music.

Play Now:	Inserts the item into the queue after the currently playing track and plays the selected item immediately.
Play Now & Replace Queue:	Clears the queue and plays the selected item immediately.
Play Next:	Inserts the item into the queue after the current song and plays it when the current song ends.
Add to End of Queue:	Adds the item to the end of the queue.





Playback starts.



Operation buttons	Function
►/II	Playback / Pause
	Skip to previous track / Skip to next track
CH/PAGE ▲ ▼	Switch to the previous page/next page in the list display

- The display switches between track title, artist name, and album title each time the main unit's STATUS is pressed.
- When a WMA (Windows Media Audio), MP3 or MPEG-4 AAC file includes album art data, the album art can be displayed while the music files are playing.
- If you use Ver.11 or later of Windows Media Player, the album art for WMA files can be displayed.

NOTE

- When playing back music files with your PC or NAS connected through wireless LAN, audio may be interrupted depending on your wireless LAN environment. In this case, connect using a wired LAN.
- The order in which the tracks/files are displayed depends on the server specifications. If the tracks/files are not displayed in alphabetical order due to the server specifications, searching by the first letter may not work properly.

Front panel





Operations accessible through the option menu

- "Adjusting the volume of each channel to match the input source (Channel Level Adjust)" ($\fbox{p. 125}$)
- "Adjusting the tone (Tone)" (main p. 126)
- "Displaying your desired video during audio playback (Video Select)" (27 p. 127)
- "Playing the same music in all zones (All Zone Stereo)" (127 p. 129)











Getting the HEOS App

You can use many online music streaming services from the HEOS App. Depending upon your geographical location, there are several options to choose from.

Download the HEOS App for iOS or Android by searching App Store, Google Play store or Amazon Appstore for "HEOS".











Remote



Index

Appendix

Contents

Changing your HEOS Account

- Tap the "Music" tab.
- 2 Select the Settings icon in the upper left corner of the screen.

Tips

- 3 Select "HEOS Account".
- 4 Change your location, change your password, delete your account or sign out of your account.

HEOS Account

HEOS Accounts can be registered in "HEOS Account" (\bigcirc <u>p. 228</u>) in the menu of this unit or by tapping "Music" tab - "Settings" icon \bigodot in the HEOS App.

What is a HEOS Account?

A HEOS Account is master account or "keychain" for managing all of your HEOS music services with one single username and password.

Why do I need a HEOS Account?

With the HEOS Account you just have to enter your music services login names and passwords one time. This allows you to easily and quickly use multiple controller apps on different devices.

You just log into your HEOS Account on any device and you will have access to all of your associated music services, play history and custom playlists, even if you are at a friend's house listening to music on their HEOS system.

Signing up for a HEOS Account

You will be instructed to signup for a HEOS Account the first time you try to access any music service from the main "Music" menu of the HEOS App.

/

Appendix

Playing from streaming music services

A music service is an online music company that provides access to vast music collections via free and/or paid subscriptions. Depending upon your geographical location, there are several options to choose from.

Selecting a room/device

1 Tap the "Rooms" tab, and select "SR6013" if there are multiple HEOS devices.

• Tap the Pencil icon 2 at the top right to switch edit mode. You can change the displayed name.



Tips

Front panel







Selecting the music track or station from music sources

- Tap the "Music" tab and select a music source.

 - All music services displayed may not be available in your location.











Browse the music to play.

After selecting a music track or radio station the app will automatically change to the "Now Playing" screen.

2

• When you select a music track to play you will be asked how you want to queue up your music.

Play Now:	Inserts the item into the queue after the currently playing track and plays the selected item immediately.			
Play Now & Replace Queue:	Clears the queue and plays the selected item immediately.			
Play Next:	Inserts the item into the queue after the current song and plays it when the current song ends.			
Add to End of Queue:	Adds the item to the end of the queue.			

• When you select a radio station the following items are displayed.

 Play Now:
 Plays the selected item immediately.

Add to HEOS Favorites: Adds to HEOS Favorites.





Front panel





Contents

Settings

Tips

Appendix

Listening to the same music in multiple rooms

The HEOS system is a true multi-room audio system that automatically synchronizes audio playback between multiple HEOS devices so that the audio coming from different rooms is perfectly in sync and always sounds amazing! You can easily add up to 32 HEOS devices to your HEOS system. You can join or group up to 16 individual HEOS devices into a group of HEOS devices that function as if they were a single HEOS device.

Grouping rooms

- **1** Press and hold your finger on room that is not playing music.
- 2 Drag it into the room that is playing music (indicated by the red outline) and lift your finger.
- **3** The two rooms will be grouped together into a single device group and both rooms will be playing the same music in perfect sync.
- When audio from the device connected to this unit is played back in a group, only 2-channel PCM input from the HDMI, digital or analog terminals can be played back.









Settings Appendix Contents Connections Playback Tips Ungrouping rooms Rooms ß Rooms Drag one room into another to group them Drag one room into another to group them 1 Press and hold your finger on room that you want to Dining Dining remove from the group. Song Name 1 Song Name 1 2 Drag it out of the group and lift your finger. Living Song Name 2 Living Song Name 2 Living Kitchen Song Name 4 NOTE 2

1→

Kitchen Bedroom

5

Norma Planete

• You can not remove the first room that started playing the music before grouping.

Front panel









Bedroom

5

Now Playing


Tips

Appendix

Grouping all rooms (party mode)

You can easily group 16 rooms together into Party Mode by using a "pinch" gesture.

- Place two fingers on the screen over the list of rooms.
- **2** Quickly pinch your two fingers together and release.
- **3** All of your rooms will be joined together and begin playing the same music in perfect sync.












Tips

Appendix

Ungrouping all rooms

You can easily ungroup all of your rooms and exit Party Mode by using a "spread" gesture.

- **1** Place two fingers close together on the screen over list of rooms.
- **2** Quickly spread your two fingers apart from each other and release.
- **3** All of your rooms will be ungrouped.











AirPlay function


Music files stored on your iPhone, iPod touch, iPad or iTunes can be played on this unit via the network.

- Source input will be switched to "HEOS Music" when AirPlay playback is started.
- You can stop AirPlay playback by choosing other input source.
- To see song and artist names together, press STATUS on the main unit.
- For information about how to use iTunes, also see the Help for iTunes.
- The screen may differ depending on the OS and software versions.

This unit supports AirPlay 2.

Sync multiple AirPlay 2 compatible devices/speakers for simultaneous playback.

• This unit supports AirPlay 2 and requires iOS 11.4 or later.













Playing songs from your iPhone, iPod touch or iPad


If you update your "iPhone/iPod touch/iPad" to iOS 4.2.1 or later, you can stream music stored in your "iPhone/iPod touch/iPad" directly to this unit.

- **1** Connect your iPhone, iPod touch or iPad Wi-Fi to the same network as this unit.
 - For details, see your device's manual.

2 Play the song on your iPhone, iPod touch or iPad.

AirPlay icon is displayed on the iPhone, iPod touch or iPad screen.

3 Tap the AirPlay icon.



Select the speaker (devices) you want to use.

Playing iTunes music with this unit

Install iTunes 10, or later, on a Mac or Windows PC that is connected to the same network as this unit.

2 Turn this unit ON.


Set "Network Control" to "Always On" for this unit. (m p. 225)

NOTE

- When "Network Control" is set to "Always On", the unit consumes more standby power.
- 3

Δ

Start iTunes and click the AirPlay icon to select the main unit.



Choose a song and click play in iTunes.

The music will stream to this unit.









NOTE

• In playback using the AirPlay function, the sound is output at the iPhone, iPod touch, iPad or iTunes volume setting level.

You should turn down the iPhone, iPod touch, iPad or iTunes volume prior to playback and then adjust it to a suitable level.

Perform iTunes playback operations with the remote control unit of this unit

With this unit's remote control unit, you can perform iTunes song play, pause, and auto search (cue) operations.

- Select the "Edit" "Preferences..." in the iTunes menu.
- **2** Select "Devices" in the iTunes setting window.
- **3** Check "Allow iTunes audio control from remote speakers", and then click "OK".

• This does not need to be set if using version 12 or later of iTunes.







Play a song from your iPhone, iPod touch or iPad on multiple synced devices (AirPlay 2)

Songs from an iPhone, iPod touch or iPad operating iOS 11.4 or later can be synced with multiple AirPlay 2 supported devices for simultaneous playback.

Play the song on your iPhone, iPod touch or iPad.

AirPlay icon is displayed on the iPhone, iPod touch or iPad screen.



2 Tap the AirPlay icon.

Displays a list of devices/speakers that can be played back on the same network.

• A circle is displayed to the right of AirPlay 2 compatible devices.



3 Tap the devices/speakers you want to use.

- Multiple AirPlay 2 compatible devices can be selected.
- Volume can be adjusted for each device individually or for all synced devices simultaneously.

	iPhone	
ò	Marantz xxxxxxx	_ 🖉
ò	Speakers	_ 🖉
		- 🔊









Spotify Connect function

Spotify is the world's most popular streaming service. If you subscribe to Spotify Premium, you can control your new speaker with your phone or tablet. Because Spotify is built-in to your speaker, you can still take calls or use other apps - the music never stops.

For information on how to set up and use Spotify Connect please visit www.spotify.com/connect

Spotify server

Playing Spotify music with this unit


Download the "Spotify App" onto your Android or iOS device beforehand. To play a Spotify track in this unit, you need to register in the Spotify premium account first.

- Connect the Wi-Fi settings of the iOS or Android device in the same network as this unit.
- **2** Launch the Spotify App.
- **3** Play back the Spotify track.
- 4 Tap the Spotify icon 🗐 to select the unit. The music will stream to this unit.









Adding to HEOS Favorites

While content is playing, press OPTION.

The option menu screen is displayed.

Playing back HEOS Favorites

- Press 🕆 (HEOS Music).
- **2** Use $\Delta \nabla$ to select "HEOS Favorites", then press ENTER.



3 Browse the content and select something to play.



- 1 While the HEOS Favorites content list is displayed, use △▽ to select the item you want to remove from HEOS Favorites, then press OPTION.
- $\label{eq:loss_loss} 2 \quad \text{Use } \Delta \nabla \text{ to select "Remove from HEOS Favorites", then} \\ \text{press ENTER.} \\$







Adjusting the volume of each channel to match the input source (Channel Level Adjust)

The volume of each channel can be changed while listening to music. You can set this for each input source.

Press OPTION.

An option menu screen is displayed.

- When the input source is "HEOS Music", an option menu for online music is displayed. Select "AVR Options...", then press ENTER.
- 2 Use $\Delta \nabla$ to select "Channel Level Adjust", then press ENTER.

The "Channel Level Adjust" screen is displayed.

3 Use $\Delta \nabla$ to select the channel that you wish to adjust.

4 Use $\triangleleft \triangleright$ to adjust the volume.

-12.0 dB - +12.0 dB (Default: 0.0 dB)

5 Use $\Delta \nabla \triangleleft \triangleright$ to select "Exit", then press ENTER.

Tips

- Select "Reset" and press ENTER if you want to restore the adjustment values of the various channels to "0.0 dB" (Default).
- Headphone volume can be adjusted when a headphone is connected.
- "Channel Level Adjust" settings are stored for each input source.
- You can only set this for speakers that output audio. In addition, you cannot set this when in the menu "HDMI Audio Out" is set to "TV". (Cp. <u>1.78</u>)





Adjusting the tone (Tone)

Adjusts the tonal quality of the sound.

Press OPTION.

An option menu screen is displayed.

 When the input source is "HEOS Music", an option menu for online music is displayed. Select "AVR Options...", then press ENTER.

2 Use $\Delta \nabla$ to select "Tone", then press ENTER.

The "Tone" screen is displayed.

3 Use $\triangleleft \triangleright$ to set the tone control function to on/off.

On:	Allow tone adjustment (bass, treble).
Off (Default):	Playback without tone adjustment.

4 Select "On" in step 3 and press ∇ to select the sound range to be adjusted.

Tips

Bass:	Adjust bass.
Treble:	Adjust treble.

5 Use $\triangleleft \triangleright$ to adjust the tone, then press ENTER.

-6 dB - +6 dB (Default : 0 dB)

- "Tone" settings are stored for each input source.
- This cannot be set when the sound mode is set to "Direct" or "Pure Direct".
- This item cannot be set when "Dynamic EQ" is set to "On". (172)
- You cannot set this when no audio signal is input or in the menu "HDMI Audio Out" is set to "TV". (<u>P. 178</u>)
- This cannot be set when the input mode is set to "7.1CH IN".

Front panel





Displaying your desired video during audio playback (Video Select)

This unit can display video from a different source on TV during audio playback. You can set this for each input source.

Supported input sources: CD* / Tuner / HEOS Music / Phono

* This cannot be set when any of the HDMI, component video or video connectors are assigned.

Press OPTION.

An option menu screen is displayed.

- When the input source is "HEOS Music", an option menu for online music is displayed. Select "AVR Options...", then press ENTER.
- 2 Use △▽ to select "Video Select", then press ENTER. The "Video Select" screen is displayed.
- **3** Use $\triangleleft \triangleright$ to select the Video Select mode.

Off (Default):	Disable Video Select mode.
On:	Enable Video Select mode.

4 If you selected "On" in step 3, press ∇ and select "Source".

Tips

5 Use $\triangleleft \triangleright$ to select the input source for video you want to play back, then press ENTER.

• "Video Select" settings are stored for each input source.









Tips

Adjusting the picture quality for your viewing environment (Picture Mode)

Supported input sources : CBL/SAT / DVD / Blu-ray / Game / AUX1 / AUX2 / Media Player / CD* / TV Audio*

* You can set the picture mode when an HDMI, component video or video connector is assigned.

Press OPTION.

An option menu screen is displayed.

2 Use △▽ to select "Picture Mode", then press ENTER. The "Picture Mode" screen is displayed.

3 Use $\triangleleft \triangleright$ to select the picture mode.

Off (Default):	No picture quality adjustment is done with this unit.
Standard:	The standard mode suited for most living room viewing environments.
Movie:	A mode suited for watching movies in a dark room such as a theater room.
Vivid:	A mode that makes graphic images for games, etc. brighter and more vivid.
Streaming:	A mode suited for low bit rate video sources.
ISF Day:	A mode suited for watching movies in a bright room during the day.
ISF Night:	A mode suited for watching movies in a dark room at night.
Custom:	Adjusts the picture quality manually.

4 Press ENTER.

• "Picture Mode" settings are stored for each input source.









Playing the same music in all zones (All Zone Stereo)

You can play back the music being played back in MAIN ZONE simultaneously in ZONE2 (another room).

It is useful when you want to enjoy the same music at the same time in multiple rooms during home party or when you want to play back the same BGM in the entire house.

Press OPTION.

An option menu screen is displayed.

 When the input source is "HEOS Music", an option menu for online music is displayed. Select "AVR Options...", then press ENTER.

2 Use $\Delta \nabla$ to select "All Zone Stereo", then press ENTER.

The "All Zone Stereo" screen is displayed.

3 Select "Start", then press ENTER.

The input source for ZONE2 is switched to the same input source as for MAIN ZONE, and playback starts in the All Zone Stereo mode.

Stopping the All Zone Stereo mode

During playback in All Zone Stereo mode, press OPTION.

An option menu screen is displayed.

 When the input source is "HEOS Music", an option menu for online music is displayed. Select "AVR Options...", then press ENTER.

2

- Use $\Delta \nabla$ to select "All Zone Stereo", then press ENTER.
- **3** Select "Stop", then press ENTER.

- The All Zone Stereo mode is canceled even when the power supply of the MAIN ZONE is turned off.
- In the All Zone Stereo mode, only the "Multi Ch Stereo" and "Stereo" sound modes can be selected.
- When "HDMI Audio Out" is set to "TV", the All Zone Stereo mode is not available. ((資一 p. 178)
- When "Input Mode" is set to other than "7.1CH IN", the All Zone Stereo mode is available. (<u>P. 193</u>)

Front panel


Rear panel

129

Remote



Selecting a sound mode



This unit allows you to enjoy various kinds of surround and stereo playback modes.

Disc formats such as Blu-ray Disc and DVD, as well as being supported by digital broadcasting, and even by streaming movies and music from internet-based subscription services.

Index

This unit supports playback of almost all of these multi-channel audio formats. It also supports surround playback of audio formats other than multi-channel audio such as 2-channel stereo audio.

<u>s</u>

130

Remote

• For audio formats recorded on a disc, see the disc jacket or label.

Selecting a sound mode

Press MOVIE, MUSIC or GAME to select a sound mode.

MOVIE :	Switches to the sound mode suitable for enjoying movies and TV programs.				
MUSIC :	Switches to the sound mode suitable for enjoying music.				
GAME :	Switches to the sound mode suitable for enjoying games.				

- The MOVIE, MUSIC, or GAME button memorizes the last sound mode selected for its button. Pressing MOVIE, MUSIC, or GAME recalls the same sound mode as the one selected at the previous playback.
- If the content played back does not support the previously selected sound mode, the most appropriate sound mode for the content is automatically selected.
- You can also press SOUND MODE on the main unit to switch the sound mode.

Switching the sound mode

- Press MOVIE, MUSIC or GAME to display a list of the sound modes that can be selected. Each time you press MOVIE, MUSIC or GAME, the sound mode changes.
- While the list is displayed, you can also use $\bigtriangleup \nabla$ to select a sound mode.
- Try out various sound modes and enjoy sound mode in your favorite mode.

 Please set the surround mode to Dolby Atmos/Surround when playing back Dolby Atmos encoded content. Dolby Atmos/Surround delivers the optimum playback experience from Blu-ray and streaming sources encoded with Dolby Atmos as well as channel based content. The default setting of this receiver is Dolby Atmos/ Surround.

[Example] When MOVIE is pressed







Direct playback

Sound recorded in source is played as is.

Press PURE to select "Direct". Direct playback begins.

- While DSD signals are played back, "DSD Direct" is displayed.
- This can also be set by pressing PURE DIRECT on the main unit.

Pure Direct playback

This mode is for playback with higher sound quality than in Direct playback mode.

This mode turns off the main unit display and analog video circuit. Doing so suppresses noise sources that affect sound quality.

Press PURE to select "Pure Direct".

The display goes dark, and Pure Direct playback begins. The PURE DIRECT indicator lights.

- In Direct and Pure Direct sound modes, the following items cannot be adjusted.
 - Tone (m<u>p. 126</u>)
 - M-DAX (@<u>p. 168</u>)
 - MultEQ[®] XT32 (mp. 171)
 - Dynamic EQ (main <u>p. 172</u>)
 - Dynamic Volume (12 <u>p. 173</u>)
 - Graphic EQ (2 <u>p. 174</u>)
- This can also be set by pressing PURE DIRECT on the main unit.

NOTE

- Video signals are only output when HDMI signals are played in the Pure Direct mode.
- When the Pure Direct mode has been selected, the display turns off after about 5 seconds.

Front panel







Auto surround playback

This mode detects the type of input digital signal, and automatically selects the corresponding mode for playback.

Perform stereo playback when the input signal is PCM. When the input signal is Dolby Digital or DTS, the music is played back according to the respective channel number.

Press PURE to select "Auto".

Auto surround playback begins.

• This can also be set by pressing PURE DIRECT on the main unit.







Settings

Description of sound mode types

Dolby sound mode

Sound mode type	Description	
Dolby Atmos*	Please select this mode to play back the contents encoded with Dolby Atmos. If you have selected a different sound mod previously, please select again this mode for Dolby Atmos content play back. It decodes Dolby Atmos content and its positioning data in real time and outputs audio from the appropriate speakers, creating natural audio images regardless o the speaker layout. Use ceiling speakers and Dolby Atmos Enabled speakers to realize a three-dimensional sound field.	
Dolby TrueHD	Please select this mode to play back the contents encoded with Dolby TrueHD at 192kHz/96kHz.	
Dolby Digital Plus	Please select this mode to play back the contents encoded with Dolby Digital Plus.	
Dolby Digital	Please select this mode to play back the contents encoded with Dolby Digital.	

* This mode is not supported in a 5.1-channel or less speaker configuration.









Remote

Sound mode type	Description
DTS Surround	This mode can be selected when playing sources recorded in DTS.
DTS ES Dscrt6.1*1	This mode is suitable for playing discs recorded in DTS-ES. The surround back channel added using the discrete method is played as an independent channel. Since all channels are independent, the 360-degree spacial expressiveness and sound localization are enhanced.
DTS ES Mtrx6.1*1	This mode is suitable for playing discs recorded in DTS-ES. The surround back channel added to the surround-left and surround-right channels by a matrix encoder at software recording time is decoded by this unit's matrix decoder and played from each channel (surround left, surround right, surround back).
DTS 96/24	This mode can be selected when playing sources recorded in DTS 96/24.
DTS-HD	This mode can be selected when playing sources recorded in DTS-HD.
DTS Express	This mode can be selected when playing sources recorded in DTS Express.
DTS:X	This mode can be selected when playing back content encoded with DTS:X. It decodes DTS:X content and its positioning data in real time and outputs audio from the appropriate speakers, creating natural audio images regardless of the speaker layout. Use height speakers to realize a three-dimensional sound field.
DTS Neural:X	This mode uses DTS Neural:X Upmixer to extend various sources to natural and realistic multi channels for playback. Use height speakers such as front height speakers to realize a three-dimensional sound field.
DTS Virtual:X*2*3	This mode uses DTS Virtual:X with virtual height and virtual surround processing to realize a three-dimensional sound field when the height speakers are not used.
def This are been all as a should be	

This can be selected when "Speaker Config." - "Surr. Back" is not set to "None". (1) p. 213) *1

*2 This can be selected when Height, Ceiling and Dolby Atmos Enabled speakers are not being used.

*3 It cannot be selected when the input signal is Dolby Digital, Dolby Digital Plus, Dolby TrueHD or Dolby Atmos.

Cound mode turns

DTS sound mode

Tips

Index

Settings

Description

	Contents	\checkmark	Connections	\bigvee	Playback		Settings	\bigvee	Tips	\bigvee	Appendix	\backslash
--	----------	--------------	-------------	-----------	----------	--	----------	-----------	------	-----------	----------	--------------

PCM multi-channel sound mode

Sound mode type Description	
Multi Ch In	This mode can be selected when playing multi-channel PCM/DSD sources.

Original sound mode

Sound mode type	Description			
Multi Ch Stereo	This mode is for enjoying stereo sound from all speakers.			
Virtual	This mode lets you experience an expansive surround sound effect when playing back through just the front (L/R) speakers only, and when listening with stereo headphones.			

Auto sound mode

Sound mode type	Description
	In this mode, the type of digital signal input, such as Dolby Digital, Dolby TrueHD, Dolby Digital Plus, Dolby Digital EX, Dolby Atmos, DTS, DTS-HD, DTS:X, DTS-ES, PCM (multi-channel) is detected, and the playback mode switches automatically to the corresponding mode. If the input signal is analog or PCM (2-channel), stereo playback is used. For Dolby Digital or DTS, the music is played back according to the respective channel number.



Contents	\bigvee	Connec
----------	-----------	--------

Stereo sound mode

Sound mode type	Description
Stereo	This mode plays 2-channel stereo audio with no additional surround sound processing.
	 Sound is output from the front left and right speakers, and subwoofer if connected.
	 When multi-channel signals are inputted, they are mixed down to 2-channel audio and are played back with no additional surround sound processing.

Direct sound mode

Sound mode type	Description
Direct	This mode plays back audio as recorded in the source.
Pure Direct	This mode plays back an even higher quality sound than the "Direct" mode. The following circuits are stopped in order to further improve sound quality. • Display indicator circuit of the main body (display will go off.)
	The analog video input/output switcher and processor is disabled.







Sound mode that can be selected for each input signal

- The following sound modes can be selected using the MOVIE, MUSIC and GAME buttons.
- Adjust the sound field effect with the menu "Surround Parameter" to enjoy surround sound the way you like it. (137 p. 165)

Input signal	Sound mode	MOVIE button	MUSIC button	GAME button
	Stereo	0	0	0
	Dolby Surround *2	0	0	0
2-channel *1	DTS Neural:X *2	0	0	0
	DTS Virtual:X *3*4	0	0	0
	Multi Ch Stereo *5	0	0	0
	Virtual	0	0	0

- *1 2-channel also includes analog input.
- *2 This mode plays back 2-channel sources in 5.1, 7.1, 9.1 or 11.1-channel playback. It cannot be selected when headphones are used or when the speaker configuration is front speakers only.
- *3 It cannot be selected when headphones are used, or when a speaker configuration with any height speakers is used.
- *4 It cannot be selected when the input signal is Dolby Digital, Dolby Digital Plus, Dolby TrueHD or Dolby Atmos.
- *5 This cannot be selected when headphones are used.





Input signal	Sound mode	MOVIE button	MUSIC button	GAME button
ulti-channel *6	Stereo	0	0	0
Dolby Digital	Dolby Digital *5	0	0	0
	Dolby Digital + Dolby Surround *5	0	0	0
	Dolby Digital + Neural:X *5	0	0	0
	Dolby Digital Plus *5	0	0	0
Dalby Digital Diva	Dolby Digital Plus + Dolby Surround *5*7	0	0	0
Dolby Digital Plus	Dolby Digital Plus + Neural:X *5	0	0	0
	Dolby Atmos *5*8	0	0	0
Dolby TrueHD	Dolby TrueHD *5	0	0	0
	Dolby TrueHD + Dolby Surround *5*7	0	0	0
	Dolby TrueHD + Neural:X *5	0	0	0
	Dolby Atmos *5*8	0	0	0
Dolby Atmos	Dolby Atmos *5	0	0	0
	DTS Surround *5	0	0	0
	DTS ES Dscrt 6.1 *5	0	0	0
	DTS ES Mtrx 6.1 *5	0	0	0
DTS	DTS 96/24 *5	0	0	0
	DTS + Dolby Surround *5	0	0	0
	DTS + Neural:X *5	0	0	0
	DTS + Virtual:X *3	0	0	0

*3 It cannot be selected when headphones are used, or when a speaker configuration with any height speakers is used.

*5 This cannot be selected when headphones are used.

*6 The sound mode that can be selected differs depending on the audio format of the input signal and the number of channels. For details, see "Types of input signals, and corresponding sound modes" (1) 2.284).

*7 This can be selected when the input signal does not contain Dolby Atmos.

*8 This can be selected when the input signal contains Dolby Atmos.



Rear panel



Remote





Contents	\bigvee	Connection
----------	-----------	------------

Input signal	Sound mode	MOVIE button	MUSIC button	GAME button
	DTS-HD HI RES *5	0	0	0
	DTS-HD MSTR *5	0	0	0
DTS-HD /	DTS Express *5	0	0	0
DTS Express	DTS-HD + Dolby Surround *5	0	0	0
	DTS-HD + Neural:X *5	0	0	0
	DTS-HD + Virtual:X *3	0	0	0
DTS:X	DTS:X *5	0	0	0
	DTS:X MSTR *5	0	0	0
	DTS:X + Virtual:X *3	0	0	0
	Multi Ch In *5	0	0	0
	Multi Ch In 7.1 *5	0	0	0
PCM multi-channel	Multi In + Dolby Surround *5	0	0	0
	Multi Ch In + Neural:X *5	0	0	0
	Multi In + Virtual:X *3	0	0	0
	Multi Ch Stereo *5	0	0	0
Multi-channel *6	Virtual	0	0	0

*3 It cannot be selected when headphones are used, or when a speaker configuration with any height speakers is used.

This cannot be selected when headphones are used. *5

*6 The sound mode that can be selected differs depending on the audio format of the input signal and the number of channels. For details, see "Types of input signals, and corresponding sound modes" (12 p. 284).

• Only "Stereo" and "Virtual" can be selected when headphones are used.












Views on the display



Shows a decoder to be used.

• In the case of the Dolby Digital Plus decoder, "DDDD+" is displayed.

2 Shows a decoder that creates sound output.

• "DDSon" indicates that the Dolby Surround decoder is being used.











HDMI Control function

A recent addition to the HDMI standard is CEC (Consumer Electronics Control), which allows control signals from one device to communicate with another device via the HDMI cable connection.

Setting procedure

- Enable the HDMI Control function of this unit. Set "HDMI Control" to "On". (<u>P. 180</u>)
- 2 Turn the power on for all the devices connected by HDMI cable.
- **3** Set the HDMI Control function for all devices connected by HDMI cable.
 - Please consult the operating instructions for the connected devices to check the settings.
 - Carry out steps 2 and 3 should any of the devices be unplugged.
- **4.** Switch the television input to the HDMI input connected to this unit.

- 5 Switch the input source of this unit to check that video from the player connected by HDMI is played back correctly.
- 6 When you turn the TV's power to standby, check that the power of this unit also goes to standby.

NOTE

- Some functions may not operate depending on the connected TV or player. Check the owner's manual of each device for details beforehand.
- The HDMI ZONE2 function is not compatible with the HDMI Control function.
- When the HDMI ZONE2 function is used with "HDMI Control" in the menu set to "On", the HDMI ZONE2 function may not fully work.



Smart Menu function

This function can be used to configure the settings of this unit, select an input source and set Tuner and Internet Radio stations using the TV remote control.

- Enable the HDMI Control function of this unit and the TV. (137 p. 180)
- 2 Set "Smart Menu" to "On" on this unit. (EP p. 182)

3 Select "AV Receiver" in a TV menu such as "Input"* or "Operate Connected HDMI Device"*.

The Smart Menu of this unit is displayed on the TV.

- This unit can be operated with the TV remote control while the Smart Menu is displayed.
- * The selection method differs depending on your TV.



Now Playing

Enjoy content from the input source currently selected on this unit.

Source

Switch the input of this unit.

If you select "HEOS Music" or "Tuner", you can continue to operate this unit using the TV remote control.

Sound Mode

Change the sound mode of this unit. You can select from the following three sound modes.

Surround:	Surround sound playback according to the input signal.
Stereo playback.	
Multi Ch Stereo: Multi-channel stereo playback.	

Front panel



Contents

Setup Menu

Displays a setup menu for configuring the settings of this unit.

Smart Select

Calls up the "Smart Select" items registered to this unit.

NOTE

- If the "HDMI Control" or "Smart Menu" settings have been changed, always reset the power to connected devices after the change.
- The Smart Menu function may not work properly depending on the specifications of your TV. In this case, set "Smart Menu" to "Off". (<u>P. 182</u>)

Front panel














You can have the power automatically switched to standby once a set time has elapsed. This is convenient for viewing and listening while going to sleep. The sleep timer function can be set for each zone.







Using the sleep timer

Press MAIN or ZONE2 to select the operating zone with the remote control.

The button for the selected zone is lit.

2 Press SLEEP and display the time you want to set.

- The sleep timer indicator lights up on the display and the sleep timer starts.
- You can set the sleep timer in the range from 10 to 120 minutes in steps of 10 minutes.

Checking the remaining time

Press SLEEP when the sleep timer is in operation. The remaining time appears on the display.

To cancel the sleep timer

Press SLEEP to select "Off". The sleep timer indicator on the display turns off.

• The sleep timer setting is canceled when the unit switches to standby mode.

NOTE

 The sleep timer function cannot turn off the power of devices connected to this unit. To turn off the power of those connected devices, set up sleep timers on the connected devices themselves.

Front panel





Contents Connections Playb	ack Settings Tips Appendix
Smart select function	
	Settings such as the input source, volume level and sound mode can be registered to the SMART SELECT 1 - 4 buttons.
	You can simply press one of the registered SMART SELECT buttons in subsequent playbacks to switch to the group of saved settings in a batch.

ZONE2 HIP PHONO (NTERNET RADIO ECO . V w TUNE+ SMART SELECT SMART SELECT 1 - 4

You can simply press one of the registered SMART SELECT buttons in subsequent playbacks to switch to the group of saved settings in a batch. By saving frequently used settings at the SMART SELECT 1-4 buttons, you will always be able to easily call up the same playback environment. The Smart Select function can be memorized for each zone.



Calling up the settings

Press MAIN or ZONE2 to select the operating zone with the remote control.

The button for the selected zone is lit.

2 Press SMART SELECT.

The Smart Select settings registered to the button you pressed are called up.

• The default settings for the input source are as shown below.

Button	Input source
SMART SELECT 1	CBL/SAT
SMART SELECT 2	Blu-ray
SMART SELECT 3	Media Player
SMART SELECT 4	HEOS Music

[MAIN ZONE] / [ZONE2]

 Volume is not registered to Smart Select in the factory default settings. See "Changing the settings" to register volume to Smart Select. (<u>Pp. 149</u>)





Changing the settings

Set the items below to the settings you want to register.

The following settings from (1 to (9) can be memorized for MAIN ZONE, and settings (1) and (2) can be memorized for ZONE2.

- ① Input source (2 <u>p. 84</u>)
- (2) Volume ((2) <u>p. 85</u>)
- (3) Sound mode ((2) <u>p. 130</u>)
- ④ Audyssey (Audyssey MultEQ[®] XT32, Audyssey Dynamic EQ[®], Audyssey Dynamic Volume[®], Audyssey LFC[™]) (127 p. 171)
- (5) " M-DAX " (☞ <u>p. 168</u>)
- (6) "Adjusting the volume of each channel to match the input source (Channel Level Adjust)" ((27 p. 125))
- (7) "Displaying your desired video during audio playback (Video Select)" (127)
- (a) "Adjusting the picture quality for your viewing environment (Picture Mode)" (2 p. 128)
- (9) " HDMI Video Output " (127 p. 183)

- Press and hold SMART SELECT while a radio station is being received is being played back with any of the following sources, the current radio station is memorized.
- Tuner / Internet Radio Station

2 Press MAIN or ZONE2 to select the operating zone with the remote control.

The button for the selected zone is lit.

3 Press and hold the desired SMART SELECT until "Smart* Memory" or "Z2 Smart* Memory" appear on the display.

The current settings will be memorized.

 $\boldsymbol{\ast}$ is displayed the number for the SMART SELECT button you pressed.

Changing the Smart Select Name

The MAIN ZONE Smart Select name displayed on the TV screen or display of this unit can be changed to a different name.

For the name change method, see "Smart Select Names" ($p \underline{p}$. 235).










Panel lock function

To prevent accidental operation of this unit, you can disable operation of the buttons on the front panel.



Disabling all key button operations

- **1** Press **(b)** while you press and hold M-DAX and DIMMER with the unit in standby mode.
- 2 Use TUNER PRESET CH + or TUNER PRESET CH to select "P/V LOCK On".
- **3** Press STATUS to enter the setting. All button operations except Φ are disabled.

Disabling all button operations except VOLUME

- **1** Press **(b)** while you press and hold M-DAX and DIMMER with the unit in standby mode.
- 2 Use TUNER PRESET CH + or TUNER PRESET CH to select "FP LOCK On".
- **3** Press STATUS to enter the setting.

All button operations except 0 and VOLUME are disabled.

Front panel







Canceling the Panel lock function

- **1** Press **(b)** while you press and hold M-DAX and DIMMER with the unit in standby mode.
- 2 Press TUNER PRESET CH + or TUNER PRESET CH to select "FP LOCK *Off".

(* The currently set mode.)

3 Press STATUS to enter the setting.

The Panel lock function is canceled.

Ó

• Even when the Panel lock function is set, you can operate the unit using the remote control unit.










Remote lock function

When connecting an IR receiver, enable the Remote lock function. When the function is enabled, you can not perform operations with the remote control unit.

By default, this function is disabled.



Disabling the sensor function of the remote control unit

- **1** Press **(b)** while you press and hold M-DAX and DIMMER with the unit in standby mode.
- 2 Use TUNER PRESET CH + or TUNER PRESET CH to select "RC LOCK On".
- **3** Press STATUS to enter the setting.

The infrared light receiving function is disabled.

Enabling the remote sensor function

- **1** Press (b) while you press and hold M-DAX and DIMMER with the unit in standby mode.
- 2 Press TUNER PRESET CH + or TUNER PRESET CH to select "RC LOCK *Off".

(* The currently set mode.)

3 Press STATUS to enter the setting.

Infrared light receiving function on the main unit is enabled.








Web control function

You can control this unit from a web control screen on a web browser.





- This unit and the PC or tablet need to be connected correctly to the network in order to use the web control function. (2 <u>p. 78</u>)
- Depending on the settings of your security-related software, you may not be able to access this unit from your PC. If this is the case, then change the settings of the security-related software.

Controlling the unit from a web control

- Switch the "Network Control" setting to "Always On". (@ <u>p. 225</u>)
- 2 Check the IP address of this unit with "Information". (© <u>p. 221</u>)

Friendly Name DHCP	
Connection	
IP Address	192.168.100.19
MAC Address	*****-000000
Checking the IP address.	

3 Start up the web browser.





For example, if the IP address of this unit is "192.168.100.19", enter "http://192.168.100.19".

🗲 🎯 📲 📴 http://192.168.100.19 🛯
<u>File Edit View Favorites Tools H</u> elp

5 When the top menu is displayed on the web browser, click on the menu item you want to operate.







Playback in ZONE2 (Another room)

You can operate this unit to enjoy video and audio in a room (ZONE2) that is different from the room where this unit is placed (MAIN ZONE). You can simultaneously play back the same source in both the MAIN ZONE and ZONE2. You can also play back separate sources in the MAIN ZONE and ZONE2.


Connecting ZONE2

You can use the following three methods to play back video and audio in ZONE2.

- "Connection through the HDMI ZONE2 connector " (12 p. 155)
- "Connecting using a speaker output terminal" (mp. 156)
- "Connecting using an external amplifier" (p. 156)

Connection 1 : Connection through the HDMI ZONE2 connector

When a TV is connected to the HDMI ZONE2 OUT connector, you can play back a video or audio from the device connected to the HDMI 1 – 7 IN connector in ZONE2 (HDMI ZONE2 function).





 When a TV is connected to the HDMI ZONE2 OUT connector, and the MAIN ZONE and ZONE2 are set to the same input source, the MAIN ZONE audio may be mixed down to 2-channel audio.


Front panel








When "Assign Mode" is set to "ZONE2" in the menu, ZONE2 audio is output from the SURROUND BACK speaker terminal. (12 p. 205)



- The analog audio signal and the 2-channel PCM signal input from HDMI connector or digital connectors (OPTICAL/COAXIAL) can be played back in ZONE2.
- If you want to play back HDMI signals other than 2-channel PCM in ZONE2, set "HDMI Audio" to "PCM". (@ p. 234) The output from a device connected to the input source selected for ZONE2 can be automatically converted to 2-channel PCM.

In this case, the MAIN ZONE audio will also be converted to 2-channel PCM if the MAIN ZONE and ZONE2 are set to the same input source. However, depending on the playback device, the playback signal may not be converted to PCM even if this setting is configured.

The audio signals of this unit's ZONE2 audio output connectors are output to the ZONE2 amplifiers and played on these amplifiers.







Contents	Connections Playback	Settings Tips Appendix	<u> </u>
Playback in ZON	NE2	Press ZONE2 to set the operating zone to ZONE2 with the remote control. The ZONE2 button lights.	
ZONE2		 Press POWER to turn on the ZONE2 power. The ZONE2 power indicator on the display lights. Power in ZONE2 can be turned on or off by pressing ZONE2 ON/OFF on the main unit. 	
Input source select buttons		3 Press the input source select button to select the input source to be played.	:
MUTE ⊄×		The audio signal of the selected source is output to ZONE2.You can also select ZONE2 as the input source by pressing ZONE2 SOURCE and then turning the INPUT SELECTOR.	
	TURE- Head (b/II) (b)		

157

Remote

Rear panel

Front panel

Display

Index

Adjusting the volume (ZONE2)

Use VOLUME $\blacktriangle V$ to adjust the volume.

At time of purchase, "Volume Limit" is set to "70 (-10 dB)".
 (12) p. 234)



• Turn VOLUME after pressing ZONE2 SOURCE on the main unit to adjust the volume.

Turning off the sound temporarily (Muting) (ZONE2)

Press MUTE **⊄**X.

The sound is reduced to the level set at "Mute Level" in the menu. ($(\underline{\mathbb{CP} p. 235})$

- To cancel mute, either adjust the sound volume or press MUTE ${\mathfrak q} \times$ again.









Menu map

When using menu operations, connect this unit to a TV and operate this unit while viewing the TV.

The recommended settings are configured for this unit by default. You can customize this unit based on your existing system and your preferences.

Setting items	Detailed items	Description	Page
	Center Level Adjust	Adjusts the center channel volume to clarify the dialog for all sources.	<u>164</u>
	Subwoofer Level Adjust	Adjusts the subwoofer channel volume for all input sources.	<u>164</u>
(‴⊙_))∕	Surround Parameter	Adjusts surround sound parameters.	<u>165</u>
M-DAX		Expands the low and high frequency components of compressed audio content such as MP3 files to enable richer audio playback.	<u>168</u>
	Audio Delay	Compensates for incorrect timing between video and audio.	<u>169</u>
	Volume	Sets the MAIN ZONE (room where the unit is located) volume setting.	<u>170</u>
	Audyssey	Makes Audyssey MultEQ [®] XT32, Audyssey Dynamic EQ [®] , Audyssey Dynamic Volume [®] and Audyssey LFC TM settings.	<u>171</u>
Graphic EQ		Uses the graphic equalizer to adjust the tone of each speaker.	<u>174</u>
	Picture Adjust	Adjusts picture quality.	<u>176</u>
	HDMI Setup	Makes settings for HDMI Audio Out, HDMI Pass Through and HDMI Control settings.	<u>178</u>
	Output Settings	Makes settings for video output.	<u>183</u>
	On Screen Display	Configures the on-screen display settings.	<u>187</u>
Video	4K Signal Format	Set the 4K signal format when the TV or playback device is 4K compatible.	<u>188</u>
	TV Format	Sets the video signal format to be output for the TV you are using.	<u>189</u>





Contents

Setting items	Detailed items	Description	Page
	Input Assign	Changes input connector assignment.	<u>190</u>
	Source Rename	Changes the display name for input source.	<u>192</u>
	Hide Sources	Removes from the display input sources that are not used.	<u>192</u>
	Source Level	Adjusts the playback level of the audio input.	<u>193</u>
Inputs	Input Select	Sets the audio input mode.	<u>193</u>
0	Audyssey [®] Setup	The acoustic characteristics of the connected speakers and listening room are measured and the optimum settings are made automatically.	<u>194</u>
Speakers	Manual Setup	Sets up the speakers manually or changes Audyssey [®] Setup settings.	<u>205</u>
	Information	Displays network information.	<u>221</u>
	Connection	Selects whether to connect the home network to a wireless LAN or a wired LAN.	221
	Settings	Used for manually setting the IP address.	224
	Network Control	Enables network communication in standby power mode.	225
Network	Friendly Name	The "Friendly Name" is the name of this unit displayed on the network. You can change the Friendly Name according to your preferences.	<u>226</u>
	Diagnostics	Used to check the network connection.	226

Front panel



Setting items	Detailed items	Description	Page
	[When the user is signed out the HEOS Account]		
	I have a HEOS Account	Selects to sign in.	<u>228</u>
	Create Account	Creates new HEOS Account. 228	
HEOS Account	Forgot Password	If you forgot your password, we'll send you an email with instructions about how to reset it.	<u>228</u>
	[When the user is signed in the HEOS Account]		
	Signed in As	Displays your HEOS Account.	
	Change Location	Selects your location.	
	Change Password	Changes your HEOS Account Password.	
	Delete Account	Deletes your HEOS Account.	228
	Sign Out	Sign out of your HEOS Account.	228







С	onte	ents
_		

Playback

Settings

Setting items	Detailed items	Description	Page
	Language	Changes the language of the display on the TV screen.	<u>229</u>
	ECO	Configures the ECO Mode and Auto Standby energy-saving functions.	229
	ZONE2 Setup	Makes settings for audio playback with ZONE2.	233
	Zone Rename	Changes the display title of each zone to one you prefer.	235
General	Smart Select Names	Changes the Smart Select Name display title to one you prefer.	235
	Trigger Out	Select the conditions for activating trigger out function.	236
	Front Display	Makes settings related to the display on this unit.	236
	Firmware	Checks for the latest firmware information about updates and upgrades, updates the firmware, and sets up the notification message display.	237
	Information	Shows information about this unit settings, input signals, etc.	240
	Usage Data	Selects whether or not to send anonymous usage data to Marantz.	<u>241</u>
	Save & Load	Save and restore device settings by using a USB memory device.	242
	Setup Lock	Protects settings from inadvertent changes.	242
	Reset	Various settings are reset to the factory default values.	<u>243</u>
	Begin Setup	Performs basic installation/connections/settings from the beginning according to the guidance indicated on the TV screen.	Page 9 of the separate
	Language Select	Sets individual setting items according to the guidance displayed on the TV screen.	manual "Quick Start
	Speaker Setup		Guide"
Setup Assistant	Speaker Calibration		
	Network Setup		
	TV Audio Connection		
	Input Setup		
	Mobile Apps		

Front panel



		Menu operations
MAIN —		Press MAIN on the remote control unit to set the operating zone to the MAIN ZONE. The MAIN button lights.
		2 Press SETUP. The menu is displayed on the TV screen.
	CH/FWGE MJTE VOLLARE	3 Use $\Delta \nabla \triangleright$ to select the menu to be set or operated, then press ENTER.
		4 Use $\triangleleft \triangleright$ to change to desired setting.
		5 Press ENTER to enter the setting.
ENTER		To return to the previous item, press BACK.Exiting the menu, press SETUP while the menu is displayed. TI
BACK —		menu display disappears.
	SMART SELECT	

Front panel



Audio

Make audio-related settings.

Center Level Adjust

Adjusts the center channel volume to clarify the dialog for all sources.

Center

Adjusts the volume output from the center channel.

-12.0 dB - +12.0 dB (Default: 0.0 dB)

ø

• This setting is also reflected in the center channel level in the "Speakers" - "Levels" menu settings. ((2) p. 217)

Subwoofer Level Adjust

Adjusts the subwoofer channel volume for all input sources.

Subwoofer 1 / Subwoofer 2

Adjusts the volume level for the Subwoofer 1 and Subwoofer 2.

-12.0 dB - +12.0 dB (Default: 0.0 dB)

 This setting is also reflected in the subwoofer channel level in the "Speakers" -"Levels" menu settings. (Pp. 217)







Surround Parameter

You can adjust the surround audio sound field effects to match your preferences.

The items (parameters) that can be adjusted depend on the signal being input and the currently set sound mode. For details on the adjustable parameters, see "Sound modes and surround parameters" ($\underline{\mathcal{CP} p. 281}$).

- Some setting items cannot be set while playback is stopped. Make the settings during playback.
- "Surround Parameter" settings are stored for each sound mode.

Cinema EQ

Gently softens the upper treble range of movie soundtracks to reduce possible harshness and improve clarity.

On:	"Cinema EQ" is used.
Off (Default):	"Cinema EQ" is not used.

Loudness Management

This sets whether to output as specified in "Dynamic Compression" or output directly without compressing the dynamic range of audio recorded in the disc.

On (Default):	Outputs are given based on enabling the settings made in "Dynamic Compression" and Dialogue normalization function.
Off:	"Dynamic Compression" settings and Dialogue normalization are disabled, and the signals on the disc are output as is.

• "Loudness Management" can be set when Dolby Digital, Dolby Digital Plus, Dolby TrueHD and Dolby Atmos signal is input.







Dynamic Compression

Compress dynamic range (difference between loud and soft sounds).

Auto:	Automatic dynamic range compression on/off control according to source.
Low / Medium / High:	These set the compression level.
Off:	Dynamic range compression is always off.

- "Dynamic Compression" can be set when Dolby Digital, Dolby Digital Plus, Dolby TrueHD, Dolby Atmos or DTS signal is input.
- The default setting is "Off". When the input signal is the Dolby TrueHD or Dolby Atmos source, the default setting is "Auto".
- "Auto" cannot be set when inputting a DTS signal.

Dialog Control

Adjust the volume of dialog in movies, vocals in music, etc. so these can be heard more easily.

0 – 6 (Default : 0)

• This can be set when a DTS:X signal that is compatible with the Dialog Control function is input.

Low Frequency Effects

Adjust the low frequency effects level (LFE).

U When "Input Mode" is set other than to "7.1CH IN"

-10 dB - 0 dB (Default: 0 dB)

□ When "Input Mode" is set to "7.1CH IN"

0 dB / +5 dB / +10 dB / +15 dB (Default: +10 dB)

- For proper playback of the different sources, we recommend setting to the values below.
 - Dolby Digital sources: 0 dB
 - DTS movie sources: 0 dB
 - DTS music sources: -10 dB



Center Spread

Center Spread expands the center channel signal to left and right front speakers to create a wider frontal audio image for the listener. It is optimized and designed primary for playback of stereo music content.

On:	Use "Center Spread".
Off (Default):	Do not use "Center Spread".

• You can set this when sound mode is "Dolby Surround".

DTS Neural:X

DTS Neural:X Expands the non-object based audio signals and optimizes them for your speaker configuration.

On (Default):

Use "DTS Neural:X".

Off:

Do not use "DTS Neural:X".

• You can set this when sound mode is "DTS:X" or "DTS:X MSTR".

Speaker Select

Makes settings for the speakers outputting sound.

Floor:	Plays back without height speakers.
Floor & Height (Default):	Plays back with height speakers.

• This can be set when the sound mode is the original sound mode.

Subwoofer

Turn subwoofer output on and off.

On (Default):	The subwoofer is used.
Off:	The subwoofer is not used.

 You can set this when the sound mode is "Direct" or "Stereo" and in the menu "Subwoofer Mode" is set to "LFE+Main". (1 p. 219)

Set Defaults

The "Surround Parameter" settings are returned to the default settings.









M-DAX

Compressed audio formats such as MP3, WMA (Windows Media Audio) and MPEG-4 AAC reduce the amount of data by eliminating signal components that are hard for the human ear to hear. The "M-DAX" function generates the signals eliminated upon compression, restoring the sound to conditions near those of the original sound before compression. It also restores the original bass characteristics for a rich and expanded tonal range.

Mode

High:	Optimized mode for compressed sources with very weak highs (64 kbps and under).
Medium:	Apply suitable bass and treble boost for all compressed sources (96 kbps and under).
Low:	Optimized mode for compressed sources with normal highs (96 kbps and over).
Off:	Do not use "M-DAX".

- The M-DAX indicator lights.
- This item can be set with analog signals or PCM signal (Sample Rate = $44.1/48~\mbox{kHz})$ is input.
- This item default setting for "HEOS Music" is "Low". All others are set to "Off".
- This cannot be set when the sound mode is set to "Direct" or "Pure Direct".
- This cannot be set when the input mode is set to "7.1CH IN".
- "M-DAX" settings are stored for each input source.
- This can also be set by pressing M-DAX on the main unit.





Audio Delay

Compensates for incorrect timing between video and audio.

- Audio Delay for game mode can be set when "Video Mode" is set to "Auto" or "Game". (Cpp. 184)
- "Audio Delay" settings are stored for each input source.
- This cannot be set when the input mode is set to "7.1CH IN".

Auto Lip Sync

Automatically adjusts the audio processing time to compensate for delays in audio/video timing from TV compatible with Auto Lip Sync.

On (Default):	Correct automatically.
Off:	Do not correct automatically.

 Automatic correction may not be performed depending on the specifications of your TV even when "Auto Lip Sync" is set to "On".

Adjust

The timing mismatch between the picture and sound needs to be corrected manually.

0 ms - 500 ms (Default : 0 ms)

- You can also finely adjust the delay correction value set by "Auto Lip Sync".
- Adjust for game mode can be set when "Video Mode" is set to "Auto" or "Game". (Cpp. 184)









Playback

Index

Appendix

Volume

Contents

Set the MAIN ZONE (room where the unit is located) volume setting.

Connections

Scale

Set how volume is displayed.

0 - 98 (Default):	Display in the range 0 (Min) to 98.
-79.5 dB - 18.0 dB:	DisplaydB (Min), in the range –79.5 dB to 18.0 dB.



• "Scale" settings are reflected in all the zones.

Limit

Make a setting for maximum volume.

60 (-20 dB) / 70 (-10 dB) / 80 (0 dB)

Off (Default)

• The dB value is displayed when the "Scale" setting is "-79.5 dB - 18.0 dB". ($\[mathbb{Cgr}]_{p.170}$)

Power On Level

Settings

Define the volume setting that is active when the power is turned on.

Tips

Last (Default):	Use the memorized setting from the last session.
Mute:	Always use the muting on condition when power is turned on.
1 – 98 (–79 dB – 18 dB) :	The volume is adjusted to the set level.

Ó

• The dB value is displayed when the "Scale" setting is "-79.5 dB - 18.0 dB". (127 p. 170)

Mute Level

Set the amount of attenuation when muting is on.

Full (Default):	The sound is muted entirely.
–40 dB :	The sound is attenuated by 40 dB down.
–20 dB :	The sound is attenuated by 20 dB down.

Audyssey®

Set Audyssey MultEQ[®] XT32, Audyssey Dynamic EQ[®], Audyssey Dynamic Volume[®] and Audyssey LFC[™]. These can be selected after Audyssey[®] Setup has been performed.

For additional information on Audyssey technology, please see "Explanation of terms" (27 p. 287).

- "MultEQ[®] XT32", "Dynamic EQ", "Reference Level Offset", "Dynamic Volume", "Audyssey LFC™" and "Containment Amount" settings are stored for each input source.
- When the sound mode is in the "Direct" or "Pure Direct" mode, "MultEQ[®] XT32", "Dynamic EQ", "Dynamic Volume" and "Audyssey LFC™" settings cannot be configured.
- When the sound mode is in "DTS Virtual:X" or sound mode that have "+Virtual:X" in the sound mode name, "MultEQ[®] XT32", "Dynamic EQ", "Dynamic Volume" and "Audyssey LFC™" settings cannot be configured.
- This cannot be set when the input mode is set to "7.1CH IN".

MultEQ[®] XT32

MultEQ[®] XT32 compensates for both time and frequency characteristics of the listening area based on Audyssey[®] Setup measurement results. Selection is done from three types of compensation curves. We recommend the "Reference" setting.

Reference (Default):	Selects the default calibrated setting with a slight roll off at high frequencies, which is optimized for movies.
L/R Bypass:	Selects the reference setting, but bypasses MultEQ [®] XT32 on the front left and right speakers.
Flat:	Selects the calibrated setting which is optimized for small rooms where your listening position is closer to the speakers.
Off:	Do not use "MultEQ® XT32".

• When using headphones, "MultEQ® XT32" is automatically set to "Off".

Front panel







Dynamic EQ

Solves the problem of deteriorating sound quality as volume is decreased by taking into account human perception and room acoustics.

Works with MultEQ® XT32.

On (Default):	Use "Dynamic EQ".
Off:	Do not use "Dynamic EQ".

 When the menu "Dynamic EQ" setting is "On", it is not possible to do "Tone" adjustment. (Cpp. 126)

Reference Level Offset

Audyssey Dynamic EQ[®] is referenced to the standard film mix level. It makes adjustments to maintain the reference response and surround envelopment when the volume is turned down from 0 dB. However, film reference level is not always used in music or other non-film content. Dynamic EQ Reference Level Offset provides three offsets from the film level reference (5 dB, 10 dB, and 15 dB) that can be selected when the mix level of the content is not within the standard. Recommended setting levels for content are shown below.

0 dB (Film Reference) (Default):	Optimized for content such as movies.
5 dB :	Select this setting for content that has a very wide dynamic range, such as classical music.
10 dB :	Select this setting for jazz or other music that has a wider dynamic range. This setting should also be selected for TV content as that is usually mixed at 10 dB below film reference.
15 dB :	Select this setting for pop/rock music or other program material that is mixed at very high listening levels and has a compressed dynamic range.

• Setting is enabled when "Dynamic EQ" is "On". (Pp. 172)

Front panel

172

Remote





Dynamic Volume

Solves the problem of large variations in volume level between TV, movies and other content (between quiet passages and loud passages, etc.) by automatically adjusting to the user's preferred volume setting.

Works with MultEQ® XT32.

Most adjustment to softest and loudest sounds.
Medium adjustment to loudest and softest sound.
Least adjustment to loudest and softest sounds.
Do not use "Dynamic Volume".

 If "Dynamic Volume" is set to "Yes" in "Audyssey[®] Setup", the setting is automatically changed to "Medium". (<u>P. 194</u>)

■ Audyssey LFC[™]

Adjusts the low frequency band to prevent bass and vibration from being conveyed to neighboring rooms.

Works with MultEQ® XT32.

On:	Use "Audyssey LFC™".
Off (Default):	Do not use "Audyssey LFC™".

Containment Amount

Adjusts the amount of low frequency containment. Use higher settings if you have close neighbors.

1 – 7 (Default : 4)



• This can be set when "Audyssey LFC™" in the menu is set to "On".

Front panel

Rear panel





Graphic EQ

Uses the graphic equalizer to adjust the tone of each speaker.

- Speakers for which "Graphic EQ" can be set differ according to the sound mode.
- This can be set when "MultEQ[®] XT32" setting is "Off". (CF p. 171)
- This cannot be set when the sound mode is set to "Direct" or "Pure Direct".
- If you are using headphones, you can set the equalizer for headphones.
 ((P_1, 174))
- This cannot be set when the input mode is set to "7.1CH IN".

Graphic EQ / Headphone EQ

Set whether to use the graphic equalizer or not.

On:	Use the graphic equalizer.
Off (Default):	Do not use the graphic equalizer.

• "Headphone EQ" is set in the menu when headphones are used.

Speaker Selection

Select whether to adjust tones for individual speakers or for all speakers.

All:	Adjust all speaker tones together.
Left/Right (Default):	Adjust the left and right speaker tones together.
Each:	Adjust the tone for each speaker.

Adjust EQ

Adjust tonal balance for each frequency band.

- 1. Select the speaker.
- Select the adjustment frequency band.
 63 Hz / 125 Hz / 250 Hz / 500 Hz / 1 kHz / 2 kHz / 4 kHz / 8 kHz / 16 kHz
- 3. Adjust the level.

-20.0 dB - +6.0 dB (Default: 0.0 dB)

- Front Dolby, Surround Dolby and Back Dolby speakers can only be set when 63 Hz/125 Hz/250 Hz/500 Hz/1 kHz.









Curve Copy

Copy the Flat correction curve created in Audyssey® Setup.

- "Curve Copy" is displayed after Audyssey® Setup has been performed.
- "Curve Copy" cannot be used when using headphones.

Set Defaults

The "Graphic EQ" settings are returned to the default settings.







Video

Make video-related settings.

Picture Adjust

Picture quality can be adjusted.

- This can be set when the "Video Conversion" setting is "On". (mp. 184)
- This can be set when "HDMI", "COMP" or "VIDEO" is assigned for each input source. (<u>Pp. 191</u>)
- "Contrast", "Brightness", "Saturation", "Noise Reduction" and "Enhancer" can be set when "Picture Mode" is set to "Custom". (<u>P. 176</u>)
- "Picture Adjust" settings are stored for each input source.
- "Picture Adjust" cannot be set when 4K signals are input.

Picture Mode

Select the desired picture mode according to the video content and your viewing environment.

Standard:	The standard mode suited for most living room viewing environments.
Movie:	A mode suited for watching movies in a dark room such as a theater room.
Vivid:	A mode that makes graphic images for games, etc. brighter and more vivid.
Streaming:	A mode suited for low bit rate video sources.
ISF Day:	A mode suited for watching movies in a bright room during the day.
ISF Night:	A mode suited for watching movies in a dark room at night.
Custom:	Adjusts the picture quality manually.
Off (Default):	No picture quality adjustment is done with this unit.

Front panel

Remote



• The two special adjustment modes, "ISF Day" and "ISF Night", should be used by a certified technician to adjust the color calibration to match the installation conditions.

We recommend that the settings and adjustments be carried out by an ISFcertified technician.

• These settings can also be configured using "Picture Mode" in the option menu. (@p. 176)

Contrast

Adjust picture contrast.

-50 - +50 (Default : 0)

Brightness

Adjust picture brightness.

-50 - +50 (Default : 0)

Saturation

Adjust picture chroma level (color saturation).

-50 - +50 (Default : 0)

Noise Reduction

Reduce overall video noise.

Low / Medium / High / Off (Default : Off)

Enhancer

Emphasize picture sharpness.

0 - +12 (Default : 0)







HDMI Setup

Make settings for HDMI Audio Out, HDMI Pass Through and HDMI Control settings.

NOTE

 When "HDMI Pass Through" and "HDMI Control" is set to "On", it consumes more standby power. (" HDMI Pass Through " (<u>P. 178</u>), " HDMI Control " (<u>P. 180</u>))

If you are not using this unit for an extended period, it is recommended that you unplug the power cord from the power outlet.

HDMI Audio Out

Select HDMI audio output device.

AVR (Default):	Play back through speakers connected to the unit.
TV:	Play back through TV connected to the unit.

- When the HDMI Control function is activated, priority is given to the TV audio setting. (127 p. 142)
- When the power of this unit is on and "HDMI Audio Out" is set to "TV", audio is output as 2-channel from the HDMI OUT connector.

HDMI Pass Through

Selects how this unit will transmit HDMI signals to the HDMI output in standby power mode.

On (Default):	Transmits the selected HDMI input through this unit's HDMI output when this unit is in standby power mode.
Off:	No HDMI signals are transmitted through this unit's HDMI output in standby power mode.







Pass Through Source

Sets the HDMI connector that inputs HDMI signals when in standby.

Last:	The most recently used input source will go into standby mode.
CBL/SAT / DVD / Blu-ray / Game / AUX1 / AUX2 / Media Player / CD* (Default : CBL/SAT):	Pass through the selected input source.

* "Pass Through Source" can be set when any of the HDMI connectors is assigned to "CD" for the input source in the "Input Assign" setting. (127 p. 190)

 "Pass Through Source" can be set when "HDMI Control" is set to "On" or "HDMI Pass Through" is set to "On". ("HDMI Pass Through " (<u>P. 178</u>), "HDMI Control" (<u>P. 180</u>))

RC Source Select

Set whether to allow this unit to be turned on by the input source select button on the remote control when this unit is on standby.

The HDMI input source cha this unit is on standby. The of this unit blinks when the	
Source Select Only: of this unit blinks when the select button of the remote pressed.	power display input source

 "RC Source Select" can be set when "HDMI Control" is set to "On" or "HDMI Pass Through" is set to "On". ("HDMI Pass Through " (p. 178), "HDMI Control " (p. 180))







HDMI Control

Contents

You can link operations with devices connected to HDMI and compatible with HDMI Control.

On:	Use HDMI Control function.
Off (Default):	Do not use HDMI Control function.

- If using the HDMI Control function, connect a TV compatible with HDMI control to the HDMI MONITOR 1 connector.
- Please consult the operating instructions for each connected device to check
 the settings.
- Refer to "HDMI Control function" for more information about the HDMI Control function. (<u>Pp. 142</u>)

NOTE

• If the "HDMI Control" settings have been changed, always reset the power to connected devices after the change.

Settings

On the TV connected to the HDMI MONITOR 1 connector, set whether to receive sound from the TV via HDMI.

Tips

On:	Use ARC function.
Off (Default):	Do not use ARC function.

- You can adjust the volume of this unit using the TV remote control.
- If using this function, use a TV compatible with ARC (Audio Return Channel) and enable the HDMI Control function of the TV.
- When "HDMI Control" is set to "On", the "ARC" settings automatically switch "On". ((了 <u>p. 180</u>)

NOTE

- If the "ARC" settings have been changed, always reset the power to connected devices after the change.
- Using an eARC function-compatible television enables audio playback from the speaker connected to this unit, regardless of "ARC" settings in the menu.

Playback

Remote

Index



TV Audio Switching

Sets automatic switching to the "TV Audio" input when a TV connected via HDMI sends an appropriate CEC control command to this unit.

On (Default):	Select the "TV Audio" input automatically when receiving a command from the TV.
Off:	Do not select the "TV Audio" input automatically when receiving a command from the TV.

ø

 "TV Audio Switching" can be set when "HDMI Control" is set to "On". ((資一<u>p. 180</u>)

Power Off Control

Links the power standby of this unit to external devices.

All (Default):	If power to a connected TV is turned off independently of the input source, power to this unit is automatically set to standby.
Video:	With an input source being selected that is assigned either "HDMI", "COMP" or "VIDEO", when you turn the power of the TV off, power to this unit is automatically set to standby. ((Pp. <u>p. 191</u>)
Off:	This unit does not link with power to a TV.

• "Power Off Control" can be set when "HDMI Control" is set to "On". (CF p. 180)







Power Saving

If "TV Speaker" is set as the audio output setting of your TV, this unit is automatically set to standby mode to reduce power consumption. This function is activated in the following cases.

- . When "TV Audio" is selected as the input source of this unit
- · When playing content from a device connected by HDMI

On:	Use Power Saving function.
Off (Default):	Do not use Power Saving function.

• "Power Saving" can be set when "HDMI Control" is set to "On". (p. 180)

Smart Menu

This function can be used to configure the settings of this unit, select an input source and set Tuner and Internet Radio stations using the TV remote control.

On:	Use Smart Menu function.
Off:	Do not use Smart Menu function.

• "Smart Menu" can be set when "HDMI Control" is set to "On". (1) 180)

NOTE

- If the "Smart Menu" settings have been changed, always reset the power to connected devices after the change.
- The Smart Menu function may not work properly depending on the specifications of your TV. In this case, set "Smart Menu" to "Off".











Output Settings

Makes settings for video output.

- This can be set when "HDMI", "COMP" or "VIDEO" is assigned for each input source. (<u>Pp. 191</u>)
- "Resolution", "Sharpness", "Progressive Mode" and "Aspect Ratio" can be set when "i/p Scaler" is set to anything other than "Off". ("Resolution" (127 p. 185), "Sharpness" (127 p. 185), "Progressive Mode" (127 p. 186), "Aspect Ratio" (127 p. 186))
- "Output Settings" cannot be set when 4K signals are input.
- "Video Conversion", "i/p Scaler", "Resolution", "Sharpness", "Progressive Mode" and "Aspect Ratio" settings are stored for each input source. (" Video Conversion " (IP <u>p. 184</u>), " i/p Scaler " (IP <u>p. 184</u>), " Resolution " (IP <u>p. 185</u>), " Sharpness " (IP <u>p. 185</u>), " Progressive Mode " (IP <u>p. 186</u>), " Aspect Ratio " (IP <u>p. 186</u>))

HDMI Video Output

Select the HDMI monitor connector to be used.

Auto(Dual) (Default):	The presence of a TV connected to the HDMI MONITOR 1 or HDMI MONITOR 2 connector is detected automatically, and that TV connection is used.
Monitor 1:	A TV connected to the HDMI MONITOR 1 connector is always used.
Monitor 2:	A TV connected to the HDMI MONITOR 2 connector is always used.

- If both the HDMI MONITOR 1 and HDMI MONITOR 2 connectors are connected and "Resolution" is set to "Auto", the signals are output with a resolution that is compatible with both TVs. (CP p. 185)
 When the "Resolution" setting in the menu is not set to "Auto", set the resolution in "Video" "HDMI Monitor 1" and "HDMI Monitor 2" to one that is compatible with both TVs. (CP p. 240)
- You can check which resolutions are compatible with your TV in "HDMI Monitor 1" and "HDMI Monitor 2". (Pp. 240)
- When connecting multiple Dolby Vision TVs, the signal will only be optimal for one TV. A TV connected to the HDMI MONITOR 1 connector has priority.

Front panel

Video Mode

Configure the video processing method to match the type of video content.

Auto (Default):	Process video automatically based on the HDMI content information.
Game:	Always process video for game content. Minimize the video delay when the video is delayed compared to the button operations on the controller of the game console.
Movie:	Perform image processing that is suitable for contents other than games.

<u>_</u>

• If "Video Mode" is set to "Auto", the mode is switched according to the input contents.

Video Conversion

The input video signal is converted automatically in conjunction with the connected TV. (r_{P} <u>p. 273</u>)

On (Default):	The input video signal is converted.
Off:	The input video signal is not converted.

i/p Scaler

Set the video input signal to be subjected to i/p Scaler processing. i/p Scaler will convert the resolution of the input video signal to the value set in "Resolution". (\underline{rr} p. 185)

Analog (Default):	Use i/p (interlace-to-progressive) scaler function for analog video signals.
Analog & HDMI:	Use i/p Scaler function for analog and HDMI video signal.
HDMI:	Use i/p Scaler function for HDMI video signals.
Off:	Do not use i/p Scaler function.



Front panel

185

Index

Set the output resolution. You can set "Resolution" separately for HDMI output of the analog video input and HDMI input.

Auto (Default):	The resolution supported by the TV connected to the HDMI MONITOR OUT connector is detected automatically and the appropriate output resolution is set.
480p/576p / 1080i / 720p / 1080p / 1080p:24Hz / 4K / 4K (60/50) :	Set the output resolution.

- When "i/p Scaler" is set to "Analog & HDMI", the resolution of both the analog video input signal and HDMI input signal can be set. (127 p. 184)
- When set to "1080p:24Hz", you can enjoy film-like pictures for film sources (in 24 Hz). For video sources and mixed sources, we recommend setting the resolution to "1080p".
- It is not possible to convert a 50 Hz signal into 1080p/24Hz. It is output at a resolution of 1080p/50Hz.

Sharpness

Settings

Enables the sharpness feature which enhances the edges of images when up-scaling video to $4\mathsf{K}.$

Tips

On:	Enables the video enhancer sharpness feature to provide image edge contouring which is optimized for converting lower resolution standard definition video to 4K.
Off (Default):	Disables the video enhancer sharpness feature.

- This item can be set when "i/p Scaler" is set to anything other than "Off".
 (P. 184)
- We recommend using this sharpness feature only when your TV sharpness is set to 0.

Progressive Mode

Set an appropriate progressive conversion mode for the source video signal.

Auto (Default):	The video signal is automatically detected and the appropriate mode is set.
Video:	Select mode suitable for video playback.
Video and Film:	Select mode suitable for video and 30- frame film material playback.

This item can be set when "i/p Scaler" is set to anything other than "Off".
 (Cp. p. 184)

Aspect Ratio

Set the aspect ratio for the video signals output to the HDMI.

16:9 (Default):	Output at 16:9 aspect ratio.
4:3 :	Output at 4:3 aspect ratio with black bars on the sides of a 16:9 TV screen. (except for 480p/576p output)

This item can be set when "i/p Scaler" is set to anything other than "Off".
 (CP_p. 184)

Front panel







On Screen Display

Select the on-screen display user interface preferences.

Volume

Sets where to display the volume level.

Bottom (Default):	Display at the bottom.
Тор:	Display at the top.
Off:	Turn display off.

• When the master volume display is hard to see when superimposed text (closed captioning) or movie subtitles are present, set to "Top".

Info

Displays status of operation temporarily when the input source is switched.

On (Default):	Turn display on.	
Off:	Turn display off.	

Now Playing

Sets the display time for the playback display when the input source is "HEOS Music" or "Tuner".

Always On (Default):	Show display continuously.
Auto Off:	Show display for 30 seconds after operation.









4K Signal Format

Set the 4K signal format to be played back by this unit when the TV or playback device connected to this unit is HDMI 4K (60Hz/50Hz) signal compatible.

4K Signal Format

Set the format of the 4K signal played back by this unit.

Standard (Default):	Select if your TV and playback devices support standard 4K 60p 4:2:0 8 bit video signals.
Enhanced:	Select if your TV, playback devices, and cables support high quality 4K 60p 4:4:4, 4:2:2 or 4K 60p 4:2:0 10 bit video signals.

[Relation between the "4K Signal Format" setting and supported resolutions]

Tips

Support	Color Pixel		4K Signal Format		
Support Resolution	Space	Depth	Enhanced	Standard (Default)	
4K 24p, 4K	RGB /	8 bit	\checkmark	\checkmark	
30p, 4K 25p	YCbCr 4:4:4	10,12 bit	\checkmark	-	
	YCbCr 4:2:2	12 bit	\checkmark	\checkmark	
4K 60p, 4K 50p	YCbCr 4:2:0	8 bit	\checkmark	\checkmark	
		10,12 bit	\checkmark	-	
	RGB / YCbCr 4:4:4	8 bit	\checkmark	-	
	YCbCr 4:2:2	12 bit	\checkmark	_	







- When setting this to "Enhanced", we recommend using a "Premium High Speed HDMI Cable" or "Premium High Speed HDMI Cable with Ethernet" that has an "HDMI Premium Certified Cable" label attached to the product package.
- When this setting is "Enhanced", configure the television or playback device settings to match this setting.
- When this setting is "Enhanced", video may not be output correctly depending on the connected playback device or HDMI cable. In this case, change this setting to "Standard".
- "Custom" is displayed for the setting item if our service engineers or custom installers has configured the HDMI signal format for this unit.
- "4K Signal Format" can also be set by the following procedure. However, the menu screen is not displayed. Watch the display while configuring the setting.
- 1. Press and hold the main unit's ZONE2 SOURCE and STATUS at the same time for at least 3 seconds.

"Video Format <NTSC>" appears on the display.

- 2. Press the main unit's DIMMER.
 - "4K Format < Std >" appears on the display.
- 3. Use the main unit's TUNER PRESET CH + or TUNER PRESET CH and select the 4K Signal Format.
- 4. Press the main unit's STATUS to complete the setting.

TV Format

Set the video signal format to be output for the TV you are using.

Format

NTSC (Default):	Select NTSC output.
PAL:	Select PAL output.

- "Format" can also be set by the following procedure. However, the menu screen is not displayed. Following the display content to make the setting.
 - 1. Press and hold the main unit's ZONE2 SOURCE and STATUS at the same time for at least 3 seconds.

"Video Format <NTSC>" appears on the display.

- 2. Use the main unit's TUNER PRESET CH + or TUNER PRESET CH and set the video signal format.
- 3. Press the main unit's STATUS to complete the setting.

NOTE

 When a format other than the video format of the connected TV is set, the picture will not be displayed properly.



Inputs

Perform settings related to input source playback.

You do not have to change the settings to use the unit. Make settings when needed.

Input Assign

By making connections as indicated by the input sources printed on the audio/video input connectors of this unit, you can just press one of the input source select buttons to easily play back audio or video from a connected device.

Please change the assignment of the HDMI input connector, digital audio input connector, analog audio input connector, component video input connector and video input connector when connecting an input source that differs from that printed to the audio/video input connectors of this unit.

Set Defaults	HDMI	DIGITAL	ANALOG	VIDEC
		COAX1		VIDEO
DVD	2	COAX2		COMP
Blu-ray				VIDEO
Game				VIDEO
Media Player		OPT2		COMP
TV Audio		OPT1		
AUX1	FRONT		FRONT	FRONT
AUX2				
CD				

• By default, each item is set as follows.

Input source	Input connector			
input source	HDMI	DIGITAL	ANALOG	VIDEO
CBL/SAT	1	COAX1	1	VIDEO1
DVD	2	COAX2	2	COMP1
Blu-ray	3	-	3	VIDEO2
Game	4	-	4	VIDEO3
Media Player	5	OPT2	_	COMP2
TV Audio	-	OPT1	_	-
AUX1	FRONT	-	FRONT	FRONT
AUX2	6	-	_	-
CD	-	-	5	-

TV set top box/satellite users please note

When using the digital audio output on a TV/satellite box:

To play the video signal assigned to "HDMI" combined with the audio signal assigned at "Input Assign" - "DIGITAL", you will also need to select "Digital" in the "Input Mode". (Imp. 193)

Front panel





HDMI

Set this to change the HDMI input connectors assigned to the input sources.

1/2/3/4/5/6/7/ FRONT:	Assign an HDMI input connector to the selected input source.
-:	Do not assign an HDMI input connector to the selected input source.

- When "HDMI Control" or "ARC" is set to "On" in the menu, "HDMI" cannot be assigned to "TV Audio". (" HDMI Control " ((<u>p. 180</u>), " ARC " (<u>(p. 180</u>))
- The eARC function does not operate when "HDMI" is set as the "TV Audio" input source.

DIGITAL

Set this to change the digital audio input connectors assigned to the input sources.

 COAX1 (Coaxial) /
 Assign a digital audio input connector to the selected input source.

 OPT1 (Optical) / OPT2:
 Do not assign a digital audio input connector to the selected input source.

Set this to change the analog audio input connectors assigned to the input sources.

1/2/3/4/5/FRONT:	Assign a analog audio input connector to the selected input source.
-:	Do not assign a analog audio input connector to the selected input source.

Set this to change the component video input connectors and composite video input connectors assigned to the input sources.

COMP1 (Component video) / COMP2 / VIDEO1 / VIDEO2 / VIDEO3 / FRONT:	Assign the video input connector to the selected input source.
-:	Do not assign a video input connector to the selected input source.

Set Defaults

The "Input Assign" settings are returned to the default settings.







Source Rename

Change the display name for input source.

This is convenient when the name of your device and the input source name of this unit are different. You can change the name to suit your needs. When the renaming is completed, the name is displayed on this unit's display and on the menu screen.

CBL/SAT / DVD / Blu-ray / Game / AUX1 / AUX2 / Media Player / CD / TV Audio / Phono:	Change the display name for input source.
Set Defaults:	The "Source Rename" settings are returned to the default settings.

Hide Sources

Remove from the display input sources that are not used.

Show (Default):	Use this source.
Hide:	Do not use this source.

• Up to 12 characters can be input.









Source Level

This function corrects the playback level of the selected input source's audio input.

Make this setting if there are differences in the input volume levels between the different sources.

-12 dB - +12 dB (Default : 0 dB)

• "Source Level" settings are stored for each input source.

Input Select

Set the audio input mode of each input source.

The input modes available for selection may vary depending on the input source.

(

• "Input Select" settings are stored for each input source.

Input Mode

Set the audio input modes for the different input sources. It is normally recommended to set the audio input mode to "Auto".

Auto (Default):	Automatically detect input signal and perform playback.
HDMI:	Play only signals from HDMI input.
Digital:	Play only signals from digital audio input.
Analog:	Play only signals from analog audio input.
7.1CH IN:	Only signals input from the 7.1CH IN connector will be played back.

- If "HDMI Control" is set to "On" and a TV compatible with the ARC is connected via the HDMI MONITOR 1 connectors, the input mode whose input source is "TV Audio" is fixed to ARC.
- When an eARC function-compatible television is connected to the HDMI MONITOR 1 connector, the input mode is fixed to eARC while the input source is "TV Audio".
- The sound mode cannot be set if the input mode is set to "7.1CH IN".

Front panel





Co	ntents	

Speakers

The acoustic characteristics of the connected speakers and listening room are measured and the optimum settings are made automatically. This is called "Audyssey[®] Setup".

You do not have to perform Audyssey® Setup when you have already performed "Speaker Calibration" in "Setup Assistant".


To set up the speakers manually, use "Manual Setup" on the menu. (12 p. 205)

Audyssey[®] Setup

To perform measurement, place the Sound calibration microphone in multiple locations all around the listening area. For best results, we recommend you measure in six or more positions, as shown in the illustration (up to eight positions).

When measuring the second and subsequent positions, install the Sound calibration microphone within 2 ft (60 cm) of the first measurement position (main listening position).

If you perform Audyssey[®] Setup, Audyssey MultEQ[®] XT32, Audyssey Dynamic EQ[®], Audyssey Dynamic Volume[®] and Audyssey LFC[™] functions are enabled.
 (127 p. 171)



FL Front speaker (L)
FR Front speaker (R)
C Center speaker
SW Subwoofer
SL Surround speaker (L)
SR Surround speaker (R)

Front panel





About the main listening position

The main listening position is the position where listeners would normally sit or where one would normally sit alone within the listening environment. Before starting Audyssey[®] Setup, place the Sound calibration microphone in the main listening position.

Audyssey MultEQ[®] XT32 uses the measurements from this position to calculate speaker distance, level, polarity, and the optimum crossover value for the subwoofer.

■ About Audyssey Sub EQ HT™

Audyssey Sub EQ HT[™] makes the integration of dual subwoofers seamless by first compensating for any level and delay differences between the two subwoofers and then applying Audyssey MultEQ[®] XT32 to both subwoofers together.

To run Audyssey Sub EQ HT[™] you must select "Measure (2 spkrs)" in "Channel Select". (௴ p. 197).

NOTE

- Make the room as quiet as possible. Background noise can disrupt the room measurements. Close windows and turn off the power on electronic devices (radios, air conditioners, fluorescent lights, etc.). The measurements could be affected by the sounds emitted by such devices.
- During the measurement process, place cell phones outside the listening room. Cell phone signals could disrupt the measurements.
- Do not stand between the speakers and Sound calibration microphone or allow obstacles in the path while the measurements are being made. Also, install the Sound calibration microphone at least 20 inches (50 cm) away from the wall.
 Failure to do so will result in inaccurate readings.
- During the measurement process, audible test tones will come from the speakers and subwoofer(s), but this is part of normal operation. If there is background noise in the room, these test signals will increase in volume.
- Operating VOLUME ▲ ▼ on the remote control unit or VOLUME on the main unit during the measurements will cancel the measurements.
- Measurement cannot be performed when headphones are connected. Unplug the headphones before performing Audyssey® Setup.







Contents Connections Playback		Settings Tips Appendix
Procedure for speaker settings (Audyssey [®] Setup)	1	Attach the Sound calibration microphone to the supplied microphone stand or own tripod and install it at the main listening position. When installing the Sound calibration microphone, point the tip of
Preparation		the microphone toward the ceiling and adjust the height to match the height of the ears of a listener in a seated position.
Measurement	2	If using a subwoofer capable of the following adjustments, set up the subwoofer as shown below.
•		When using a subwoofer with a direct mode
Calculation & Store		Set the direct mode to "On" and disable the volume adjustment and crossover frequency setting.
↓		When using a subwoofer without a direct mode
Check		Make the following settings:
\checkmark		 Volume : 12 o'clock position Crossover frequency : Maximum/Highest Frequency Low pass filter : Off
Finish		Standby mode : Off
		- Grandby more . On




196

Remote



3 Connect the Sound calibration microphone to the SETUP MIC jack of this unit.



When the Sound calibration microphone is connected, the following screen is displayed.



4 Select "Start", then press ENTER.

Audyssey® Setup can also make the following settings.

Amp Assign

The signals output from the HEIGHT1 and HEIGHT2 speaker terminals can be switched in accordance with your speaker environment. ("Amp Assign" ($\underline{\mathbb{CP}}$ <u>p. 205</u>))

Channel Select

If channels that are not to be used are set in advance, measurement for the set channels is skipped, and measuring time can be reduced. You can also change the number of surround back speakers and subwoofer.

Dolby Speaker Setup

Set the distance between the Dolby Atmos Enabled speaker and the ceiling.

This can be set when using the Front Dolby Atmos Enabled, Surround Dolby Atmos Enabled or Back Dolby Atmos Enabled speaker.

Follow the instructions on the screen display and press "Next" to proceed further.

Front panel

197

Contents Connections Playback

Settings

6 When the following screen is displayed, select "Begin Test" and then press ENTER.

Start the measurement of the first position.



When the detected speaker is displayed, select "Next" and then press ENTER.



· Measurement requires several minutes.

NOTE

- If "Caution!" is displayed on TV screen:
 - Go to "Error messages" (Pp p. 202). Check any related items, and perform the necessary procedures.
 - If the volume level for the subwoofer is not appropriate, an error message is displayed. See "Subwoofer level error message and how to adjust" (<u>P. 203</u>).





8 Move the Sound calibration microphone to position 2, select "Continue", then press ENTER.

The measurement of the second position starts. Measurements can be made in up to eight positions.



□ Stopping Audyssey[®] Setup

- (1) Press BACK to display the popup screen.
- $\overline{(2)}$ Press \triangleleft to select "Yes", then press ENTER.

9 Repeat step 8, measuring positions 3 to 8.

• To skip measuring the fourth and subsequent listening position, press ⊲ to select "Complete" and press ENTER to proceed to step 11.

10 Select "Continue", then press ENTER.



Start the analysis and storage of the measurement results.

· Analysis takes several minutes to complete.

The more speakers and measurement positions that there are, the more time it takes to perform the analysis.

NOTE

• When the measurement results are being saved, make sure the power is not turned off.

Front panel





Playback

11 Perform the settings for Audyssey Dynamic EQ[®] and Audyssey Dynamic Volume[®].

The following screen is displayed during the analysis. Configure the settings as preferred.

💍 Audyssey Setup	NUDYSSEY
Audyssey Dynamic EQ maintains ba sound at low volumes letting you e and television.	
Turn on Dynamic EQ?	
Yes No	
Analyzing room data	50%
	30%

 Dynamic EQ corrects the frequency response in consideration of the audio characteristics of the room and human hearing ability so that sound can be heard even at low volume.

This is recommended when using the unit with the volume turned down, e.g. when enjoying a movie or TV program in the middle of the night.

• Dynamic Volume adjusts the output volume to the optimal level while constantly monitoring the level of the audio input to the unit. Optimal volume control is performed automatically without any loss in the dynamism and clarity of the sound when, for example, the volume suddenly increases for commercials shown during television programs. 2 When the analysis and storage ends, unplug the Sound calibration microphone from the SETUP MIC jack on the main unit and then press "Next".

	Audyssey Setup Analyzing and correcting y e disconnect the micropho	our room data	
	Applying room corre	ections	
B	ack		100% Next





13 Select "Details" and press ENTER to verify the measurement results.

 Subwoofers may measure a greater reported distance than the actual distance due to added electrical delay common in subwoofers.

NOTE

 Do not change the speaker connection or subwoofer volume after Audyssey[®] Setup. If these are changed, run Audyssey[®] Setup again in order to configure the optimum equalizer settings.











Error messages

An error message is displayed if Audyssey[®] Setup could not be completed due to speaker placement, the measurement environment, etc. If an error message is displayed, check the relevant items and perform the necessary measures. Be sure to turn off the power before checking speaker connections.

Examples	Error details	Measures
No speakers found.	 Sound calibration microphone is not detected. 	Connect the included Sound calibration microphone to the SETUP MIC jack of this unit.
	Not all speakers could be detected.	Check the speaker connections.
Ambient noise is too high or level is too	There is too much noise in the room.	Either turn off any device generating noise or move it away.
low		Perform again when the surroundings are quieter.
	 Speaker or subwoofer sound is too low. 	• Check the speaker installation and the direction in which the speakers are facing.
		Adjust the subwoofer's volume.
Front R : None	 The displayed speaker could not be detected. 	Check the connections of the displayed speaker.
Front R : Phase	• The displayed speaker is connected with the	Check the polarity of the displayed speaker.
	polarity reversed.	• For some speakers, this error message may be displayed even if the speaker is properly connected. If you are sure the connection is correct, press ▷ to select "Ignore", then press ENTER.

Front panel



Subwoofer level error message and how to adjust

The optimal level of each subwoofer channel for Audyssey $^{\otimes}$ Setup measurement is 75 dB.

During subwoofer level measurement, an error message is displayed when one level of subwoofers is outside the 72 - 78 dB range.

When using a subwoofer with built-in amplifier (active type), adjust the subwoofer volume so that the subwoofer level is within the 72 to 78 dB range.



- Select "SW Level Matching" and then press ENTER.
- Adjust the volume control on your subwoofer so that the measured level is within the 72 to 78 dB range.
- **3** When the measured level is within the 72 to 78 dB range, select "Next" and then press ENTER.
 - If you use two subwoofers, the second subwoofer's adjustment will be started. Repeat the operation from step 2, 3.









Retrieving Audyssey® Setup settings

If you set "Restore..." to "Restore", you can return to Audyssey[®] Setup measurement result (value calculated at the start by MultEQ[®] XT32) even when you have changed each setting manually.

💍 Audyssey Setu	p AULTOXISEY MULTOXISE DYNAMIC YOLIME
	utomatically measure the acoustics of ze your speakers using the included phone stand.
Set the following items	
if necessary.	
Amp Assign	
Channel Select	
Dolby Speaker Setup	
Check Results	
Restore	
Start	

Front panel









Manual Setup

Perform when setting the speakers manually or when changing settings made in ${\rm Audyssey}^{\circledast}$ Setup.

- If you add or remove a speaker after performing Audyssey[®] Setup, you will no longer be able to select Audyssey MultEQ[®] XT32, Audyssey Dynamic EQ[®] or Audyssey Dynamic Volume[®]. (127 p. 171)
- "Manual Setup" can be used without changing the settings. Please set if necessary.

Amp Assign

Select the power amplifier usage method to match your speaker system.

Assign Mode

Select how to use the power amp.

You need to configure the detailed settings for the speaker configuration in accordance with the selected mode. Select Assign Mode configure the corresponding detailed settings.

- Setting to use the 9-channel power amplifier in this unit and an external power amplifier connected to PRE OUT to play back up to 11.1-channels.
 - You can connect speakers for up to 11.1channels for MAIN ZONE.

11.1ch:





Contents	Connections Playback	Settings	Tips Appendix
9.1ch:	 Settings to assign all power amplifier within this unit to MAIN ZONE to play back up to 9.1-channels. You can connect speakers for up to 11.1- channels for MAIN ZONE. Speakers to output audio are automatically switched for playing back up to 9.1- channels in accordance with the input signal and sound mode. 	7.1ch (Bi-Amp):	 Setting to assign the power amplifiers in this unit for front speaker bi-amp connection to 2-channels. You can connect speakers for up to 9.1 channels for MAIN ZONE. Speakers to output audio are automaticall switched for playing back up to 7.1-channels in accordance with the input signal and sound mode.
7.1ch + ZONE2 (Default):	 Setting to assign the power amplifiers in this unit for ZONE2 to 2-channels. You can connect speakers for up to 9.1- channels for MAIN ZONE. Speakers to output audio are automatically switched for playing back up to 7.1- channels in accordance with the input signal and sound mode. 	5.1ch (Bi-Amp) + ZONE2:	 Setting to assign the power amplifiers in this unit for front speaker bi-amp connection to 2-channels. Setting to assign the power amplifiers in this unit for ZONE2 to 2-channels.



Remote



Layout

Select the floor speakers location.

5ch & SB (Default):	This layout combines a surround back speaker with the basic 5-channel layout.
5ch:	This is a basic 5-channel layout that uses front speakers, center speakers and surround speakers.

• Setting to assign the power amplifiers within this unit for connecting the second set of front speakers.

• You can switch between the desired combination of front speakers A and front speakers B.

Switch the front speaker using the "Front

Speaker" setting. (1 p. 220)

7.1ch + Front B:

• You can connect speakers for up to 9.1channels for MAIN ZONE.

Speakers to output audio are automatically switched for playing back up to 7.1channels in accordance with the input signal and sound mode.

- When "Assign Mode" is set to "7.1ch + ZONE2", "7.1ch (Bi-Amp)" or "7.1ch + Front B" in the menu, the assigned channels are output from HEIGHT2 speaker terminals.
- When Assign Mode is set to "5.1ch (Bi-Amp) + ZONE2" in the menu, the front channels for Bi-Amp connection are output from HEIGHT1 speaker terminals, and the ZONE2 channels are output from HEIGHT2 speaker terminals.





Height

Height Sp

Select the number of the height speakers and ceiling speakers used in MAIN ZONE.

None:	Uses no height and ceiling speakers.
2ch (Default):	Uses a set of (two) height speakers or ceiling speakers.
4ch:	Uses two sets of (four) height speakers or ceiling speakers.

Dolby Sp

Select the number of the Dolby Atmos Enabled speakers used in MAIN ZONE.

None (Default):	Uses no Dolby Atmos Enabled speakers.
2ch:	Uses a set of (two) Dolby Atmos Enabled speakers.
4ch:	Uses two sets of (four) Dolby Atmos Enabled speakers.

Front panel





Rear panel

Remote

Index

-

-

-

-

-

-

Top Middle

HEIGHT 1

Front Height

Top Front

Top Middle

Top Rear

Rear Height

Front Height

				Front Height & Top Rear	Front Height	Top Rear
	4ch	None	*1	Front Height & Rear Height	Front Height	Rear Height
	401	none	*1	Top Front & Top Rear	Top Front	Top Rear
				Top Front & Rear Height	Top Front	Rear Height
			Top Middle & Rear Height	Top Middle	Rear Height	
	None 2ch		Front Dolby	Front Dolby	-	
		2ch		Surround Dolby	Surround Dolby	-
				Back Dolby *2	Back Dolby	-

*1 This can be selected when "Assign Mode" is set to "11.1ch" or "9.1ch" in the menu.

*2 This can be selected when "Assign Mode" is set to "11.1ch" and "Floor" - "Layout" is set to "5ch & SB" in the menu.

Layout

Height Sp

None

2ch

Select the height, ceiling, or Dolby Atmos Enabled speaker location.

Dolby Sp

None

None

Mode " (2 p. 205), "Floor" - " Layout " (2 p. 207))

Layout

Front Height (Default)

Top Front

Top Middle

Top Rear

Rear Height

Front Height & Top Middle

Playback

Settings

NOTE

The layouts that can be selected differ depending on the combinations of "Assign Mode" and "Floor" - "Layout" in the menu. (" Assign

Contents	\bigvee	Connections	\bigvee	Playback	\bigvee	Settings	\checkmark	Tips	\bigvee	Appendix	\backslash

	Settings				AUDIO OUT connectors	
Height Sp	Dolby Sp	NOTE	Layout	HEIGHT 1	HEIGHT 2	
			Front Dolby & Top Rear	Front Dolby	Top Rear	
		*1	Front Dolby & Rear Height	Front Dolby	Rear Height	
Och	2ch		Front Height & Surr. Dolby	Front Height	Surround Dolby	
2ch			Front Height & Back Dolby *3	Front Height	Back Dolby	
			Top Front & Surr. Dolby	Top Front	Surround Dolby	
			Top Front & Back Dolby *3	Top Front	Back Dolby	
None	4ch	4ch *1	Front Dolby & Surr. Dolby	Front Dolby	Surround Dolby	
None		4CN	None 4ch	<u>۴</u>	Front Dolby & Back Dolby *3	Front Dolby

*1 This can be selected when "Assign Mode" is set to "11.1ch" or "9.1ch" in the menu.

*3 This can be selected when "Assign Mode" is set to "11.1ch" and "Floor" - "Layout" is set to "5ch & SB" in the menu.







Pre-out

When "Assign Mode" is set to "11.1ch", selects the PRE OUT connector the external power amplifier used in MAIN ZONE. The PRE OUT connectors that can be selected differ depending on the combination of "Floor" - "Layout" and "Height" - "Layout" settings configured in the menu.

View Terminal Config.

This shows how to connect the speaker terminals and PRE OUT connectors for your "Amp Assign" setting on the menu screen.

Speaker Config.

Select whether or not speakers are present, playback capacity for low bass frequencies and speaker size.

• When speakers for which you assigned Height1 in "Amp Assign" are set to "None", "None" is automatically set for Height2.

Front

Set the front speaker size.

Large (Default):	Use a large speaker that can adequately play back very low bass frequencies.
Small:	Use a small speaker that has inadequate playback capacity for very low bass frequencies.

- When "Subwoofer" is set to "No", "Front" is automatically set to "Large".
- When "Front" is set to "Small", you cannot set speakers other than "Front" to "Large".

Front panel





Center

Set the presence and size of the center speaker.

Large:	Use a large speaker that can adequately play back very low bass frequencies.
Small (Default):	Use a small speaker that has inadequate playback capacity for very low bass frequencies.
None:	Select when a center speaker is not connected.

Subwoofer

Set the presence of a subwoofer.

2 spkrs:	Use two subwoofers.		
1 spkr (Default):	Use only one subwoofer.		
None:	Select when a subwoofer is not connected.		

• When "Subwoofer" is set to "None" and you set "Front" to "Small", "Subwoofer" is automatically set to "1 spkr".

Surround

Set the presence and size of the surround speakers.

Large:	Use a large speaker that can adequately play back very low bass frequencies.
Small (Default):	Use a small speaker that has inadequate playback capacity for very low bass frequencies.
None:	Select when the surround speakers are not connected.

• When "Surround" is set to "None", "Surr. Back", "Surround Dolby" and "Back Dolby" are automatically set to "None".





Surr. Back

Set the presence, size and number of surround back speakers.

Large:	Use a large speaker that can adequately play back very low bass frequencies.
Small (Default):	Use a small speaker that has inadequate playback capacity for very low bass frequencies.
None:	Select when the surround back speakers are not connected.
2 spkrs (Default):	Use two surround back speakers.
1 spkr:	Use only one surround back speaker. Connect to the L terminal to SURROUND BACK when this setting is selected.

• When "Surr. Back" is set to "None" or "1 spkr", "Back Dolby" is automatically set to "None".

Front Height

Set the presence and size of the front height speakers.

Large:	Use a large speaker that can adequately play back very low bass frequencies.
Small (Default):	Use a small speaker that has inadequate playback capacity for very low bass frequencies.
None:	Select when the front height speakers are not connected.

Top Front

Set the presence and size of the top front speakers.

Large:	Use a large speaker that can adequately play back very low bass frequencies.
Small (Default):	Use a small speaker that has inadequate playback capacity for very low bass frequencies.
None:	Select when the top front speakers are not connected.





Top Middle

Set the presence and size of the top middle speakers.

Large:	Use a large speaker that can adequately play back very low bass frequencies.
Small (Default):	Use a small speaker that has inadequate playback capacity for very low bass frequencies.
None:	Select when the top middle speakers are not connected.

Front Dolby

Set the presence and size of the front Dolby speakers.

Large:	Use a large speaker that can adequately play back very low bass frequencies.
Small (Default):	Use a small speaker that has inadequate playback capacity for very low bass frequencies.
None:	Select when the front Dolby speakers are not connected.

Surround Dolby

Set the presence and size of the surround Dolby speakers.

Large:	Use a large speaker that can adequately play back very low bass frequencies.
Small (Default):	Use a small speaker that has inadequate playback capacity for very low bass frequencies.
None:	Select when the surround Dolby speakers are not connected.

Top Rear

Set the presence and size of the top rear speakers.

Large:	Use a large speaker that can adequately play back very low bass frequencies.
Small (Default):	Use a small speaker that has inadequate playback capacity for very low bass frequencies.
None:	Select when the top rear speakers are not connected.



Rear Height

Set the presence and size of the rear height speakers.

Large:	Use a large speaker that can adequately play back very low bass frequencies.
Small (Default):	Use a small speaker that has inadequate playback capacity for very low bass frequencies.
None:	Select when the rear height speakers are not connected.

Back Dolby

Set the presence and size of the back Dolby speakers.

Large:	Use a large speaker that can adequately play back very low bass frequencies.
Small (Default):	Use a small speaker that has inadequate playback capacity for very low bass frequencies.
None:	Select when the back Dolby speakers are not connected.

• When speakers for which you assigned Height1 in "Amp Assign" are set to "None", "None" is automatically set for Height2.

Distances

Set distance from listening position to speakers.

Measure beforehand the distance from the listening position to each speaker.

Unit

Set the unit of distance.

Feet (Default)

Meters

Step

Set the minimum variable width of the distance.

1 ft / 0.1 ft (Default: 1 ft)

0.1 m / 0.01 m







Set the distance

0.0 ft - 60.0 ft / 0.00 m - 18.00 m

- The speakers that can be selected differ depending on the "Amp Assign" and "Speaker Config." settings. ("Amp Assign" (<u>\$\$ p. 205</u>), "Speaker Config." (<u>\$\$ p. 211</u>))
- Default settings:

Front L / Front R / F. Height L / F. Height R / Center / Front Dolby L / Front Dolby R / Subwoofer 1 / Subwoofer 2: 12.0 ft (3.60 m) Speakers other than the above: 10.0 ft (3.00 m)

• Set the difference in the distance between the speakers to less than 20.0 ft (6.00 m).

Dolby Speaker Setup

Set the distance between the Dolby Atmos Enabled speaker and the ceiling.

3.0 ft - 11.0 ft / 0.90 m - 3.30 m (Default: 6.0 ft / 1.80 m)

• This can be set when "Front Dolby", "Surround Dolby" or "Back Dolby" is set to "Large" or "Small" in "Speaker Config.".

Set Defaults

The "Distances" settings are returned to the default settings.







Levels

Set the volume of the test tone to be the same at the listening position when it is output from each speaker.

Test Tone Start

A test tone is output from the selected speaker.

While listening to the test tone, adjust the volume output from the selected speaker.

-12.0 dB - +12.0 dB (Default : 0.0 dB)

- The set "Levels" are reflected in all sound modes.
- If you wish to adjust the channel level for each input source, carry out the settings in "Channel Level Adjust". (2 p. 125)
- When headphones are connected to the PHONES connector on this unit, you cannot set "Levels".

Set Defaults

The "Levels" settings are returned to the default settings.







Crossovers

Set in accordance with the lower limit frequency of the base frequencies that can be played back through each speaker. See the speaker manual for information concerning speaker crossover frequency.

Speaker Selection

Selects how to set the crossover frequency.

All (Default):	Sets the same crossover frequency for all speakers.
Individual:	Selects the crossover points for each speaker individually.

Set the crossover frequency

40 Hz / 60 Hz / 80 Hz / 90 Hz / 100 Hz / 110 Hz / 120 Hz / 150 Hz / 200 Hz / 250 Hz (Default: 80 Hz)

Ø

- "Crossovers" can be set when the "Subwoofer Mode" setting is "LFE+Main", or when you have a speaker that is set to "Small". (127 p. 219)
- The default crossover frequency is "80 Hz", which will work best with the widest variety of speakers. We recommend setting to a higher frequency that the crossover frequency when small speakers are used. For example, set to "250 Hz" when the frequency range of the speakers is 250 Hz – 20 kHz.
- Sound below the crossover frequency is cut off from the output of the speakers set in "Small". This cut off bass frequency is output from the subwoofer or front speakers.
- The speakers that can be set when "Individual" is selected differ depending on to the "Subwoofer Mode" setting. (<u>Pp. 219</u>)
 - When "LFE" is selected, speakers set to "Small" at "Speaker Config." can be set. If the speakers are set to "Large", "Full Band" is displayed and the setting cannot be made. (Pp. 211)
 - When "LFE+Main" is selected, speakers can be set regardless of the "Speaker Config." setting. (Pp. 211)

Front panel

218



Bass

Set subwoofer and LFE signal range playback.

Subwoofer Mode

Select low range signals to be reproduced by subwoofer.

LFE (Default):	The low range signal of the channel set to "Small" speaker size is added to the LFE signal output from the subwoofer.
LFE+Main:	The low range signal of all channels is added to the LFE signal output from the subwoofer.

- "Subwoofer Mode" can be set when "Speaker Config." "Subwoofer" in the menu is set to other than "None". ((資一<u>p. 212</u>)
- Play music or a movie source and select the mode offering the strongest bass.
- If "Speaker Config." "Front" and "Center" are set to "Large", and "Subwoofer Mode" is set to "LFE", no sound may be output from the subwoofers, depending on the input signal or selected sound mode. (<u>Pr. 211</u>) Select "LFE+Main" if you want the bass signals to always be produced from the subwoofer.

LPF for LFE

Set LFE signal playback range. Set this when you want to change the playback frequency (low pass filter point) of the subwoofer.

80 Hz / 90 Hz / 100 Hz / 110 Hz / 120 Hz / 150 Hz / 200 Hz / 250 Hz (Default: 120 Hz)











Front Speaker

Set the front speaker A/B to use for every sound mode.

A (Default):	Front speaker A is used.
B:	Front speaker B is used.
A+B :	Both front speakers A and B are used.

• This can be set when "Assign Mode" is set to "7.1ch + Front B". (p. 207)









Network

To use this unit by connecting it to a home network (LAN), you must configure network settings.

If you set up your home network (LAN) via DHCP, set "DHCP" to "On". (Use the default setting.) This allows this unit to use your home network (LAN). When assigning an IP address to each device manually, you need to assign an IP address to this unit using the "IP Address" settings, and enter information about your home network (LAN) such as the gateway address and subnet mask, etc.

Information

Display network information.

Friendly Name / Connection / SSID / DHCP / IP Address / MAC Address (Ethernet) / MAC Address (Wi-Fi) / Wi-Fi signal strength

Connection

Choose whether to connect the home network to a wireless LAN or a wired LAN.

When connecting to the network using wired LAN, select "Wired (Ethernet)" after connecting a LAN cable.

When connecting to the network using wireless LAN, select "Wireless (Wi-Fi)" and configure the "Wi-Fi Setup". ($\mathbb{CP} p.222$)

Connect Using

Select the method for connecting to the home network (LAN).

Wired (Ethernet):	Use a LAN cable to connect to a network.
Wireless (Wi-Fi)	Use the wireless LAN (Wi-Fi) function to
(Default):	connect to a network.

Front panel



Wi-Fi Setup

Connect to a wireless LAN (Wi-Fi) router.

The router can be connected in the following ways. Select the connection method to suit your home environment.

Scan Networks

Select the network you wish to connect to from the list of possible networks shown on the TV screen.

1. Select the network you wish to connect to from the list of wireless networks.

Select "Rescan" if the network cannot be found.

2. Enter your password and select "OK".

Use iOS Device

Use your iOS device (iPhone/iPod/iPad) to connect to the network. By connecting your iOS device to this unit using Wi-Fi, the unit can be automatically connected to the same network as your device.

- 1. Select "Use iOS Device" on the TV screen.
- Check that your iOS device is connected to the wireless LAN (Wi-Fi) router and select "Marantz SR6013" from "SET UP NEW AIRPLAY SPEAKER..." at the bottom of the Wi-Fi configuration screen of your iOS device.
- 3. Tap "Next" on the screen of the iOS device.

• The iOS device firmware version needs to support iOS 7 or later.







WPS Router

Use a WPS-compatible router to connect using the push button method.

- 1. Select "Push Button" on the TV screen.
- 2. Switch to the WPS mode by pressing the WPS button of the router you wish to connect to.
 - The time for pressing the button varies depending on the router.
- 3. Select "Connect" on the TV screen within 2 minutes.

Manual

Enter the name (SSID) and password of the network you wish to connect to.

1. Set the following items.

SSID:	Input the name of the wireless network (SSID).
Security:	Select the encryption method according to the encryption setting of the access point you are using.
Password:	Input the password.

2. Select "Connect" at the end of the setting.

- The wireless LAN (Wi-Fi) settings of this unit can also be configured from a PC or tablet that supports wireless LAN connection.
 - 1. Press and hold the ZONE2 SOURCE and TUNER PRESET CH + buttons on the main unit for at least 3 seconds when the power of the unit is on.
 - Connect the wireless LAN of the PC or tablet used to "Marantz SR6013" when the message "Connect your Wi-Fi device to Wi-Fi network called "Marantz SR6013"." appears in the display.
- 3. Start up the browser and enter "192.168.1.16/Settings/" in the URL.
- 4. Use the browser to enter the settings, select "Connect" and then exit the settings.
- The Default key of this unit is fixed at "1". Set Default key of the router to "1" to use.










Settings

Configure the IP address.

- If you are using a broadband router (DHCP function), the information required for network connection such as the IP address will be automatically configured since the DHCP function is set to "On" in the default settings of this unit.
- Set up the IP Address, Subnet Mask, Default Gateway and DNS server information only when assigning a fixed IP address or when connecting to a network without DHCP function.



DHCP

Selects how to connect to the network.

On	Configure the network settings
(Default):	automatically from your router.
Off:	Configure the network settings manually.

IP Address

Set the IP address within the ranges shown below.

The Network Audio function cannot be used if other IP addresses are set.

CLASS A: 10.0.0.1 - 10.255.255.254 CLASS B: 172.16.0.1 - 172.31.255.254 CLASS C: 192.168.0.1 - 192.168.255.254

Subnet Mask

When connecting an xDSL modem or connector adapter directly to this unit, input the subnet mask indicated in the documentation supplied by your provider. Normally input "255.255.255.0".

Front panel



224





Default Gateway

When connected to a gateway (router), input its IP address.

DNS

Enter the DNS address indicated in the documentation supplied by your provider.

- If you cannot connect to the Internet, recheck the connections and settings. ($(\underline{\mathcal{T}p.78})$
- If you do not understand about Internet connection, contact your ISP (Internet Service Provider) or the store from which you purchased your computer.

Network Control

Enables network communication in standby power mode.

Off In Standby:	Suspend network function during standby.
Always On (Default):	Network is on during standby. Main unit operable with a network compatible controller.

• When using the web control function, Marantz 2016 AVR Remote App or HEOS App, use with the "Network Control" setting set to "Always On".

NOTE

When "Network Control" is set to "Always On", the unit consumes more standby power.





Friendly Name

The Friendly Name is the name of this unit displayed on the network. You can change the Friendly Name according to your preferences.

Friendly Name

Selects Friendly Name from the list.

When you select "Other", you can change the Friendly Name according to your preferences.

Home Theater /Living Room / Family Room / Guest Room / Kitchen / Dining Room / Master Bedroom / Bedroom / Den / Office / Other

- Up to 30 characters can be input.
- The default Friendly Name on first use is "Marantz SR6013".

Set Defaults

Restores Friendly Name, which you had changed, to the default setting.

Diagnostics

Used to check the network connection.

Physical Connection

Checks the physical LAN port connection.

ОК	
Error:	The LAN cable is not connected. Check the connection.

When connected using a wireless LAN, "Connection Wireless (Wi-Fi)" will be displayed.

Router Access

Checks the connection from this unit to the router.

ОК	
Error:	Failed to communicate with the router. Check the router settings.

Front panel







С	o	nt	eı	nts

Internet Access

Checks whether this unit has access to the Internet (WAN).

ОК
Error:



HEOS Account

Make HEOS Account-related settings.

HEOS Account is needed in order to use HEOS Favorites.

The menu displayed differs depending on the status of the HEOS Account.

You have not signed in

I have a HEOS Account

If you already have a HEOS Account, enter the current account name and password to sign in.

Create Account

If you do not have a HEOS Account, create a new HEOS Account.

Forgot Password

If you have forgotten the password, an email explaining how to reset the password will be sent.

You have already signed in

Signed in As

The currently signed in HEOS Account is displayed.

Change Location

Change the regional settings for the signed in HEOS Account.

Change Password

Change the password for the signed in HEOS Account.

Delete Account

Delete the signed in HEOS Account.

Sign Out

Sign out from the HEOS Account.





General

Make various other settings.

Language

Set the language for display the menu on the TV screen.

English / Français / Español (Default: English)

- "Language" can also be set up by the following operation. However, the menu screen is not displayed. Watch the display while configuring the settings.
- 1. Press and hold the main unit's ZONE2 SOURCE and STATUS at the same time for at least 3 seconds.

"Video Format <NTSC>" appears on the display.

2. Press DIMMER on the main unit twice.

"GUI Language ENGLISH" appears on the display.

- 3. Use the main unit's TUNER PRESET CH + or TUNER PRESET CH and set the language.
- 4. Press the main unit's STATUS to complete the setting.

ECO

Configure the ECO Mode and auto standby mode settings.

ECO Mode

This mode can reduce the power consumption and heat generation of your AV receiver when power on.

This is done by reducing the power supply line to the power amplifier, in turn the maximum power output.





Playback

On:	Power savings are always active, regardless of volume or input signal.
Auto:	Gives you the best balance between power savings and maximum power output: For low volume levels, the power savings are active. If you increase the volume level, the power savings are switched off automatically, so you can enjoy maximum output power without distortion. If the volume is set to a high level but no input signal is detected for more than 2 minutes, this unit will enable power savings. When an input signal is detected again or the input source is changed, this unit will automatically turn off power savings again at high volume levels.
Off (Default):	No power savings.

- When the unit is switching between the different power saving states in "ECO Mode: Auto", you may notice a click noise from the inside of this unit, this is normal.
- If content is paused for more than 2 minutes and playback is resumed from the same source at these high volume levels, there may be short delay before maximum power is restored.

Front panel





Power On Default

Set the mode to ECO when the power is on.

Last (Default):	The ECO Mode will be set to the previous setting before the power was switched off.
On:	When power is turned on, the mode will always be switched to the ECO Mode in "On".
Auto:	When power is turned on, the mode will always be switched to the ECO Mode in "Auto".
Off:	When power is turned on, the mode will always be switched to the ECO Mode in "Off".

On Screen Display

Display the power consumption of this unit using a meter on the TV screen.

Always On:	Always display the meter on the TV screen.
Auto (Default):	Display the meter when changing the mode or volume.
Off:	Do not display the meter.







Auto Standby

Set so the unit power automatically switches to standby.

MAIN ZONE

Sets the time for switching to auto standby when there are no audio or video signals input into this unit.

Before the unit enters standby mode, "Auto Standby" is displayed on the unit display and the menu screen.

60 min:	The unit goes into standby after 60 minutes.
30 min:	The unit goes into standby after 30 minutes.
15 min:	The unit goes into standby after 15 minutes.
Off (Default):	The unit does not go into standby automatically.

ZONE2

When there are no operations for a certain period of time as set here, the power is automatically shut off even if there is audio or video input.

8 hours:	Switches ZONE2 the standby state after about 8 hours.
4 hours:	Switches ZONE2 to the standby state after about 4 hours.
2 hours:	Switches ZONE2 to the standby state after about 2 hours.
Off (Default):	Does not automatically switch ZONE2 to the standby state.





ZONE2 Setup

Makes settings for audio playback with ZONE2.

 Values set for "Volume Limit" and "Power On Volume" are displayed according to the setting specified for the volume "Scale". (27 p. 170)

Bass

Adjust bass.

-10 dB - +10 dB (Default : 0 dB)

Treble

Adjust treble.

-10 dB - +10 dB (Default : 0 dB)

High Pass Filter

Make settings for cutting the low range to reduce distortion in the bass.

On:	The low range is attenuated.
Off (Default):	The low range is not attenuated.

Lch Level

Adjust the left channel output level.

-12 dB - +12 dB (Default : 0 dB)

Rch Level

Adjust the right channel output level.

-12 dB - +12 dB (Default : 0 dB)

Channel

Set whether to playback in stereo or monaural.

Stereo (Default):	Stereo playback.
Mono:	Monaural playback.



233



HDMI Audio

Selects the audio signal format for playing an HDMI source in ZONE2.

Through (Default):	The HDMI audio signal is passed through this unit to the device in ZONE2.
PCM:	The HDMI audio signal input into this unit is converted to a PCM signal that can be output from the ZONE2 PRE OUT connectors or speaker terminals.

Volume Level

Set the volume output level.

Variable (Default):	Volume can be adjusted.
1 – 98 (–79 dB – 18 dB):	Volume is fixed at the desired level. The volume cannot be adjusting using the remote control unit.

The dB value is displayed when the "Scale" setting is "-79.5 dB - 18.0 dB".
 (P. 170)

Volume Limit

Make a setting for maximum volume.

60 (-20 dB) / 70 (-10 dB) / 80 (0 dB)
(Default : 70 (-10 dB))

Do not set a maximum volume.

Off:

- This can be set when "Volume Level" is set to "Variable". (1) <u>p. 234</u>)
- The dB value is displayed when the "Scale" setting is "-79.5 dB 18.0 dB".
 (12) p. 170)

Power On Volume

Define the volume setting that is active when the power is turned on.

Last (Default):	Use the memorized setting from the last session.
Mute:	Always mute when power is turned on.
1 – 98 (–79 dB – 18 dB):	The volume is adjusted to the set level.

- This can be set when "Volume Level" is set to "Variable". (mp. 234)
- The dB value is displayed when the "Scale" setting is "-79.5 dB 18.0 dB".
 (CP p. 170)

234





Mute Level

Set the amount of attenuation when muting is on.

Full (Default):	The sound is muted entirely.
-40 dB :	The sound is attenuated by 40 dB down.
-20 dB :	The sound is attenuated by 20 dB down.

Zone Rename

Change the display title of each zone to one you prefer.

MAIN ZONE / ZONE2

Set Defaults: The default setting is restored for the edited zone name.

• Up to 10 characters can be input.

Smart Select Names

Change the smart select name that appears on the TV screen to one you prefer.

Smart Select 1 / Smart Select 2 / Smart Select 3 / Smart Select 4

Set Defaults:	The default setting is restored for the edited
Set Delauits.	smart select name.

• Up to 16 characters can be input.









Tips

Trigger Out

Select the conditions for activating trigger out. For details about how to connect the DC OUT jack, see "DC OUT jack" (\underline{rr} <u>p. 81</u>).

□ When setting for zone (MAIN ZONE / ZONE2)

Trigger out is activated through linkage to the power of the zone set to "On".

□ When setting for input source

Activate trigger out when the input source set to "On" is selected.

When setting for HDMI monitor

Activate trigger out when the HDMI monitor set to "On" is selected.

On:	Activate trigger on this mode.
:	Do not activate trigger on this mode.

Front Display

Makes settings related to the display on this unit.

Dimmer

Adjust the display brightness of this unit.

Bright (Default):	Normal display brightness.
Dim:	Reduced display brightness.
Dark:	Very low display brightness.
Off:	Turns the display off.

Ø

• You can also adjust the display by pressing DIMMER on the main unit.







Firmware

Checks for the latest firmware information about updates and upgrades, updates the firmware, and sets up the notification message display for upgrades.

Check for Update

Check for firmware updates.

The firmware can be updated if a firmware update has been released.

Update Now:	Execute the update process. When the update starts, the menu screen is shut down. During the update, the progress is shown on the display.
Update Later:	Update later.

 This unit automatically retries updating if updating fails. If an update still cannot be performed, an "Update Error" message appears in the display. See "Troubleshooting" – "Update/upgrade error messages" for information on update error messages. (IFP p. 267)

Check the conditions according to the message and try the update again.

• This menu cannot be selected when "Allow Update" is set to "Off".

Auto-Update

Turns on Automatic Updates so that futures updates are automatically downloaded and installed when this unit is in standby mode.

□ Auto-Update

This unit will automatically update to the newest firmware when in standby mode.

On:	Turns on Automatic Updates.	
Off (Default):	Turns off Automatic Updates.	

Time Zone

Change the time zone.

Set the time zone that matches the area where you live.



• This menu cannot be selected when "Allow Update" is set to "Off".





Allow Update

Enable or disable updates and upgrades for this unit.

On (Default):	Enables this unit to receive updates and upgrades.
Off:	Prevents this unit from receiving update and upgrade.

• This setting causes Incompatibilities between this unit and HEOS App.

Upgrade Notification

When the latest Upgrade firmware is available, a notification message is displayed on the TV screen at power on.

The notification message is displayed for about 40 seconds when the power is turned on.

On (Default):	Display upgrade message.
Off:	Do not display upgrade message.

• This menu cannot be selected when "Allow Update" is set to "Off".









Add New Feature

Display new features that can be downloaded to this unit and perform an upgrade.

Upgrade Package:	Display the items to be upgraded.
Upgrade Status: Display a list of the additional fun provided by the upgrade.	
Upgrade:	Execute the upgrade process. When the upgrade starts, the menu screen is shut down. During the upgrade, the amount of upgrade time which has elapsed is displayed.

- Information regarding the "Update" function and "Add New Feature" will be announced on the Marantz website each time related plans are defined. See the Marantz website for details about upgrades.
- When the procedure is complete, "Registered" is displayed in this menu and upgrades can be carried out. If the procedure has not been carried out, "------" is displayed.

The ID number shown on this screen is needed when carrying out the procedure.

The ID number can also be displayed by pressing and holding the main unit's STATUS and SOUND MODE for at least 3 seconds.

 If the upgrade is not successful, "Upgrade Error" message appears in the display. See "Troubleshooting" – "Update/upgrade error messages" for information on upgrade error messages. (127 p. 267) Check the settings and network environment and then perform the upgrade again.

• This menu cannot be selected when "Allow Update" is set to "Off".

Notes concerning use of "Update" and "Add New Feature"

- In order to use these functions, you must have the correct system requirements and settings for an Internet connection. (<u>P. p. 78</u>)
- Do not turn off the power until updating or upgrading is completed.
- Approximately 1 hour is required for the updating/upgrading procedure to be completed.
- Once updating/upgrade starts, normal operations on this unit cannot be performed until updating/upgrading is completed. Furthermore, there may be cases where backup data is reset for the parameters, etc., set on this unit.
- If the update or upgrade fails, press and hold the O on the main unit for more than 5 seconds, or remove and re-insert the power cord. After about 1 minute, "Please wait" appears on the display and update restarts. If the error continues, check the network environment.



239



240

Video

Show the HDMI input/output signals and HDMI monitor information for MAIN ZONE.

Tips

HDMI Signal Info.

Resolution / HDR / Color Space / Pixel Depth

HDMI Monitor 1 / HDMI Monitor 2

Interface / HDR / Resolutions

ZONE

Show information about current settings.

MAIN ZONE:	This item shows information about settings for MAIN ZONE. The information displayed differs according to the input source.
ZONE2:	This item shows information about settings for ZONE2.

Firmware

Version:	Displays information for the current firmware.
DTS Version:	Displays the current DTS version.

Playback



Information

Sound Mode:

Input Signal:

Sample Rate:

Format:

Offset:

Flag:

Audio

Show information about this unit settings, input signals, etc.

Show the audio information for MAIN ZONE.

Connections

The currently set sound mode.

The number of input signal channels

The input signal's sampling frequency. The dialogue normalization correction

This is displayed when inputting signals including a surround back channel. "MATRIX" is displayed with DTS-ES

Matrix input signals, "DISCRETE" with

DTS-ES Discrete signals.

(presence of front, surround, LFE).

The input signal type.

value.

Notifications

Displays and sets notifications.

Also, sets whether or not to display the notification when the power is turned on.

Notification Alerts

On (Default):	Notification messages are displayed.
Off:	Notification messages are not displayed.

• Press INFO on the remote control unit to display current source name, volume, sound mode name, and other information at the bottom of the screen.



Usage Data

To help us improve our products and customer service, Marantz collects anonymous information about how you use this unit (such as frequently used input sources and sound modes and speaker settings). Marantz will never provide any information we collect to third parties.

Yes:	Provide information on the operating status of this unit.
No:	Do not provide information on the operating status of this unit.





Index



Save & Load

Save and restore device settings by using a USB memory device.

- Use a USB memory device that has at least 128 MB of free space and is formatted to FAT32. Data may not Save/Load correctly to some USB memory devices.
- It may take up to 10 minutes for data to Save/Load. Do not turn off the power until the process is complete.

Save Configuration

Current unit settings are stored on the USB memory device. When the settings are saved correctly, "Saved" appears on the display and the file "config.avr" is created on the USB memory device.

• Do not change the file name of the created file. Doing so will prevent the file from being recognized as a settings file when restoring.

Load Configuration

Settings saved on the USB memory device are restored.

When the saved settings are restored correctly, "Loaded" appears on the display and the unit automatically restarts.

Setup Lock

Protect settings from inadvertent changes.

Lock

On:	Turn protection on.	
Off (Default):	Turn protection off.	

• When cancelling the setting, set "Lock" to "Off".

NOTE

• When "Lock" is set to "On", no setting items are displayed except for "Setup Lock".





242



Reset

Returns settings to the factory default.

Initialization can be performed for all unit settings or for Network settings only.

All Settings

All settings are reset to the factory default values.

Network Settings

Only network settings are reset to the factory default values.


- Before returning the settings to the default settings, use the "Save & Load" function from the menu to save and restore the details of various settings configured on the unit. (27 p. 242)
- The "Reset" operation can also be performed by using the button on the main unit. For details on resetting all of the settings to the factory defaults see "Resetting factory settings" (<u>P p. 268</u>), and for details on resetting the network settings to the factory defaults see "Resetting network settings" (<u>P p. 269</u>).

NOTE

• Do not disconnect the power or turn the device off during network settings initialization.







Front panel



Contents

Tips

I want the volume not to become too loud by mistake	246
I want to keep the volume at the same level when I turn the power on	246
I want to have the subwoofer always output audio	246
I want to make human voices in the movies clearer	246
I want to keep bass and clarity during playback at a lower volume level	246
I want to automatically adjust the volume level difference in content such as TV and movies	246
I want to set the optimized listening environment after changing the configuration/position of the speakers or changing a speaker to a new one	247
I want to combine a desired video with the current music	247
I want to skip unused input sources	247
I want to enjoy the same music in all zones at the home party, etc.	247
I want to minimize the delay in video signals when I'm playing a game on my game console	247
I want to operate this unit using the TV remote control	247

Connections

Troubleshooting

Settings

Power does not turn on / Power is turned off	249
Operations cannot be performed through the remote control unit	250
Display on this unit shows nothing	250
No sound comes out	251
Desired sound does not come out	252
Sound is interrupted or noise occurs	255
No video is shown on the TV	256
The menu screen is not displayed on the TV	258
The color of the menu screen and operations content displayed on the television is different from normal	258
AirPlay cannot be played back	259
USB memory devices cannot be played back	260
Bluetooth cannot be played back	261
The Internet radio cannot be played back	262
Music files on PC or NAS cannot be played back	263
Various online services cannot be played	264
The HDMI Control function does not work	264
Cannot connect to a wireless LAN network	265
When using HDMI ZONE2, the devices does not function properly	266
Update/upgrade error messages	267

Tips

Rear panel

245

Remote



Playback

 $\langle \rangle$

Tips

I want the volume not to become too loud by mistake

• Set the volume upper limit for "Volume Limit" in the menu beforehand. This prevents children or others from increasing the volume too much by mistake. You can set this for each zone. (" Volume " (197 p. 170), " Volume Limit " (197 p. 234))

I want to keep the volume at the same level when I turn the power on

By default, the volume setting when power was previously set to standby on this unit is applied at next power on with no change. To use a fixed volume level, set the volume level at power on for "Power On Volume" in the menu. You can set this for each zone. (" Volume " (<u>p. 170</u>), " Power On Volume" (<u>p. 234</u>))

I want to have the subwoofer always output audio

• Depending on the input signals and sound mode, the subwoofer may not output audio. When "Subwoofer Mode" in the menu is set to "LFE+Main", you can have the subwoofer always output audio. (12 p. 219)

I want to make human voices in the movies clearer

• Use "Center Level Adjust" in the menu to adjust the level. (12 p. 164)

I want to keep bass and clarity during playback at a lower volume level

• Set "Dynamic EQ" in the menu to "On". This setting corrects the frequency characteristics to allow you to enjoy clear sound without the bass being lost even during playback at a lower volume level. (1) 172)

I want to automatically adjust the volume level difference in content such as TV and movies

• Set "Dynamic Volume" in the menu. Volume level changes (between quiet scenes and loud scenes) in TV shows or movies are automatically adjusted to your desired level. (137 p. 173)

I want to set the optimized listening environment after changing the configuration/position of the speakers or changing a speaker to a new one

• Perform Audyssey® Setup. This automatically makes the optimized speaker settings for the new listening environment. (13 p. 194)

I want to combine a desired video with the current music

 Set "Video Select" in the option menu to "On". You can combine the current music with your desired video source from a Set-top Box or DVD, etc. while listening to music from the Tuner, CD, Phono, HEOS Music, USB or Bluetooth. (Pp. 127)

I want to skip unused input sources

• Set unused input sources for "Hide Sources" in the menu. This allows you to skip unused input sources when turning the INPUT SELECTOR knob on this unit. (197 p. 192)

I want to enjoy the same music in all zones at the home party, etc.

• Set "All Zone Stereo" in the option menu to "Start". You can simultaneously play back music in another room (ZONE2) that is played back in MAIN ZONE. (127 p. 129)

I want to minimize the delay in video signals when I'm playing a game on my game console

• When the video is delayed against button operations with the controller on the game console, set "Video Mode" in the menu to "Game". (19 p. 184)

I want to operate this unit using the TV remote control

- Select "AV Receiver" in a TV menu such as "Input" * or "Operate Connected HDMI Device" *. The Smart Menu of this unit is displayed on the TV. This Smart Menu can be operated using the remote control of your TV.
- * The selection method differs depending on your TV. See the owner's manual of your TV for details.



	Contents	\bigvee	Connections	\bigvee	Playback	\bigvee	Settings	\bigvee	Tips	\bigvee	Appendix	
--	----------	-----------	-------------	-----------	----------	-----------	----------	-----------	------	-----------	----------	--

Troubleshooting

If a problem should arise, first check the following:

- 1. Are the connections correct?
- 2. Is the set being operated as described in the owner's manual?
- 3. Are the other devices operating properly?

If steps 1 to 3 above do not improve the problem, restarting the device may improve the problem.
 Continue pressing the Φ button on the unit until "Restart" appears in the display, or remove and re-insert the power cord of the unit.

If this unit does not operate properly, check the corresponding symptoms in this section.

If the symptoms do not match any of those described here, consult your dealer as it could be due to a fault in this unit. In this case, disconnect the power immediately and contact the store where you purchased this unit.



Settings

Index

Power does not turn on / Power is turned off

Power does not turn on.

Front panel

• Check whether the power plug is correctly inserted into the power outlet. (127 p. 82)

Power automatically turns off.

- The sleep timer is set. Turn on the power again. (127 p. 145)
- "Auto Standby" is set. "Auto Standby" is triggered when there is no operation for a set amount of time. To disable "Auto Standby", set "Auto Standby" on the menu to "Off". (127 p. 232)

Power turns off and the power indicator flashes in red approx. every 2 seconds.

- The protection circuit has been activated due to a rise in temperature within this unit. Turn the power off, wait about an hour until this unit cools down sufficiently, and then turn the power on again. (127 p. 295)
- Please re-install this unit in a place having good ventilation.

Power turns off and the power indicator flashes in red approx. every 0.5 seconds.

- Check the speaker connections. The protection circuit may have been activated because speaker cable core wires came in contact with each other or a core wire was disconnected from the connector and came in contact with the rear panel of this unit. After unplugging the power cord, take corrective action such as firmly re-twisting the core wire or taking care of the connector, and then reconnect the wire. ((Pp. 37))
- Turn down the volume and turn on the power again. (12 p. 84)

Display

• This unit's amplifier circuit has failed. Unplug the power cord and contact our customer service center.

Power does not turn off even when the power button is pressed, and the display shows "ZONE2 On".

• The power supply of ZONE2 is turned to ON. To turn off the power supply of this unit (standby), press the ZONE2 ON/OFF on the main unit, or press the POWER Φ button after pressing the ZONE2 button on the remote control unit to turn off the power supply of ZONE2.

The power to this unit does not turn off when you press the Power operation button. "HEOS On" appears on the display.

Rear panel

• A HEOS device on the same network is playing an input source from this unit. Stop playback on the HEOS device when turning this unit off (setting it to standby). The power of this unit will turn off automatically after around 20 minutes.

249

Remote

Operations cannot be performed through the remote control unit

Operations cannot be performed through the remote control unit.

- Batteries are worn out. Replace with new batteries. (12 p. 9)
- Operate the remote control unit within a distance of about 23 ft/7 m from this unit and at an angle of within 30°. (127 p. 9)
- Remove any obstacle between this unit and the remote control unit.
- Insert the batteries in the proper direction, checking the \oplus and Θ marks. (127 p. 9)
- The set's remote control sensor is exposed to strong light (direct sunlight, inverter type fluorescent bulb light, etc.). Move the set to a place in which the remote control sensor will not be exposed to strong light.
- The operation target zone does not correspond to the zone setting specified on the remote control unit. Press the MAIN or ZONE2 button to select the operating zone of the remote control. (127 p. 163)
- When using a 3D video device, the remote control unit of this unit may not function due to effects of infrared communications between units (such as TV and glasses for 3D viewing). In this case, adjust the direction of units with the 3D communications function and their distance to ensure they do not affect operations from the remote control unit of this unit.

Display on this unit shows nothing

Display is off.

- Set "Dimmer" on the menu to something other than "Off". (p. 236)
- When the sound mode is set to "Pure Direct", the display is off. (p. 132)







No sound comes out

No sound comes out of speakers.

- Check the connections for all devices. (Pp. 37)
- · Insert connection cables all the way in.
- · Check that input connectors and output connectors are not reversely connected.
- Check cables for damage.
- Check that speaker cables are properly connected. Check that cable core wires come in contact with the metal part on speaker terminals. (127 p. 37)
- Securely tighten the speaker terminals. Check speaker terminals for looseness. (1) p. 37)
- Check that a proper input source is selected. (2 p. 84)
- Adjust the volume. (main p. 85)
- Cancel the mute mode. (2 p. 85)
- Check the digital audio input connector setting. (p. 190)
- Check the digital audio output setting on the connected device. On some devices, the digital audio output is set to off by default.
- When a headphone is plugged into the PHONES jack on the main unit, sound is not output from the speaker terminal and PRE OUT connector.

No sound comes out when using the DVI-D connection.

• When this unit is connected to a device equipped with a DVI-D connector, no sound is output. Make a separate audio connection.

No sound comes out of a TV that is connected via HDMI.

• Audio signals input to 7.1CH IN connectors on this unit cannot be output to the TV.



Settings

Desired sound does not come out

The volume does not increase.

- The maximum volume is set too low. Set the maximum volume using "Limit" on the menu. (12 p. 170)
- Appropriate volume correction processing is performed according to the input audio format and settings, so the volume may not reach the upper limit.

No sound comes out with the HDMI connection.

- Check the connection of the HDMI connectors. (
 <u>p. 65</u>)
- When outputting HDMI audio from the speakers, set "HDMI Audio Out" on the menu to "AVR". To output from the TV, set "TV". (@p. 178)
- When using the HDMI Control function, check that the audio output is set to the AV amplifier on the TV. (127 p. 142)

When an eARC function-compatible television is connected, television audio is not output from the speaker connected to this unit

- eARC function settings may be required depending on the eARC function-compatible television you are using. Make sure eARC is set to on if this setting exists on your television. For more information, check your television's owner's manual.
- Make sure the input source of this unit is "TV Audio".
- The eARC function does not operate when the HDMI input connector is set to the "TV Audio" input source. To enable eARC function operation, remove the HDMI input connector setting, then restart this unit and the television.

No sound comes out of a specific speaker.

- Check that speaker cables are properly connected.
- Check that a selection other than "None" is set for the "Speaker Config." setting in menu. (12 p. 211)
- Check the "Assign Mode" setting in the menu. (mp. 205)
- When the sound mode is "Stereo" and "Virtual", audio is only output from the front speakers and subwoofer.



No sound is produced from subwoofer.

- Check the subwoofer connections.
- Turn on the subwoofer's power.
- Set "Speaker Config." "Subwoofer" in the menu to "1 spkr" or "2 spkrs". (p. 212)
- When "Speaker Config." "Front" in the menu is set to "Large", depending on the input signal and the sound mode, no sound may be output from the subwoofer. (127 p. 212)
- When no subwoofer audio signal (LFE) is included in the input signals, no sound may be output from the subwoofer. (19 p. 219)
- You can make the subwoofer always output sound by setting the "Subwoofer Mode" to "LFE+Main". (19 p. 219)

DTS sound is not output.

• Check that the digital audio output setting on the connected device is set to "DTS".

Dolby Atmos, Dolby TrueHD, DTS-HD, Dolby Digital Plus audio is not output.

- Make HDMI connections. (Pp. 70)
- Check the digital audio output setting on the connected device. On some devices, "PCM" is set by default.

DTS Neural:X mode cannot be selected.

• DTS Neural:X cannot be selected when using the headphones.

Dolby Surround mode cannot be selected.

• Dolby Surround cannot be selected when using the headphones.

Sound modes other than "Stereo" or "Direct" cannot be selected.

• Only "Stereo" or "Direct" can be selected for the sound mode if Headphone:X signals are input.



Audyssey MultEQ[®] XT32, Audyssey Dynamic EQ[®], Audyssey Dynamic Volume[®] and Audyssey LFC[™] cannot be selected.

- These cannot be selected when you have not performed Audyssey[®] Setup. (197 p. 194)
- Switch to a sound mode other than "Direct" or "Pure Direct". (2 p. 132)
- These cannot be selected when sound mode is "DTS Virtual:X" or sound mode that have "+Virtual:X" in the sound mode name.
- These cannot be selected when using the headphones.

"M-DAX" cannot be selected.

- Check that an analog signal or PCM signal (Sample Rate = 44.1/48 kHz) is input. For playback of multichannel signals such as Dolby Digital or DTS surround, "M-DAX" cannot be used. (127 p. 168)
- Switch to a sound mode other than "Direct" or "Pure Direct". (2 p. 132)

No audio is output from PRE OUT or speakers for ZONE2.

- In ZONE2, the audio can be played back when signals input from digital connectors (OPTICAL/COAXIAL) are in 2ch PCM format.
- In ZONE2, the audio can be played back when signals input from the HDMI connector are in 2ch PCM format. To play back the audio in ZONE2 irrespective of the input signal format, set "HDMI Audio" in the menu to "PCM". Depending on the played back device, the audio may not be played back even with this setting. In that case, set the audio format to "PCM (2ch)" on the played back device. (12) p. 234)
- When listening to audio from a Bluetooth device in ZONE2, remove any obstructions between the Bluetooth device and this unit and use it within a range of about 98.4 ft/30 m.





Sound is interrupted or noise occurs

During playback from the Internet radio or USB memory device, sound is occasionally interrupted.

- When the transfer speed of the USB memory device is slow, sound may occasionally be interrupted.
- The network communication speed is slow or the radio station is busy.

When making a call on iPhone, noise occurs in audio output on this unit.

• When making a call, keep a distance of 0.7 ft/20 cm or longer between iPhone and this unit.

Noise often occurs in FM/AM broadcasting.

- Change the antenna orientation or position. (mp. 76)
- Separate the AM loop antenna from the unit.
- Use an outdoor antenna. (12 p. 76)
- Separate the antenna from other connection cables. (12 p. 76)

The sounds appear to be distorted.

- Lower the volume. (2 p. 85)
- Set "Off" to the "ECO Mode". When "On" or "Auto" is in the "ECO Mode", the audio may by distorted when the playback volume is high. (1) p. 229)

Sound cuts out when using Wi-Fi connection.

- The frequency band used by the wireless LAN is also used by microwave ovens, cordless telephones, wireless game controllers and other wireless LAN devices. Using such devices at the same time as this unit may cause sound to cut out due to electronic interference. Sound cut out can be improved using the following methods. (127 p. 78)
 - Install devices that cause interference away from this unit.
 - Turn off the power supply to devices that cause interference.
 - Change the settings of the router channel to which this unit is connected to. (See the instruction manual of the wireless router for details on how to change the channel.)
 - Switch to a wired LAN connection.
- Particularly when you play back large music files, depending on your wireless LAN environment, the playback sound may be interrupted. In this case, make the wired LAN connection. (127 p. 222)









No video is shown on the TV

No picture appears.

- Check the connections for all devices. (2 p. 65)
- Insert connection cables all the way in.
- · Check that input connectors and output connectors are not reversely connected.
- Check cables for damage.
- Match the input settings to the input connector of the TV connected to this unit. (127 p. 190)
- Check that the proper input source is selected. (12 p. 84)
- Check the video input connector setting. (p. 190)
- Check that the resolution of the player corresponds to that of the TV. (12 p. 240)
- Check whether the TV is compatible with copyright protection (HDCP). If connected to a device not compatible with HDCP, video will not be output correctly. (127 p. 272)
- To enjoy content that is copyright protected by HDCP 2.2, use a playback device and TV compatible with HDCP 2.2 only.
- The HDMI signal cannot be converted to an analog signal. Use analog connections. (127 p. 273)
- To play back a 4K (60/50Hz) video, use a "High Speed HDMI Cable" or an "High Speed HDMI Cable with Ethernet". In order to achieve a higher fidelity for 4K (60/50Hz) videos, it is recommended to use a "Premium High Speed HDMI Cables" or an "Premium High Speed HDMI Cables with Ethernet" that has an HDMI Premium Certified Cable label on the product package.

No video is shown on the TV with the DVI-D connection.

• With the DVI-D connection, on some device combinations, devices may not function properly due to the copy guard copyright protection (HDCP). (<u>P. 272</u>)



No video from an input source such as a game console is shown on the TV.

• When special video signals are input from a game console, etc., the Video Conversion function may not function. Connect the input connector to the monitor output connector of the same type.

While the menu is being displayed, no video is shown on the TV.

- The video being played will not appear in the background of the menu when the menu is operated during playback of the following video signals.
 - Some images of 3D video contents
 - Computer resolution images (example: VGA)
 - Video with an aspect ratio other than 16:9 or 4:3
 - 4K video
 - Some kind of HDR signals

When using HDMI ZONE2, the video output in MAIN ZONE is interrupted.

• When ZONE2 is operated with the same input source selected for MAIN ZONE and ZONE2, video in MAIN ZONE may be interrupted.



The menu screen is not displayed on the TV

The menu screen or status information screen is not displayed on the TV.

- The menu screen is only displayed on this unit and a TV connected with an HDMI cable. If this unit is connected to a TV using a different video output connector, operate while watching the display on this unit.
- The status information will not appear on the TV when the following video signals are being played.
 - Some images of 3D video content
 - Computer resolution images (example: VGA)
 - Video with an aspect ratio other than 16:9 or 4:3
 - Some kind of HDR signals
- When a 2D video is converted to a 3D video on the TV, the menu screen or status information screen is not displayed properly. (12) p. 241)
- In the pure direct playback mode, the menu screen or status information is not displayed. Switch to a sound mode other than the pure direct mode. (127 p. 131)
- Set the "TV Format" setting in the menu to a selection that is appropriate for the TV. (p. 189)

The color of the menu screen and operations content displayed on the television is different from normal

The color of the menu screen and operations content displayed on the television is different.

• Performing operations on this unit during playback of a Dolby Vision signal may cause variance in the color display of the menu screen and operations content. This is a characteristic of the Dolby Vision signal and is not a malfunction.



AirPlay cannot be played back

The AirPlay icon is not displayed on iTunes / iPhone / iPod touch / iPad.

- This unit and PC / iPhone / iPod touch / iPad are not connected to the same network (LAN). Connect it to the same LAN as this unit. (127 p. 78)
- The firmware on iTunes / iPhone / iPod touch / iPad is not compatible with AirPlay. Update the firmware to the latest version.

Audio is not output.

- The volume on iTunes / iPhone / iPod touch / iPad is set to the minimum level. The volume on iTunes / iPhone / iPod touch / iPad is linked with the volume on this unit. Set a proper volume level.
- The AirPlay playback is not performed, or this unit is not selected. Click the AirPlay icon on the iTunes / iPhone / iPod touch / iPad screen and select this unit. (127 p. 118)

Audio is interrupted during the AirPlay playback on iPhone / iPod touch / iPad.

- Quit the application running in the background of the iPhone/iPod touch/iPad, and then play using AirPlay.
- Some external factors may be affecting the wireless connection. Modify the network environment by taking measures such as shortening the distance from the wireless LAN access point.

iTunes cannot be played back through the remote control unit.

• Enable the "Allow iTunes audio control from remote speakers" setting on iTunes. Then, you can perform playback, pause, and skip operations through the remote control unit.



Settings

USB memory devices cannot be played back

USB memory device is not recognized.

- Disconnect and reconnect the USB memory device. (12 p. 75)
- Mass storage class compatible USB memory devices are supported.
- This unit does not support a connection through a USB hub. Connect the USB memory device directly to the USB port.
- The USB memory device must be formatted to FAT16 or FAT32.
- Not all USB memory devices are guaranteed to work. Some USB memory devices are not recognized. When using a type of portable hard disc drive compatible with the USB connection that requires power from an AC adapter, use the AC adapter that came with the drive.

Files on the USB memory device are not displayed.

- Files of a type not supported by this unit are not displayed. (pp. 86)
- This unit is able to display files in a maximum of eight folder layers. A maximum of 5000 files (folders) can also be displayed for each layer. Modify the folder structure of the USB memory device.
- When multiple partitions exist on the USB memory device, only files on the first partition are displayed.

iOS and Android devices are not recognized.

• The USB port of this unit does not support playback from iOS and Android devices.

Files on a USB memory device cannot be played.

- Files are created in a format that is not supported by this unit. Check the formats supported by this unit. (13 p. 275)
- You are attempting to play a file that is copyright protected. Files that are copyright protected cannot be played on this unit.
- Playback may not be possible if the album art file size exceeds 2 MB.





Bluetooth cannot be played back

Bluetooth devices cannot be connected to this unit.

- The Bluetooth function in the Bluetooth device has not been enabled. See the Owner's Manual of the Bluetooth device to enable the Bluetooth function.
- Bring the Bluetooth device near to this unit.
- The Bluetooth device cannot connect with this unit if it is not compatible with the A2DP profile.
- Turn the power of the Bluetooth device off and on again, and then try again.

The sound is cut off.

- Bring the Bluetooth device near to this unit.
- · Remove obstructions between the Bluetooth device and this unit.
- To prevent electromagnetic interference, locate this unit away from microwave ovens, wireless LAN devices and other Bluetooth devices.
- Reconnect the Bluetooth device.









The Internet radio cannot be played back

A list of broadcasting stations is not displayed.

- The LAN cable is not properly connected, or the network is disconnected. Check the connection status. (127 p. 78)
- Perform the network diagnostic mode.

Internet Radio cannot be played.

- The selected radio station is broadcasting in a format that is not supported by this unit. Formats that can be played back in this unit are MP3, WMA and AAC. (127 p. 278)
- The firewall function is enabled on the router. Check the firewall setting.
- The IP address is not properly set. (pp. 224)
- Check the power of the router is on.
- To obtain the IP address automatically, enable the DHCP server function on the router. Also, set the DHCP setting to "On" on this unit. (1) p. 224)
- To obtain the IP address manually, set the IP address on this unit. (12 p. 224)
- Some radio stations broadcast silently during some time period. In this case, no audio is output. Wait for a while and select the same radio station, or select another radio station. (127 p. 103)
- The selected radio station is not in service. Select a radio station in service.

Cannot connect to favorite radio stations.

• Radio station is not currently in service. Register radio stations in service.

Music files on PC or NAS cannot be played back

Files stored on a computer cannot be played.

- Files are stored in a non-compatible format. Record in a compatible format. (p. 277)
- Files that are copyright protected cannot be played on this unit.
- The USB port of this unit cannot be used for connection to a computer.
- Media sharing settings on the server or NAS do not allow this unit. Change the settings to allow this unit. For details, see the owner's manual of the server or NAS.

Server is not found, or it is not possible to connect to the server.

- The computer's or router's firewall is activated. Check the computer's or router's firewall settings.
- Computer's power is not turned on. Turn on the power.
- Server is not running. Launch the server.
- IP address of this unit is wrong. Check the IP address of this unit. (12 p. 221)

Music files on PC cannot be played back.

• Even if PC is connected to the USB port on this unit, music files on it cannot be played back. Connect PC to this unit through the network. (127 p. 78)

Files on PC or NAS are not displayed.

• Files of a type not supported by this unit are not displayed. (27)

Music stored on a NAS cannot be played.

- If you use a NAS in conformity with the DLNA standard, enable the DLNA server function in the NAS setting.
- If you use a NAS that does not conform with the DLNA standard, play the music via a PC. Set Windows Media Player's media sharing function and add NAS to the selected play folder.
- If connection is restricted, set audio equipment as the connection target.

Various online services cannot be played

Various online services cannot be played.

• The online service may have been discontinued.

The HDMI Control function does not work

The HDMI Control function does not work.

- Check that "HDMI Control" in the menu is set to "On". (
 <u>p. 180</u>)
- You cannot operate devices that are not compatible with the HDMI Control function. In addition, depending on the connected device or the settings, the HDMI Control function may not work. In this case, operate the external device directly. (127 p. 142)
- Check that the HDMI Control function setting is enabled on all devices connected to this unit. (127 p. 142)
- When you make connection related changes such as connecting an additional HDMI device, the link operation settings may be initialized. Turn off this unit and devices connected via HDMI, and turn them on again. (127 p. 142)
- The HDMI MONITOR 2 connector is not compatible with the HDMI Control function. Use the HDMI MONITOR 1 connector to connect to the TV. (1) p. 65)







Index

Cannot connect to a wireless LAN network

Cannot connect to the network.

- The network name (SSID), password and encryption setting have not been set up correctly. Configure the network settings according to the setting details of this unit. (127 p. 223)
- Shorten the distance from the wireless LAN access point and remove any obstructions to improve access first before re-connecting again. Place the unit away from microwave ovens and other network access points.
- Configure the access point channel settings away from channels that are being used by other networks.
- This unit is not compatible with WEP (TSN).

Cannot connect to a WPS Router.

Front panel

- Check that the WPS mode of the router is operating.
- Press the WPS button on the router and then press the "Connect" button displayed on the TV within 2 minutes.
- A router/settings that are compatible with WPS 2.0 standards are required. Set the encryption time to "None", "WPA-PSK (AES)" or WPA2-PSK (AES). (12) p. 223)
- If the router encryption method is WEP/WPA-TKIP/WPA2-TKIP, you cannot connect by using the WPS button on the router. In this case, use the "Scan Networks" or "Manual" method to connect.

265

Remote

Rear panel

Cannot connect to the network using iPhone/iPod touch/iPad.

• Update the iPhone/iPod touch/iPad firmware to the latest version.

Display

• When configuring the settings via a wireless connection, iOS 7 or later needs to be supported.

When using HDMI ZONE2, the devices does not function properly

When using MAIN ZONE, video output is interrupted in HDMI ZONE2.

• With the same input source selected for MAIN ZONE and ZONE2, when you operate MAIN ZONE, video may be interrupted in HDMI ZONE2.

When using HDMI ZONE2, no video or audio is output from the TV in ZONE2.

- Check that the power is on for ZONE2. (12 p. 157)
- Check the input source for ZONE2. (p. 157)
- The AUX1-HDMI connector on the front panel does not support the HDMI ZONE2 function.
- In ZONE2, playback is only possible when the input signals are HDMI signals.
- When the TV does not support the input audio format, audio is not output. Set the audio format to "PCM" on the playback device. Alternatively, set "ZONE2 Setup" "HDMI Audio" in the menu to "PCM". (1) 234)
- When the TV is not compatible with the resolution of the input video, no video is output. Set the output resolution on the playback device to a resolution that is compatible with the TV.

When using HDMI ZONE2, MAIN ZONE audio is played back as PCM.

• When the same input source is selected for MAIN ZONE and ZONE2, the audio format is limited according to the specifications of the TV in ZONE2.





Update/upgrade error messages

If an update/upgrade is interrupted or fails, an error message appears.

Display	Description
Connection failed. Please check your network, then try again.	The network connection is unstable. Connection to the server failed. Check your network environment and try the update again.
Update failed. Please check your network, then try again.	The download of the firmware failed. Check your network environment and try the update again.
Upgrade failed. Please check your network, then try again.	The download of the firmware failed. Check your network environment and try the upgrade again.
Please check your network, unplug and reconnect the power cord, and try again.	The update failed. Press and hold the \oplus on the main unit for more than 5 seconds, or remove and re-insert the power cord. The update restarts automatically.
Please contact customer service in your area.	This unit may be broken. Contact our Customer Service Center in your area.










Resetting factory settings

If the indicators are incorrect or the unit cannot be operated, restarting the unit may improve the problem. We recommend restarting the unit before returning the settings to the default settings. (127 p. 248)

If the operations are not improved by restarting the unit, follow the steps below.

Various settings are reset to the factory default values. Make settings again.



Turn off the power using Φ.

- 2 Press () while simultaneously pressing M-DAX and ZONE2 SOURCE.
- **3** Remove your fingers from the two buttons when "Initialized" appears on the display.

- Before returning the settings to the default settings, use the "Save & Load" function from the menu to save and restore the details of various settings configured on the unit. (<u>Pp. 242</u>)
- You can also reset all settings to the factory defaults using "Reset" "All Settings" in the menu. ($p.\,243)$






Resetting network settings

If network contents cannot be played or the unit cannot connect to the network, restarting the unit may improve the problem. We recommend restarting the unit before returning the settings to the default settings. (127 p. 248)

If the operations are not improved by restarting the unit, follow the steps below.

Network settings are reset to the factory default values. Make settings again.

However, the menu "Amp Assign", "Speaker Config." and "Video" settings are not reset.



- Press () to turn on power to the unit.
- **2** Turn INPUT SELECTOR to select "HEOS Music".
- **3** Press and hold the main unit's DIMMER and TUNER PRESET CH – at the same time for at least 3 seconds.
- **4** Remove your fingers from the two buttons when "Network Reset..." appears on the display.
- 5 "Completed" is shown in the display when reset is complete.

Ê

- Before returning the settings to the default settings, use the "Save & Load" function from the menu to save and restore the details of various settings configured on the unit. (<u>Pp. 242</u>)
- You can also reset the network settings to the factory defaults using "Reset" "Network Settings" in the menu. (p. 243)

NOTE

Remote

• Do not turn the power off until reset is complete.

Front panel





About HDMI

HDMI is an abbreviation of High-Definition Multimedia Interface, which is an AV digital interface that can be connected to a TV or amplifier. With the HDMI connection, high definition video and high quality audio formats adopted by Blu-ray Disc players (Dolby Digital Plus, Dolby TrueHD, DTS-HD, DTS-HD Master Audio) can be transmitted, which is not possible with the analog video transmission.

Furthermore, in the HDMI connection, audio and video signals can be transmitted through a single HDMI cable, while in conventional connections it is necessary to provide audio and video cables separately for connection between devices. This allows you to simplify the wiring configuration that tends to be quite complex in a home theater system. This unit supports the following HDMI functions.

• Deep Color

An imaging technology supported by HDMI. Unlike RGB or YCbCr, which uses 8 bits (256 shades) per color, it can use 10 bits (1024 shades), 12 bits (4096 shades), or 16 bits (65536 shades) to produce colors in higher definition.

Both devices linked via HDMI must support Deep Color.

• x.v.Color

This function lets HDTVs display colors more accurately. It enables display with natural, vivid colors.

"x.v.Color" is trademark of Sony Corporation.

• 3D

This unit supports input and output of 3D (3 dimensional) video signals of HDMI. To play back 3D video, you need a TV and player that provide support for the HDMI 3D function and a pair of 3D glasses.

• 4K

This unit supports input and output of 4K (3840 x 2160 pixels) video signals of HDMI.

Content Type

It automatically makes settings suitable for the video output type (content information).

Adobe RGB color, Adobe YCC601 color

The color space defined by Adobe Systems Inc. Because it is a wider color space than RGB, it can produce more vivid and natural images.

sYCC601 color

Each of these color spaces defines a palette of available colors that is larger than the traditional RGB color model.



Auto Lip Sync

This function can automatically correct delay between the audio and video.

Use a TV that is compatible with the Auto Lip Sync function.

HDMI Pass Through

Even when the power to this unit is set to standby, signals input from the HDMI input connector are output to a TV or other device that is connected to the HDMI output connector.

HDMI Control

If you connect the unit and an HDMI Control function compatible TV or player with an HDMI cable and then enable the HDMI Control function setting on each device, the devices will be able to control each other.

Power off link

This unit power off can be linked to the TV power off step.

Audio output destination switching

From the TV, you can switch whether to output audio from the TV or the AV amplifier.

· Volume adjustment

You can adjust this unit's volume in the TV volume adjustment operation.

· Input source switching

You can switch this unit input sources through linkage to TV input switching.

When playing the player, this unit input source switches to the source for that player.

• ARC (Audio Return Channel)

This function transmits audio signals from the TV to this unit through the HDMI cable and plays back the audio from the TV on this unit based on the HDMI Control function.

If a TV without the ARC function is connected via HDMI connections, video signals of the playback device connected to this unit are transmitted to the TV, but this unit can not play back the audio from the TV. If you want to enjoy surround audio for TV program, a separate audio cable connection is required.

In contrast, if a TV with the ARC function is connected via HDMI connections, no audio cable connection is required. Audio signals from the TV can be input to this unit through the HDMI cable between this unit and the TV. This function allows you to enjoy surround playback on this unit for the TV.

• eARC (Enhanced Audio Return Channel)

The eARC function is an extension of the conventional ARC function. It utilizes dedicated eARC function control to play back television audio from this unit without passing through HDMI control. Furthermore, the eARC function can transmit multichannel linear PCM, Dolby TrueHD, Dolby Atmos, DTS-HD Master Audio, DTS:X and other audio formats not compatible with conventional ARC. Connecting to an eARC function-compatible television also enables enjoyment of higher-quality surround playback of the audio content played from your television.

Front panel



Settings

Supported audio formats

2-channel Linear PCM	2-channel, 32 kHz – 192 kHz, 16/20/24 bit
Multi-channel Linear PCM	7.1-channel, 32 kHz – 192 kHz, 16/20/24 bit
Bitstream	Dolby Digital / DTS / Dolby Atmos / Dolby TrueHD / Dolby Digital Plus / DTS:X / DTS-HD Master Audio / DTS-HD High Resolution Audio / DTS Express
DSD	2-channel – 5.1-channel, 2.8 MHz

Supported video signals

- 480i
- 576i
- 720p 60/50Hz
- 1080p 60/50/24Hz

- 480p
- 576p
- 1080i 60/50Hz
- 4K 60/50/30/25/24 Hz

Copyright protection system

In order to play back digital video and audio such as BD video or DVD video via HDMI connection, both this unit and the TV or player must to support the copyright protection system known as HDCP (Highbandwidth Digital Content Protection System). HDCP is copyright protection technology comprised of data encryption and authentication of the connected AV devices. This unit supports HDCP.

 If a device that does not support HDCP is connected, video and audio are not output correctly. Read the owner's manual of your television or player for more information.

 When connecting this unit to a device that is compatible with the Deep Color, 4K, ARC and eARC functions, use a "High Speed HDMI cable with Ethernet" that bears the HDMI logo.

Front panel








Video conversion function

This unit automatically converts the input video signals as shown in the diagram before outputting them to the TV.



\int	Contents		Connections	\setminus	Playback	\setminus	Settings	\setminus	Tips	\mathbf{N}	Appendix	٨
--------	----------	--	-------------	-------------	----------	-------------	----------	-------------	------	--------------	----------	---

This unit can convert the input video signals to the resolution that is set for "Resolution" in the menu before outputting them to the TV. (127 p. 185)

	Output signal		HDMI											
Input signal		480i/576i	480p/576p	720p	1080i	1080p	1080p 24Hz	4K 30/25/24Hz	4K 60/50Hz					
	480i/576i	\checkmark	~											
	480p/576p		\checkmark	\checkmark	\checkmark	\checkmark	\checkmark	\checkmark	~					
	720p			\checkmark	\checkmark	\checkmark	\checkmark	\checkmark	~					
HDMI	1080i			\checkmark	\checkmark	\checkmark	\checkmark	\checkmark	\checkmark					
HDIVII	1080p 24Hz					\checkmark	\checkmark	\checkmark	\checkmark					
	1080p					\checkmark	\checkmark	\checkmark	~					
	4K 30/25/24Hz							\checkmark						
	4K 60/50Hz								√ *					
	480i/576i	\checkmark	~	\checkmark	\checkmark	\checkmark	\checkmark	\checkmark	~					
	480p/576p													
Component Video	720p													
	1080i													
	1080p													
Video	480i/576i	\checkmark	\checkmark											

* The HDMI connector on the front panel supports YCbCr 4:2:0 format only.





Contents	\setminus /	Co
----------	---------------	----

Playing back a USB memory devices

- This unit is compatible with MP3 ID3-Tag (Ver. 2) standard.
- This unit can show the artwork that was embedded by using MP3 ID3-Tag Ver. 2.3 or 2.4.
- This unit is compatible with WMA META tags.
- If the image size (pixels) of an album artwork exceeds 500 × 500 (WMA/MP3/Apple Lossless/DSD) or 349 × 349 (MPEG-4 AAC), then music may not be played back properly.

Compatible formats

	Sampling frequency	Channel	Bit rate	Extension
WMA *1	32/44.1/48 kHz	2-channel	48 – 192 kbps	.wma
MP3	32/44.1/48 kHz	2-channel	32 – 320 kbps	.mp3
WAV	32/44.1/48/88.2/ 96/176.4/192 kHz	2-channel	-	.wav
MPEG-4 AAC*1	32/44.1/48 kHz	2-channel	16 – 320 kbps	.aac/.m4a/.mp4
FLAC	32/44.1/48/88.2/ 96/176.4/192 kHz	2-channel	-	.flac
Apple Lossless*2	32/44.1/48/88.2/ 96/192 kHz	2-channel	_	.m4a
DSD	2.8/5.6 MHz	2-channel	-	.dsf/.dff

*1 Only files that are not protected by copyright can be played on this unit. Content downloaded from pay sites on the Internet are copyright protected. Also, files encoded in WMA format when ripped from a CD, etc. on a computer may be copyright protected, depending on the computer's settings.

*2 The Apple Lossless Audio Codec (ALAC) decoder is distributed under the Apache License, Version 2.0 (<u>http://www.apache.org/licenses/LICENSE-2.0</u>).





Maximum number of playable files and folder

The limits on the number of folders and files that can be displayed by this unit are as follows.

Item	USB memory device
Memory capacity	FAT16 : 2 GB, FAT32 : 2 TB
Number of folder directory levels *1	8 levels
Number of folders	500
Number of files*2	5000

*1 The limited number includes the root folder.

*2 The allowable number of files may differ according to the USB memory device capacity and the file size.

Playing back a Bluetooth device

This unit supports the following Bluetooth profile.

- A2DP (Advanced Audio Distribution Profile): When a Bluetooth device that supports this standard is connected, monaural and stereo sound data can be streamed at a high quality.
- AVRCP (Audio/Video Remote Control Profile): When a Bluetooth device that supports this standard is connected, the Bluetooth device can be operated from this unit.

About Bluetooth communications

Radio waves broadcast from this unit may interfere with the operation of medical devices. Make sure you turn off the power of this unit and Bluetooth device in the following locations as radio wave interference may cause malfunctions.

- Hospitals, trains, aircraft, petrol kiosks and places where flammable
 gases are generated
- Near automatic doors and fire alarms

Front panel



Front panel

Connections

Playing back a file saved on a PC or NAS

- This unit is compatible with MP3 ID3-Tag (Ver. 2) standard.
- This unit can show the artwork that was embedded by using MP3 ID3-Tag Ver. 2.3 or 2.4.
- This unit is compatible with WMA META tags.

Contents

- If the image size (pixels) of an album artwork exceeds 500 × 500 (WMA/MP3/WAV/FLAC/Apple Lossless/DSD) or 349 × 349 (MPEG-4 AAC), then
 music may not be played back properly.
- A server or server software compatible with distribution in the corresponding formats is required to play music files via a network.
 For playing mentioned audio formats via a network a server software, for example Twonky Media Server or jRiver Media Server, needs to be installed on your computer or NAS for full support. There are other server software available too. Please check supported formats.

Specifications of supported files

	Sampling frequency	Channel	Bit rate	Extension
WMA *1	32/44.1/48 kHz	2-channel	48 – 192 kbps	.wma
MP3	32/44.1/48 kHz	2-channel	32 – 320 kbps	.mp3
WAV	32/44.1/48/88.2/ 96/176.4/192 kHz	2-channel	_	.wav
MPEG-4 AAC*1	32/44.1/48 kHz	2-channel	16 – 320 kbps	.aac/.m4a/.mp4
FLAC	32/44.1/48/88.2/ 96/176.4/192 kHz	2-channel	_	.flac
Apple Lossless*2	32/44.1/48/88.2/ 96/192 kHz	2-channel	-	.m4a
DSD	2.8/5.6 MHz	2-channel	-	.dsf/.dff

*1 Only files that are not protected by copyright can be played on this unit. Content downloaded from pay sites on the Internet are copyright protected. Also, files encoded in WMA format when ripped from a CD, etc. on a computer may be copyright protected, depending on the computer's settings.

277

*2 The Apple Lossless Audio Codec (ALAC) decoder is distributed under the Apache License, Version 2.0 (http://www.apache.org/licenses/LICENSE-2.0).







Front panel



Playback

Playing back Internet Radio

Contents

Playable broadcast station specifications

	Sampling frequency	Bit rate	Extension
WMA	32/44.1/48 kHz	48 – 192 kbps	.wma
MP3	32/44.1/48 kHz	32 – 320 kbps	.mp3
MPEG-4 AAC	32/44.1/48 kHz	16 – 320 kbps	.aac/ .m4a/ .mp4

Connections

Personal memory plus function

The most recently used settings (input mode, HDMI output mode, sound mode, tone control, channel level, MultEQ[®] XT32, Dynamic EQ, Dynamic Volume, M-DAX and audio delay, etc.) are saved for each input source.

Settings

• "Surround Parameter" settings are stored for each sound mode.

Last function memory

This function stores the settings which were made before going into the standby mode.



Index

Sound modes and channel output

 \bigcirc This indicates the audio output channels or surround parameters that can be set.

◎ This indicates the audio output channels. The output channels depend on the settings of "Speaker Config.". (1) <u>p. 211</u>)

							Channel outpu	ut					
Sound mode	Front L/R	Center	Surround L/R	Surround Back L/R	Front Height L/R	Top Front L/R	Top Middle L/R	Top Rear L/R	Rear Height L/R	Front Dolby Atmos Enabled L/R	Surround Dolby Atmos Enabled L/R	Back Dolby Atmos Enabled L/R	Subwoofer
Direct/Pure Direct (2-channel)	0												◎*5
Direct/Pure Direct (Multi-channel)	0	O	O	◎*4	◎*4	◎*4	◎*4	©*4	©*4	◎*4	◎*4	◎*4	O
DSD Direct (2-channel)	0												©*5
DSD Direct (Multi-channel)	0	0	0										O
Stereo	0												O
Dolby Atmos	0	0	O	O	O	O	O	0	O	0	O	0	O
Dolby TrueHD	0	O	0	◎*4	◎*4								O
Dolby Digital Plus	0	O	O	◎*4	©*4								O
Dolby Digital	0	O	0										O
Dolby Surround *1	0	O	O	◎*6	O	O	0	O	O	O	0	0	O
DTS:X	0	O	O	O	O	O	0	O	O	0	0	0	O
DTS-HD	0	O	0	◎*4	◎*4								O
DTS Express	0	O	O	O									O
DTS 96/24	0	O	0	O									O
DTS Surround	0	O	O	O									O
DTS Neural:X *2	0	O	O	O	O	O	O	O	O	O	O	O	O
DTS Virtual:X *3	0	O	O	O									O
Multi Ch In	0	O	O	◎*4									O
Multi Ch Stereo	0	O	O	◎*7	©*7	◎*7	◎*7	©*7	◎*7	◎*7	©*7	◎*7	O
Virtual	0												O

*1 - *7 : "Sound modes and channel output" (12 p. 280)



Contents Connections Playback	Settings Tips	Appendix
-------------------------------	---------------	----------

- *1 The applicable sound mode includes "Dolby Surround" and sound modes that have "+Dolby Surround" in the sound mode name.
- *2 The applicable sound mode includes "DTS Neural:X" and sound modes that have "+Neural:X" in the sound mode name.
- *3 The applicable sound mode includes "DTS Virtual:X" and sound modes that have "+Virtual:X" in the sound mode name.
- *4 A signal for each channel contained in an input signal is output as audio.
- *5 Audio is output when "Subwoofer Mode" in the menu is set to "LFE+Main". (p. 219)
- *6 Audio is not output when "Speaker Config." "Surr. Back" in the menu is set to "1 spkr". (13 p. 213)
- *7 Audio is output from the speakers specified in the "Surround Parameter" "Speaker Select" settings. (197 p. 167)



Contents		/
Contents	\mathbf{X}	/

Sound modes and surround parameters

				ŧ	Surround Parameter				
Sound mode	Cinema EQ	Loudness Management *2	Dynamic Compression *3	Dialog Control *4	Low Frequency Effects *5	Speaker Select *6	Center Spread	DTS Neural:X	Subwoofer
Direct/Pure Direct (2-channel) *1		0	0						○*7
Direct/Pure Direct (Multi-channel) *1		0	0	0	0				
DSD Direct (2-channel)									○*7
DSD Direct (Multi-channel)									
Stereo		0	0	0	0				○*8
Dolby Atmos	0	0	0		0				
Dolby TrueHD	0	0	0		0				
Dolby Digital Plus	0	0	0		0				
Dolby Digital	0	0	0		0				
Dolby Surround	0	0	0				0		
DTS:X	0		0	0	0			0	
DTS-HD	0				0				
DTS Express	0				0				
DTS 96/24	0				0				
DTS Surround	0		0		0				
DTS Neural:X	0	0	0						
DTS Virtual:X	0		0						
Multi Ch In	0				0				
Multi Ch Stereo	0	0	0	0	0	0			
Virtual		0	0		0				

*1 - *8 : "Sound modes and surround parameters" (127 p. 283)



	Tone	Center Level	Subwoofer Level		Aud		M-DAX	
Sound mode	*9	Adjust *10	Adjust *11	MultEQ® XT32 *12*13*14	Dynamic EQ *15	Dynamic Volume *15	Audyssey LFC™ *15	*16
Direct/Pure Direct (2-channel) *1			○*7					
Direct/Pure Direct (Multi-channel) *1		0	0					
DSD Direct (2-channel)			○*7					
DSD Direct (Multi-channel)		0	0					
Stereo	0		○*8	0	0	0	0	0
Dolby Atmos	0	0	0	0	0	0		
Dolby TrueHD	0	0	0	0	0	0	0	
Dolby Digital Plus	0	0	0	0	0	0	0	
Dolby Digital	0	0	0	0	0	0	0	
Dolby Surround	0	0	0	0	0	0		0
DTS:X	0	0	0	0	0	0	0	
DTS-HD	0	0	0	0	0	0	0	
DTS Express	0	0	0	0	0	0	0	
DTS 96/24	0	0	0	0	0	0	0	
DTS Surround	0	0	0	0	0	0	0	
DTS Neural:X	0	0	0	0	0	0	0	0
DTS Virtual:X	0	0	0					0
Multi Ch In	0	0	0	0	0	0	0	
Multi Ch Stereo	0	0	0	0	0	0	0	0
Virtual	0		0	0	0	0	0	0

*1, *7 - *16: "Sound modes and surround parameters" (Pp. 283)





Contents \setminus / Connections \setminus / Playback \setminus /	Contents \	/ Connections	/ Playback	$\langle \rangle$	S
---	------------	---------------	------------	-------------------	---

- *1 During playback in Pure Direct mode, the surround parameters are the same as in Direct mode.
- *2 This item can be selected when a Dolby Digital, Dolby Digital Plus, Dolby TrueHD or Dolby Atmos signal is played.
- *3 This item can be selected when a Dolby Digital, Dolby Digital Plus, Dolby TrueHD, Dolby Atmos, DTS:X or DTS signal is played.
- *4 This item can be selected when a DTS:X signal that is compatible with the Dialog Control function is input.
- *5 This item can be selected when a Dolby Digital or DTS signal or DVD-Audio is played.
- *6 This item can be selected when Height, Ceiling or Dolby Atmos Enabled speakers are used.
- *7 This setting is available when "Subwoofer Mode" in the menu is set to "LFE+Main". (127 p. 219)
- *8 This item can be set when "Front" is set to "Small" or "Subwoofer Mode" is set to "LFE+Main". (27 p. 211, 219)
- *9 This item cannot be set when "Dynamic EQ" is set to "On". (12 p. 172)
- *10 This item cannot be set when "Center" is set to "None". (p. 212)
- *11 This item cannot be set when "Subwoofer" in the menu is set to "None". (p. 212)
- *12 This item cannot be set when Audyssey® Setup (Speaker Calibration) has not been performed.
- *13 This item cannot be selected when a DTS:X format with a sampling frequency of over 48 kHz is input.
- *14 This item cannot be set when sound mode is "DTS Virtual:X" or sound mode that have "+Virtual:X" in the sound mode name.
- *15 This item cannot be set when "MultEQ® XT32" in the menu is set to "Off". (p. 171)
- *16 This item can be set when the input signal is analog, PCM 48 kHz or 44.1 kHz.





Contents	$\langle \rangle$	(

Types of input signals, and corresponding sound modes

• This indicates the default sound mode.

 \bigcirc This indicates the selectable sound mode.

			2-chanr	nel signal							Multi-char	nnel signal					
Sound mode	NOTE	Dolby Digital (+/HD)	DTS (-HD)	Analog / PCM	DSD (Super Audio CD)	Dolby Atmos	Dolby TrueHD	Dolby Digital Plus	Dolby Digital (EX)	DTS:X	DTS-HD	DTS Express	DTS ES Dscrt6.1	DTS ES Mtrx6.1	DTS	PCM multi- channel	DSD (Super Audio CD)
Direct																	
Direct		0	0	O*2		0	0	0	0	0	0	0	0	0	0	0	
DSD Direct					0												0
Pure Direct																	
Pure Direct		0	0	0		0	0	0	0	0	0	0	0	0	0	0	
DSD Pure Direct					0												0
Stereo																	
Stereo		0	0			0	0	0	0	0	0	0	0	0	0	0	0
Dolby Surround																	
Dolby Atmos	*1																
Dolby TrueHD						○*3	0										
Dolby Digital Plus						○*4		0									
Dolby Digital									0								
Dolby (D+) (HD) + Dolby Surround							•		•								
Dolby (D+) (HD) + Neural:X							0	0	0								
Dolby Surround			0	0	0												

*1 - *4 : "Types of input signals, and corresponding sound modes" (12 p. 286)





			2-chanr	el signal							Multi-cha	nnel signal					
Sound mode	NOTE	Dolby Digital (+/HD)	DTS (-HD)	Analog / PCM	DSD (Super Audio CD)	Dolby Atmos	Dolby TrueHD	Dolby Digital Plus	Dolby Digital (EX)	DTS:X	DTS-HD	DTS Express	DTS ES Dscrt6.1	DTS ES Mtrx6.1	DTS	PCM multi- channel	DSD (Super Audio CD)
DTS Surround																	
DTS:X MSTR / DTS:X																	
DTS-HD MSTR											0*9						
DTS-HD HI RES											○*10						
DTS Express												0					
DTS ES Dscrt 6.1	*5												0				
DTS ES Mtrx 6.1	*5													0			
DTS 96/24															○*11		
DTS Surround													0	0	0		
DTS (-HD) + Dolby Surround											0	0	0	0	0		
DTS (-HD) + Neural:X	*6																
DTS (-HD) / DTS:X + Virtual:X	*7									0	0	0	0	0	0		
DTS Neural:X	*6	0		0	0												
DTS Virtual:X	*8		0	0	0												
Multi Ch In																	
Multi Ch In																	
Multi Ch In 7.1	*5															○*12	
Multi In + Dolby Surround																0	0
Multi In + Neural:X																0	0
Multi In + Virtual:X																0	0
Original sound mode																	
Multi Ch Stereo		0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
Virtual		0	0	0	0	○*13	0	0	0		0	0	0	0	0	0	0

*5 - *13 : "Types of input signals, and corresponding sound modes" (1 p. 286)





ſ	Contents	\bigvee	Connections	\bigvee	Playback	\bigvee	Settings	\bigvee	Tips	\bigvee	Appendix	
---	----------	-----------	-------------	-----------	----------	-----------	----------	-----------	------	-----------	----------	--

- *1 This item can be selected when using any of the Surround Back, Front Height, Top Front, Top Middle, Top Rear, Rear Height, Front Dolby, Surround Dolby or Back Dolby speaker.
- *2 The default sound mode for the AirPlay playback is "Direct".
- *3 This can be selected when the Dolby Atmos signal contains the Dolby TrueHD signal.
- *4 This can be selected when the Dolby Atmos signal contains the Dolby Digital Plus signal.
- *5 This item can be selected when surround back speakers are used.
- *6 This item cannot be selected when a DTS(-HD) format with a sampling frequency of over 48 kHz is input.
- *7 This item cannot be selected when a DTS:X format with a sampling frequency of over 48 kHz is input.
- *8 This item cannot be selected when the input signal is Dolby Digital, Dolby Digital Plus, Dolby TrueHD or Dolby Atmos.
- *9 This item can be selected when the input signal is DTS-HD Master Audio.
- *10 This item can be selected when the input signal is DTS-HD Hi Resolution.
- *11 This item can be selected when the input signal is DTS 96/24.
- *12 This item can be selected when the input signals contain surround back signals.
- *13 This can be selected when the Dolby Atmos signal contains the Dolby TrueHD or Dolby Digital Plus signal.







Explanation of terms

Audyssey

Audyssey Dynamic EQ®

Audyssey Dynamic EQ[®] solves the problem of deteriorating sound quality as volume is decreased by taking into account human perception and room acoustics.

Audyssey Dynamic EQ[®] works in tandem with Audyssey MultEQ[®] XT32 to provide well-balanced sound for every listener at any volume level.

Audyssey Dynamic Volume®

Dynamic Volume solves the problem of large variations in volume level between television programs, commercials, and between the soft and loud passages of movies. Audyssey Dynamic EQ[®] is integrated into Dynamic Volume so that as the playback volume is adjusted automatically, the perceived bass response, tonal balance, surround impression, and dialog clarity remain the same.

Audyssey LFC[™] (Low Frequency Containment)

Audyssey LFC[™] solves the problem of low frequency sounds disturbing people in neighboring rooms or apartments. Audyssey LFC[™] dynamically monitors the audio content and removes the low frequencies that pass through walls, floors and ceilings. It then applies psychoacoustic processing to restore the perception of low bass for listeners in the room. The result is great sound that no longer disturbs the neighbors.

Audyssey MultEQ[®] XT32

Audyssey MultEQ[®] XT32 is a room equalization solution that calibrates any audio system so that it can achieve optimum performance for every listener in a large listening area. Based on several room measurements, MultEQ[®] XT32 calculates an equalization solution that corrects for both time and frequency response problems in the listening area and also performs a fully automated surround system setup.

Front panel







Settings

Dolby

Dolby Atmos

Introduced first in the cinema, Dolby Atmos brings a revolutionary sense of dimension and immersion to the Home Theater experience. Dolby Atmos is an adaptable and scalable object based format that reproduces audio as independent sounds (or objects) that can be accurately positioned and move dynamically throughout the 3 dimensional listening space during playback. A key ingredient of Dolby Atmos is the introduction of a height plane of sound above the listener.

Dolby Atmos Stream

Dolby Atmos content will be delivered to your Dolby Atmos Enabled AV receiver via Dolby Digital Plus or Dolby TrueHD on Blu-ray Disc, downloadable files and streaming media. A Dolby Atmos stream contains special metadata that describes the positioning of sounds within the room. This object audio data is decoded by a Dolby Atmos AV receiver and scaled for optimum playback through Home Theater speaker systems of every size and configuration.

Dolby Digital

Dolby Digital is a multi-channel digital signal format developed by Dolby Laboratories.

A total of 5.1-channels are played: 3 front channels ("FL", "FR" and "C"), 2 surround channels ("SL" and "SR") and the "LFE" channel for low frequency effects.

Because of this, there is no crosstalk between channels and a realistic sound field with a "three-dimensional" feeling (sense of distance, movement and positioning) is achieved. This delivers a thrilling surround sound experience in the home.

Dolby Digital Plus

Dolby Digital Plus is an improved Dolby Digital signal format that is compatible with up to 7.1-channels of discrete digital sound and also improves sound quality thanks to extra data bit rate performance. It is upwardly compatible with conventional Dolby Digital, so it offers greater flexibility in response to the source signal and the conditions of the playback device.

Dolby Surround

Dolby Surround is a next generation surround technology that intelligently up mixes stereo; 5.1 and 7.1 content for playback through your surround speaker system. Dolby Surround is compatible with traditional speaker layouts, as well as Dolby Atmos enabled playback systems that employ inceiling speakers or products with Dolby speaker technology.

288

Remote



Settings

Dolby Speaker Technology (Dolby Atmos Enabled speakers)

A convenient alternative to speakers built into the ceiling, Dolby Atmos Enabled speakers employ the ceiling above you as a reflective surface for reproducing audio in the height plane above the listener. These speakers feature a unique upward firing driver and special signal processing. These features can be built into a conventional speaker or standalone speaker module. The features minimally impact the overall speaker footprint while providing an immersive listening experience during Dolby Atmos and Dolby Surround playback.

Dolby TrueHD

Dolby TrueHD is a high definition audio technology developed by Dolby Laboratories, using lossless coding technology to faithfully reproduce the sound of the studio master.

This format provides the facility to support up to 8 audio channels with a sampling frequency of 96 kHz/24 bit resolution and up to 6 audio channels with a sampling frequency of 192 kHz/24 bit resolution.

DTS

Dialog Control

Gives you control of the listening experience. You can lift the dialog out from the background sounds when clarity and intelligibility are desired. This requires that content has been authored to support Dialog Control.

DTS

This is an abbreviation of Digital Theater System, which is a digital audio system developed by DTS. DTS delivers a powerful and dynamic surround sound experience, and is found in the world's finest movie theaters and screening rooms.

DTS 96/24

DTS 96/24 is a digital audio format enabling high sound quality playback in 5.1-channels with a sampling frequency of 96 kHz and 24 bit quantization on DVD-Video.

DTS Digital Surround

DTSTM Digital Surround is the standard digital surround format of DTS, Inc., compatible with a sampling frequency of 44.1 or 48 kHz and up to 5.1-channels of digital discrete surround sound.

Front panel

289



DTS-ES[™] Discrete 6.1

DTS-ES[™] Discrete 6.1 is a 6.1-channel discrete digital audio format adding a surround back (SB) channel to the DTS digital surround sound. Decoding of conventional 5.1-channel audio signals is also possible according to the decoder.

DTS-ES[™] Matrix 6.1

DTS-ES[™] Matrix 6.1 is a 6.1-channel audio format that inserts a surround back (SB) channel to the DTS digital surround sound through matrix encoding. Decoding of conventional 5.1-channel audio signals is also possible according to the decoder.

DTS Express

DTS Express is an audio format supporting low bit rates (max. 5.1-channels, 24 to 256 kbps).

DTS-HD

This audio technology provides higher sound quality and enhanced functionality than the conventional DTS and is adopted as an optional audio for Blu-ray Disc.

This technology supports multi-channel, high data transfer speed, high sampling frequency, and lossless audio playback. Maximum 7.1-channels are supported in Blu-ray Disc.

DTS-HD High Resolution Audio

DTS-HD High Resolution Audio is an improved version of the conventional DTS, DTS-ES and DTS 96/24 signals formats, compatible with sampling frequencies of 96 or 48 kHz and up to 7.1-channels of discrete digital sound. High data bit rate performance provides high quality sound. This format is fully compatible with conventional products, including conventional DTS digital surround 5.1-channel data.

DTS-HD Master Audio

DTS-HD Master Audio is a lossless audio format created by Digital Theater System (DTS). This format provides the facility to support up to 8 audio channels with a sampling frequency of 96 kHz/24 bit resolution and up to 6 audio channels with a sampling frequency of 192 kHz/24 bit resolution. It is fully compatible with conventional products, including conventional DTS digital surround 5.1-channel data.

DTS:X

DTS:X produces a hemisphere of audio, where flyovers as well as ambient backgrounds become truly enveloping. DTS:X objects enable audio to move smoothly from one speaker to any other creating life-like realism.

290





Playback

DTS Neural:X

Enables an immersive audio experience for older content. DTS Neural:X can upmix your stereo, 5.1 or 7.1 content to take full advantage of all speakers in your surround sound system.

DTS Virtual:X

DTS Virtual:X allows you to enjoy multi-dimensional sound regardless of room size, layout, or speaker configuration.

Audio

Apple Lossless Audio Codec

This is a codec for lossless audio compression method developed by Apple Inc. This codec can be played back on iTunes, iPod or iPhone. Data compressed to approximately 60 - 70% can be decompressed to exactly the same original data.

FLAC (Free Lossless Audio Codec)

FLAC stands for Free lossless Audio Codec, and is a lossless free audio file format. Lossless means that the audio is compressed without any loss in quality.

The FLAC license is as shown below.

Copyright (C) 2000, 2001, 2002, 2003, 2004, 2005, 2006, 2007, 2008, 2009 Josh Coalson

Redistribution and use in source and binary forms, with or without modification, are permitted provided that the following conditions are met:

- Redistributions of source code must retain the above copyright notice, this list of conditions and the following disclaimer.
- Redistributions in binary form must reproduce the above copyright notice, this list of conditions and the following disclaimer in the documentation and/or other materials provided with the distribution.
- Neither the name of the Xiph.org Foundation nor the names of its contributors may be used to endorse or promote products derived from this software without specific prior written permission.

Front panel







Playback

THIS SOFTWARE IS PROVIDED BY THE COPYRIGHT HOLDERS AND CONTRIBUTORS "AS IS" AND ANY EXPRESS OR IMPLIED WARRANTIES, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE ARE DISCLAIMED. IN NO EVENT SHALL THE FOUNDATION OR CONTRIBUTORS BE LIABLE FOR ANY DIRECT, INDIRECT, INCIDENTAL, SPECIAL, EXEMPLARY, OR CONSEQUENTIAL DAMAGES (INCLUDING, BUT NOT LIMITED TO, PROCUREMENT OF SUBSTITUTE GOODS OR SERVICES; LOSS OF USE, DATA, OR PROFITS; OR BUSINESS INTERRUPTION) HOWEVER CAUSED AND ON ANY THEORY OF LIABILITY, WHETHER IN CONTRACT, STRICT LIABILITY, OR TORT (INCLUDING NEGLIGENCE OR OTHERWISE) ARISING IN ANY WAY OUT OF THE USE OF THIS SOFTWARE, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGE.

LFE

This is an abbreviation of Low Frequency Effect, which is an output channel that emphasizes low frequency effect sound. Surround audio is intensified by outputting 20 Hz to 120 Hz deep bass to the system subwoofer(s).

MP3 (MPEG Audio Layer-3)

This is an internationally standardized audio data compression scheme, using the "MPEG-1" video compression standard. It compresses the data volume to about one eleventh its original size while maintaining sound quality equivalent to a music CD.

MPEG (Moving Picture Experts Group), MPEG-2, MPEG-4

These are the names for digital compression format standards used for the encoding of video and audio. Video standards include "MPEG-1 Video", "MPEG-2 Video", "MPEG-4 Visual", "MPEG-4 AVC". Audio standards include "MPEG-1 Audio", "MPEG-2 Audio", "MPEG-4 AAC".

WMA (Windows Media Audio)

This is audio compression technology developed by Microsoft Corporation.

WMA data can be encoded using Windows Media® Player.

To encode WMA files, only use applications authorized by Microsoft Corporation. If you use an unauthorized application, the file may not work properly.

Sampling frequency

Sampling involves taking a reading of a sound wave (analog signal) at regular intervals and expressing the height of the wave at each reading in digitized format (producing a digital signal).

The number of readings taken in one second is called the "sampling frequency". The larger the value, the closer the reproduced sound is to the original.

Front panel

292





Speaker impedance

This is an AC resistance value, indicated in Ω (ohms). Greater power can be obtained when this value is smaller.

Dialogue normalization function

This function operates automatically during playback of Dolby Digital, Dolby Digital Plus, Dolby TrueHD, Dolby Atmos, DTS or DTS-HD sources. It automatically corrects the standard signal level for individual program sources.

Dynamic range

The difference between the maximum undistorted sound level and the minimum discernible level above the noise emitted by the device.

Downmix

This function converts the number of channels of surround audio to a lower number of channels and plays back according to the system's configuration.

Video

ISF

ISF (Imaging Science Foundation) is an organization that certifies video technicians who are then qualified to carry out calibration and adjustment to match the installation conditions. It also sets quality standards for the optimization of device video performance.

Progressive (sequential scanning)

This is a scanning system of the video signal that displays 1 frame of video as one image. Compared to the interlace system, this system provides images with less flickering and jagged edges.

Front panel







Network

AirPlay

AirPlay sends (plays) contents recorded in iTunes or on an iPhone/iPod touch/iPad to a compatible device via the network.

WEP Key (network key)

This is key information used for encrypting data when conducting data transfer. On this unit, the same WEP key is used for data encryption and decryption, so the same WEP key must be set on both devices in order for communications to be established between them.

Wi-Fi[®]

Wi-Fi Certification assures tested and proven interoperability by the Wi-Fi Alliance, a group certifying interoperability among wireless LAN devices.

WPA (Wi-Fi Protected Access)

This is a security standard established by the Wi-Fi Alliance. In addition to the conventional SSID (network name) and WEP key (network key), it also uses a user identification function and encrypting protocol for stronger security.

WPA2 (Wi-Fi Protected Access 2)

This is a new version of the WPA established by the Wi-Fi Alliance, compatible with more secure AES encryption.

WPA-PSK/WPA2-PSK (Pre-shared Key)

This is a simple authentication system for mutual authentication when a preset character string matches on the wireless LAN access point and client.

Network Names (SSID: Service Set Identifier)

When forming wireless LAN networks, groups are formed to prevent interference, data theft, etc. These groups are based on "SSID (network names)". For enhanced security, a WEP key is set so that communication is unavailable unless both the "SSID" and the WEP key match. This is suitable for constructing a simplified network.







Others

HDCP

When transmitting digital signals between devices, this copyright protection technology encrypts the signals to prevent content from being copied without authorization.

MAIN ZONE

The room where this unit is placed is called the MAIN ZONE.

Pairing

Pairing (registration) is an operation that is required in order to connect a Bluetooth device to this unit using Bluetooth. When paired, the devices authenticate each other and can connect without mistaken connections occurring.

When using Bluetooth connection for the first time, you need to pair this unit and the Bluetooth device to be connected.

Protection circuit

This is a function to prevent damage to devices within the power supply when an abnormality such as an overload, excess voltage occurs or over temperature for any reason.





Trademark information



Apple, AirPlay, iPad, iPad Air, iPad Pro and iPhone are trademarks of Apple Inc., registered in the U.S. and other countries.

The trademark "iPhone" is used in Japan with a license from Aiphone K.K.

Use of the Works with Apple badge means that an accessory has been designed to work specifically with the technology identified in the badge and has been certified by the developer to meet Apple performance standards.



LFC

Manufactured under license from Audyssey Laboratories[™]. U.S. and foreign patents pending. Audyssey MultEQ[®] XT32, Audyssey Dynamic EQ[®], Audyssey Dynamic Volume[®] and Audyssey LFC[™] are registered trademarks of Audyssey Laboratories.



The Bluetooth[®] word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by D&M Holdings Inc. is under license. Other trademarks and trade names are those of their respective owners.





Manufactured under license from Dolby Laboratories. Dolby, Dolby Atmos, Dolby Audio, Dolby Surround, Dolby Vision, and the double-D symbol are trademarks of Dolby Laboratories.

Front panel

296











For DTS patents, see <u>http://patents.dts.com</u>. Manufactured under license from DTS, Inc. DTS, the Symbol, DTS and the Symbol together, DTS:X, the DTS:X logo, Virtual:X, and the DTS Virtual:X logo are registered trademarks and/or trademarks of DTS, Inc. in the United States and/or other countries. © DTS, Inc. All Rights Reserved.



The terms HDMI, HDMI High-Definition Multimedia Interface, and the HDMI Logo are trademarks or registered trademarks of HDMI Licensing Administrator, Inc.

This item incorporates copy protection technology that is protected by U.S. patents and other intellectual property rights of Rovi Corporation. Reverse engineering and disassembly are prohibited.



The Wi-Fi CERTIFIED logo is a registered trademark of the Wi-Fi Alliance.

Wi-Fi Certification provides assurance that the device has passed the interoperability test conducted by the Wi-Fi Alliance, a group that certifies interoperability among wireless LAN devices.









Contents	Connections	Playback	Settings	Tips	Appendix	
----------	-------------	----------	----------	------	----------	--

Specifications

Power amplifier	
Rated output:	Front:
	110 W + 110 W (8 Ω/ohms, 20 Hz – 20 kHz with 0.08 % T.H.D.)
	150 W + 150 W (6 Ω/ohms, 1 kHz with 0.7 % T.H.D.)
	Center:
	110 W (8 Ω/ohms, 20 Hz – 20 kHz with 0.08 % T.H.D.)
	150 W (6 Ω/ohms, 1 kHz with 0.7 % T.H.D.)
	Surround:
	110 W + 110 W (8 Ω/ohms, 20 Hz – 20 kHz with 0.08 % T.H.D.)
	150 W + 150 W (6 Ω/ohms, 1 kHz with 0.7 % T.H.D.)
	Surround back / Height1 / Height2:
	110 W + 110 W (8 Ω/ohms, 20 Hz – 20 kHz with 0.08 % T.H.D.)
	150 W + 150 W (6 Ω/ohms, 1 kHz with 0.7 % T.H.D.)
Output connectors:	4 – 16 Ω/ohms







Contents	tions Playback Settings Tips Appendix
Analog	
Input sensitivity:	200 mV
Frequency response:	10 Hz – 100 kHz — +1, –3 dB (Direct mode)
S/N:	100 dB (IHF-A weighted, Direct mode)
Distortion:	0.005 % (20 Hz – 20 kHz) (Direct mode)
Rated output:	1.2 V
• Digital	
D/A output:	Rated output — 2 V (at 0 dB playback)
	Total harmonic distortion — 0.008 % (1 kHz, at 0 dB)
	S/N ratio — 102 dB
	Dynamic range — 100 dB
Digital input:	Format — Digital audio interface
Phono equalizer	
Input sensitivity:	2.5 mV
RIAA deviation:	±1 dB (20 Hz to 20 kHz)
S/N:	74 dB (IHF-A)
Distortion factor:	0.03 % (1 kHz, 3 V)





Video section		
 Standard video connectors 		
Input/output level and impedance:	1 Vp-p, 75 Ω/ohms	
Frequency response:	5 Hz – 10 MHz — 0, –3 dB	
Color component video connector		
Input/output level and impedance:	Y signal — 1 Vp-p, 75 Ω/ohms P _B / C _B signal — 0.7 Vp-p, 75 Ω/ohms P _R / C _R signal — 0.7 Vp-p, 75 Ω/ohms	
Frequency response:	5 Hz – 60 MHz — 0, –3 dB	
Tuner section	[FM]	[AM]
	(Note: μ V at 75 Ω /ohms, 0 dBf = 1 x 10 ⁻¹⁵ W)	
Reception frequency range:	87.5 MHz – 107.9 MHz	520 kHz – 1710 kHz
Effective sensitivity:	1.2 μV (12.8 dBf)	18 μV
50 dB sensitivity:	MONO – 2.8 µV (20.2 dBf)	
S/N ratio:	MONO — 70 dB (IHF–A weighted, Direct mode) STEREO — 67 dB (IHF–A weighted, Direct mode)	
Distortion:	MONO — 0.7 % (1 kHz) STEREO — 1.0 % (1 kHz)	





Contents Connections	Playback Settings Tips Appendix				
Wireless LAN section					
Network type (wireless LAN standard)	Conforming to IEEE 802.11a/b/g/n (Wi-Fi [®] compliant) *1				
Security:	WEP 64 bit, WEP 128 bit				
	WPA/WPA2-PSK (AES)				
	WPA/WPA2-PSK (TKIP)				
Used frequency range:	2.4 GHz, 5 GHz				

*1 The Wi-Fi[®] CERTIFIED Logo and the Wi-Fi CERTIFIED On-Product Logo are registered trademarks of the Wi-Fi Alliance.



Contents Connections	Playback Settings Tips Appendix
Bluetooth section	
Communications system:	Bluetooth Specification Version 3.0 + EDR (Enhanced Data Rate)
Transmission power:	Bluetooth Specification Power Class 1
Maximum communication range:	Approx. 98.4 ft/30 m in line of sight *2
Used frequency range:	2.4 GHz
Modulation scheme:	FHSS (Frequency-Hopping Spread Spectrum)
Supported profiles:	A2DP (Advanced Audio Distribution Profile) 1.2
	AVRCP (Audio Video Remote Control Profile) 1.5
Corresponding codec:	SBC
Transmission range (A2DP):	20 Hz – 20,000 Hz

*2 The actual communication range varies depending on the influence of such factors as obstructions between devices, electromagnetic waves from microwave ovens, static electricity, cordless phones, reception sensitivity, antenna performance, operating system, application software etc.

General

Power supply:	AC 120 V, 60 Hz
Power consumption:	680 W
Power consumption in standby mode:	0.2 W *
Power consumption in CEC standby	
mode:	0.5 W

* When "Network Control" in the menu is set to "Off In Standby" and "HDMI Pass Through" is set to "Off".


For purposes of improvement, specifications and design are subject to change without notice.











3D 270
4K 270
5.1-channel 34, 43
7.1-channel 34, 44
9.1-channel 48

11.1-channel 55

Contents

Index

A T

Provide a second second

AirPlay1	117
All Zone Stereo 1	129
Audio formats 272, 275, 277, 2	278
Audio settings 159, 1	64
Audyssey Dynamic EQ® 2	287
Audyssey Dynamic Volume® 2	287
Audyssey LFC™	287
Audyssey MultEQ® XT32 2	287
Audyssey settings 171, 1	196
Audyssey Sub EQ HT™1	195
Audyssey® Setup	194
Auto sound mode 1	133
Auto Standby 2	232

C C

Cable	۲۷ 70

167 D

Direct sound mode	137
Display	20
Dolby Atmos	
Dolby sound mode	134, 288
DTS sound mode	135, 289
DVD player	71, 85

Β

ECO Mode	229
External control device	80

G G

Tips

Game console	
General settings	162, 229

B H

HDCP	272
HDMI Control	142, 180
HEOS Account	109, 228
HEOS Favorites	123

B

Input Assign 1	90
Input settings 160, 1	90
Input signal 2	84
Input source	84
Internet Radio 1	02

304





Appendix

Connections

Playback

 \vee

Settings

Connections

Playback

Settings

Tips

CF L	
Listening position	. 194

K∰ M	
M-DAX	168
Menu map	159
Muting	. 85

K∰ N	
NAS	104
Network settings	221

Original sound mode	136

P P	
Pairing 91, 92	
PC 104	
PCM multi-channel sound mode 136	
Protection circuit 295	
Pure direct 132	

C S
Satellite tuner 70
Set-top box
Setup Assistant 162
Sleep timer 145
Smart select 147
Sound mode 131, 279, 281
Speaker connection 37
Speaker settings 160, 194
Spotify 121
Stereo sound mode 137

Front panel







Contents

Connections

Playback

Settings

K∰ T	
Tips 24	6
Troubleshooting 24	8
TV 65, 67, 6	8

USB memory device	75, 86

K∰ V	
Video camcorder	
Video Conversion	184, 273
Video Select	127
Video settings	159, 176
Volume	85, 125

C W	
Web control	153
Wi-Fi settings	222
Wired LAN	78, 221
Wireless LAN	79, 222

C Z









License

License information for the software used in the unit

About GPL (GNU-General Public License), LGPL (GNU Lesser General Public License) License

This product uses GPL/LGPL software and software made by other companies.

After you purchase this product, you may procure, modify or distribute the source code of the GPL/LGPL software that is used in the product.

Marantz provides the source code based on the GPL and LPGL licenses at the actual cost upon your request to our customer service center. However, note that we make no guarantees concerning the source code. Please also understand that we do not offer support for the contents of the source code.

This section describes software license used for this unit. To maintain the correct content, the original (English) is used.

GPL

Open Source Used	Version
bridge-utils	2.8
busybox	1.21.1
ebtables	2.0.10-4
Linux kernel	3.10.74
mtd-utils	1.4.3
ntfs-3g_ntfsprogs	2011.4.12
ntpclient	2007
u-boot	2015.01
wireless-tools	version 29







Front panel



Open Source Used	Version
ffmpeg	0.8.3
glibc	2.9
libmms	0.6.2
QT	5.4.2

Babel

MIT License

Copyright (c) 2014-2018 Sebastian McKenzie < sebmck@gmail.com >

Permission is hereby granted, free of charge, to any person obtaining a copy of this software and associated documentation files (the "Software"), to deal in the Software without restriction, including without limitation the rights to use, copy, modify, merge, publish, distribute, sublicense, and/or sell copies of the Software, and to permit persons to whom the Software is furnished to do so, subject to the following conditions:

The above copyright notice and this permission notice shall be included in all copies or substantial portions of the Software. THE SOFTWARE IS PROVIDED "AS IS", WITHOUT WARRANTY OF ANY KIND, EXPRESS OR IMPLIED, INCLUDING BUT NOT LIMITED TO THE WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE AND NONINFRINGEMENT. IN NO EVENT SHALL THE AUTHORS OR COPYRIGHT HOLDERS BE LIABLE FOR ANY CLAIM, DAMAGES OR OTHER LIABILITY, WHETHER IN AN ACTION OF CONTRACT, TORT OR OTHERWISE, ARISING FROM, OUT OF OR IN CONNECTION WITH THE SOFTWARE OR THE USE OR OTHER DEALINGS IN THE SOFTWARE.

u curl-7.24.0

Settings

COPYRIGHT AND PERMISSION NOTICE

Copyright (c) 1996 - 2014, Daniel Stenberg, <<u>daniel@haxx.se</u>> All rights reserved.

Tips

Permission to use, copy, modify, and distribute this software for any purpose with or without fee is hereby granted, provided that the above copyright notice and this permission notice appear in all copies.

THE SOFTWARE IS PROVIDED "AS IS", WITHOUT WARRANTY OF ANY KIND, EXPRESS OR IMPLIED, INCLUDING BUT NOT LIMITED TO THE WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE AND NONINFRINGEMENT OF THIRD PARTY RIGHTS. IN NO EVENT SHALL THE AUTHORS OR COPYRIGHT HOLDERS BE LIABLE FOR ANY CLAIM, DAMAGES OR OTHER LIABILITY, WHETHER IN AN ACTION OF CONTRACT, TORT OR OTHERWISE, ARISING FROM, OUT OF OR IN CONNECTION WITH THE SOFTWARE OR THE USE OR OTHER DEALINGS IN THE SOFTWARE.

Except as contained in this notice, the name of a copyright holder shall not be used in advertising or otherwise to promote the sale, use or other dealings in this Software without prior written authorization of the copyright holder.

Contents

Connections

Playback

e2fsprogs-libs-1.40.8/lib/uuid

Redistribution and use in source and binary forms, with or without modification, are permitted provided that the following conditions are met:

- 1. Redistributions of source code must retain the above copyright notice, and the entire permission notice in its entirety, including the disclaimer of warranties.
- 2. Redistributions in binary form must reproduce the above copyright notice, this list of conditions and the following disclaimer in the documentation and/or other materials provided with the distribution.
- **3.** The name of the author may not be used to endorse or promote products derived from this software without specific prior written permission.

THIS SOFTWARE IS PROVIDED "AS IS" AND ANY EXPRESS OR IMPLIED WARRANTIES, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE, ALL OF WHICH ARE HEREBY DISCLAIMED. IN NO EVENT SHALL THE AUTHOR BE LIABLE FOR ANY DIRECT, INDIRECT, INCIDENTAL, SPECIAL, EXEMPLARY, OR CONSEQUENTIAL DAMAGES (INCLUDING, BUT NOT LIMITED TO, PROCUREMENT OF SUBSTITUTE GOODS OR SERVICES; LOSS OF USE, DATA, OR PROFITS; OR BUSINESS INTERRUPTION) HOWEVER CAUSED AND ON ANY THEORY OF LIABILITY, WHETHER IN CONTRACT, STRICT LIABILITY, OR TORT (INCLUDING NEGLIGENCE OR OTHERWISE) ARISING IN ANY WAY OUT OF THE USE OF THIS SOFTWARE, EVEN IF NOT ADVISED OF THE POSSIBILITY OF SUCH DAMAGE.

D expat-2.0.1

Copyright (c) 1998, 1999, 2000 Thai Open Source Software Center Ltd and Clark Cooper

Copyright (c) 2001, 2002, 2003, 2004, 2005, 2006 Expat maintainers.

Permission is hereby granted, free of charge, to any person obtaining a copy of this software and associated documentation files (the "Software"), to deal in the Software without restriction, including without limitation the rights to use, copy, modify, merge, publish, distribute, sublicense, and/or sell copies of the Software, and to permit persons to whom the Software is furnished to do so, subject to the following conditions:

The above copyright notice and this permission notice shall be included in all copies or substantial portions of the Software.

THE SOFTWARE IS PROVIDED "AS IS", WITHOUT WARRANTY OF ANY KIND, EXPRESS OR IMPLIED, INCLUDING BUT NOT LIMITED TO THE WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE AND NONINFRINGEMENT.

IN NO EVENT SHALL THE AUTHORS OR COPYRIGHT HOLDERS BE LIABLE FOR ANY CLAIM, DAMAGES OR OTHER LIABILITY, WHETHER IN AN ACTION OF CONTRACT, TORT OR OTHERWISE, ARISING FROM, OUT OF OR IN CONNECTION WITH THE SOFTWARE OR THE USE OR OTHER DEALINGS IN THE SOFTWARE.

Front panel



aetopt

Contents

http://cvsweb.netbsd.org/bsdweb.cgi/src/lib/libc/stdlib/

Copyright (c) 1987, 1993, 1994 The Regents of the University of California. All rights reserved.

Redistribution and use in source and binary forms, with or without modification, are permitted provided that the following conditions are met:

- 1. Redistributions of source code must retain the above copyright notice, this list of conditions and the following disclaimer.
- 2. Redistributions in binary form must reproduce the above copyright notice, this list of conditions and the following disclaimer in the documentation and/or other materials provided with the distribution.
- 3. Neither the name of the University nor the names of its contributors may be used to endorse or promote products derived from this software without specific prior written permission.

THIS SOFTWARE IS PROVIDED BY THE REGENTS AND CONTRIBUTORS "AS IS" AND ANY EXPRESS OR IMPLIED WARRANTIES, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE ARE DISCLAIMED. IN NO EVENT SHALL THE REGENTS OR CONTRIBUTORS BE LIABLE FOR ANY DIRECT, INDIRECT, INCIDENTAL, SPECIAL, EXEMPLARY, OR CONSEQUENTIAL DAMAGES (INCLUDING, BUT NOT LIMITED TO, PROCUREMENT OF SUBSTITUTE GOODS OR SERVICES; LOSS OF USE, DATA, OR PROFITS; OR BUSINESS INTERRUPTION) HOWEVER CAUSED AND ON ANY THEORY OF LIABILITY, WHETHER IN CONTRACT, STRICT LIABILITY, OR TORT (INCLUDING NEGLIGENCE OR OTHERWISE) ARISING IN ANY WAY OUT OF THE USE OF THIS SOFTWARE, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGE.

□ jQuery

Settings

Copyright 2014 jQuery Foundation and other contributors http://jquery.com/

Tips

Permission is hereby granted, free of charge, to any person obtaining a copy of this software and associated documentation files (the "Software"), to deal in the Software without restriction, including without limitation the rights to use, copy, modify, merge, publish, distribute, sublicense, and/or sell copies of the Software, and to permit persons to whom the Software is furnished to do so, subject to the following conditions:

The above copyright notice and this permission notice shall be included in all copies or substantial portions of the Software.

THE SOFTWARE IS PROVIDED "AS IS", WITHOUT WARRANTY OF ANY KIND, EXPRESS OR IMPLIED, INCLUDING BUT NOT LIMITED TO THE WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE AND NONINFRINGEMENT. IN NO EVENT SHALL THE AUTHORS OR COPYRIGHT HOLDERS BE LIABLE FOR ANY CLAIM, DAMAGES OR OTHER LIABILITY, WHETHER IN AN ACTION OF CONTRACT, TORT OR OTHERWISE, ARISING FROM, OUT OF OR IN CONNECTION WITH THE SOFTWARE OR THE USE OR OTHER DEALINGS IN THE SOFTWARE.



□ libpcap-1.4.0

License: BSD

Redistribution and use in source and binary forms, with or without modification, are permitted provided that the following conditions are met:

- 1. Redistributions of source code must retain the above copyright notice, this list of conditions and the following disclaimer.
- 2. Redistributions in binary form must reproduce the above copyright notice, this list of conditions and the following disclaimer in the documentation and/or other materials provided with the distribution.
- **3.** The names of the authors may not be used to endorse or promote products derived from this software without specific prior written permission.

THIS SOFTWARE IS PROVIDED "AS IS" AND WITHOUT ANY EXPRESS OR IMPLIED WARRANTIES, INCLUDING, WITHOUT LIMITATION, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE.

libtar-1.2.11

Copyright (c) 1998-2003 University of Illinois Board of Trustees Copyright (c) 1998-2003 Mark D. Roth

All rights reserved.

Developed by: Campus Information Technologies and Educational Services, University of Illinois at Urbana-Champaign

Permission is hereby granted, free of charge, to any person obtaining a copy of this software and associated documentation files (the "Software"), to deal with the Software without restriction, including without limitation the rights to use, copy, modify, merge, publish, distribute, sublicense, and/or sell copies of the Software, and to permit persons to whom the Software is furnished to do so, subject to the following conditions:

- Redistributions of source code must retain the above copyright notice, this list of conditions and the following disclaimers.
- Redistributions in binary form must reproduce the above copyright notice, this list of conditions and the following disclaimers in the documentation and/or other materials provided with the distribution.
- Neither the names of Campus Information Technologies and Educational Services, University of Illinois at Urbana-Champaign, nor the names of its contributors may be used to endorse or promote products derived from this Software without specific prior written permission.

THE SOFTWARE IS PROVIDED "AS IS", WITHOUT WARRANTY OF ANY KIND, EXPRESS OR IMPLIED, INCLUDING BUT NOT LIMITED TO THE WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE AND NONINFRINGEMENT.

IN NO EVENT SHALL THE CONTRIBUTORS OR COPYRIGHT HOLDERS BE LIABLE FOR ANY CLAIM, DAMAGES OR OTHER LIABILITY, WHETHER IN AN ACTION OF CONTRACT, TORT OR OTHERWISE, ARISING FROM, OUT OF OR IN CONNECTION WITH THE SOFTWARE OR THE USE OR OTHER DEALINGS WITH THE SOFTWARE.

Front panel

311



DNS 320.10.80

Contents

The majority of the source code in the mDNSResponder project is licensed under the terms of the Apache License, Version 2.0, available from:

<http://www.apache.org/licenses/LICENSE-2.0>

To accommodate license compatibility with the widest possible range of client code licenses, the shared library code, which is linked at runtime into the same address space as the client using it, is licensed under the terms of the "Three-Clause BSD License".

The Linux Name Service Switch code, contributed by National ICT Australia Ltd (NICTA) is licensed under the terms of the NICTA Public Software Licence (which is substantially similar to the "Three-Clause BSD License", with some additional language pertaining to Australian law).

□ mongoose

Settinas

https://github.com/cesanta/mongoose/

Copyright (c) 2004-2013 Sergey Lyubka

Permission is hereby granted, free of charge, to any person obtaining a copy of this software and associated documentation files (the "Software"), to deal in the Software without restriction, including without limitation the rights to use, copy, modify, merge, publish, distribute, sublicense, and/or sell copies of the Software, and to permit persons to whom the Software is furnished to do so, subject to the following conditions:

The above copyright notice and this permission notice shall be included in all copies or substantial portions of the Software.

Tips

THE SOFTWARE IS PROVIDED "AS IS", WITHOUT WARRANTY OF ANY KIND, EXPRESS OR IMPLIED, INCLUDING BUT NOT LIMITED TO THE WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE AND NONINFRINGEMENT. IN NO EVENT SHALL THE AUTHORS OR COPYRIGHT HOLDERS BE LIABLE FOR ANY CLAIM, DAMAGES OR OTHER LIABILITY, WHETHER IN AN ACTION OF CONTRACT, TORT OR OTHERWISE, ARISING FROM, OUT OF OR IN CONNECTION WITH THE SOFTWARE OR THE USE OR OTHER DEALINGS IN THE SOFTWARE.

312



openssl-1.0.0d

Contents

Copyright (c) 1998-2011 The OpenSSL Project. All rights reserved.

Redistribution and use in source and binary forms, with or without modification, are permitted provided that the following conditions are met:

- 1. Redistributions of source code must retain the above copyright notice, this list of conditions and the following disclaimer.
- 2. Redistributions in binary form must reproduce the above copyright notice, this list of conditions and the following disclaimer in the documentation and/or other materials provided with the distribution.
- All advertising materials mentioning features or use of this software must display the following acknowledgment:
 "This product includes software developed by the OpenSSL Project for use in the OpenSSL Toolkit. (http://www.openssl.org/)"
- The names "OpenSSL Toolkit" and "OpenSSL Project" must not be used to endorse or promote products derived from this software without prior written permission. For written permission, please contact <u>openssl-core@openssl.org.</u>
- 5. Products derived from this software may not be called "OpenSSL" nor may "OpenSSL" appear in their names without prior written permission of the OpenSSL Project.
- 6. Redistributions of any form whatsoever must retain the following acknowledgment:

"This product includes software developed by the OpenSSL Project for use in the OpenSSL Toolkit (<u>http://www.openssl.org/</u>)"

THIS SOFTWARE IS PROVIDED BY THE OpenSSL PROJECT "AS IS" AND ANY EXPRESSED OR IMPLIED WARRANTIES, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE ARE DISCLAIMED. IN NO EVENT SHALL THE OpenSSL PROJECT OR ITS CONTRIBUTORS BE LIABLE FOR ANY DIRECT, INDIRECT, INCIDENTAL, SPECIAL, EXEMPLARY, OR CONSEQUENTIAL DAMAGES (INCLUDING, BUT NOT LIMITED TO, PROCUREMENT OF SUBSTITUTE GOODS OR SERVICES; LOSS OF USE, DATA, OR PROFITS; OR BUSINESS INTERRUPTION) HOWEVER CAUSED AND ON ANY THEORY OF LIABILITY, WHETHER IN CONTRACT, STRICT LIABILITY, OR TORT (INCLUDING NEGLIGENCE OR OTHERWISE) ARISING IN ANY WAY OUT OF THE USE OF THIS SOFTWARE, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGE.

This product includes cryptographic software written by Eric Young (<u>eay@cryptsoft.com</u>). This product includes software written by Tim Hudson (<u>tjh@cryptsoft.com</u>).

Playback

Settings

Tips



D portmap-6.0

Copyright (c) 1990 The Regents of the University of California.

- All rights reserved.
- Redistribution and use in source and binary forms, with or without modification, are permitted provided that the following conditions are met:
- 1. Redistributions of source code must retain the above copyright notice, this list of conditions and the following disclaimer.
- Redistributions in binary form must reproduce the above copyright notice, this list of conditions and the following disclaimer in the documentation and/or other materials provided with the distribution.
- A II advertising materials mentioning features or use of this software must display the following acknowledgement: This product includes software developed by the University of California, Berkeley and its contributors.
- Neither the name of the University nor the names of its contributors may be used to endorse or promote products derived from this software without specific prior written permission.
- THIS SOFTWARE IS PROVIDED BY THE REGENTS AND CONTRIBUTORS "AS IS" AND ANY EXPRESS OR IMPLIED WARRANTIES, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE ARE DISCLAIMED. IN NO EVENT SHALL THE REGENTS OR CONTRIBUTORS BE LIABLE FOR ANY DIRECT, INDIRECT, INCIDENTAL, SPECIAL, EXEMPLARY, OR CONSEQUENTIAL DAMAGES (INCLUDING, BUT NOT LIMITED TO, PROCUREMENT OF SUBSTITUTE GOODS OR SERVICES; LOSS OF USE, DATA, OR PROFITS; OR BUSINESS INTERRUPTION) HOWEVER CAUSED AND ON ANY THEORY OF LIABILITY, WHETHER IN CONTRACT, STRICT LIABILITY, OR TORT (INCLUDING NEGLIGENCE OR OTHERWISE) ARISING IN ANY WAY OUT OF THE USE OF THIS SOFTWARE, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGE.

pstdint.h-0.1.12

- BSD License:
- Copyright (c) 2005-2011 Paul Hsieh
- All rights reserved.
- Redistribution and use in source and binary forms, with or without modification, are permitted provided that the following conditions are met:
- 1. Redistributions of source code must retain the above copyright notice, this list of conditions and the following disclaimer.
- Redistributions in binary form must reproduce the above copyright notice, this list of conditions and the following disclaimer in the documentation and/or other materials provided with the distribution.
- **3.** The name of the author may not be used to endorse or promote products derived from this software without specific prior written permission.
- THIS SOFTWARE IS PROVIDED BY THE AUTHOR "AS IS" AND ANY EXPRESS OR IMPLIED WARRANTIES, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE ARE DISCLAIMED.
- IN NO EVENT SHALL THE AUTHOR BE LIABLE FOR ANY DIRECT, INDIRECT, INCIDENTAL, SPECIAL, EXEMPLARY, OR CONSEQUENTIAL DAMAGES (INCLUDING, BUT NOT LIMITED TO, PROCUREMENT OF SUBSTITUTE GOODS OR SERVICES; LOSS OF USE, DATA, OR PROFITS; OR BUSINESS INTERRUPTION) HOWEVER CAUSED AND ON ANY THEORY OF LIABILITY, WHETHER IN CONTRACT, STRICT LIABILITY, OR TORT (INCLUDING NEGLIGENCE OR OTHERWISE) ARISING IN ANY WAY OUT OF THE USE OF THIS SOFTWARE, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGE.



314





rl78flash 2000.3.1

License

The MIT License (MIT) Copyright (c) 2012 Maxim Salov

Permission is hereby granted, free of charge, to any person obtaining a copy of this software and associated documentation files (the "Software"), to deal in the Software without restriction, including without limitation the rights to use, copy, modify, merge, publish, distribute, sublicense, and/or sell copies of the Software, and to permit persons to whom the Software is furnished to do so, subject to the following conditions:

The above copyright notice and this permission notice shall be included in all copies or substantial portions of the Software.

THE SOFTWARE IS PROVIDED "AS IS", WITHOUT WARRANTY OF ANY KIND, EXPRESS OR IMPLIED, INCLUDING BUT NOT LIMITED TO THE WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE AND NONINFRINGEMENT. IN NO EVENT SHALL THE AUTHORS OR COPYRIGHT HOLDERS BE LIABLE FOR ANY CLAIM, DAMAGES OR OTHER LIABILITY, WHETHER IN AN ACTION OF CONTRACT, TORT OR OTHERWISE, ARISING FROM, OUT OF OR IN CONNECTION WITH THE SOFTWARE OR THE USE OR OTHER DEALINGS IN THE SOFTWARE.

Given selite 2003.5.7

SQLite Copyright SQLite is in the Public Domain

All of the code and documentation in SQLite has been dedicated to the public domain by the authors. All code authors, and representatives of the companies they work for, have signed affidavits dedicating their contributions to the public domain and originals of those signed affidavits are stored in a firesafe at the main offices of Hwaci. Anyone is free to copy, modify, publish, use, compile, sell, or distribute the original SQLite code, either in source code form or as a compiled binary, for any purpose, commercial or non-commercial, and by any means.

The previous paragraph applies to the deliverable code and documentation in SQLite - those parts of the SQLite library that you actually bundle and ship with a larger application. Some scripts used as part of the build process (for example the "configure" scripts generated by autoconf) might fall under other open-source licenses. Nothing from these build scripts ever reaches the final deliverable SQLite library, however, and so the licenses associated with those scripts should not be a factor in assessing your rights to copy and use the SQLite library.

All of the deliverable code in SQLite has been written from scratch. No code has been taken from other projects or from the open internet. Every line of code can be traced back to its original author, and all of those authors have public domain dedications on file. So the SQLite code base is clean and is uncontaminated with licensed code from other projects.

Front panel



stricpy.c , v1.11

- Copyright (c) 1998 Todd C. Miller < Todd.Miller@courtesan.com>
- Permission to use, copy, modify, and distribute this software for any purpose with or without fee is hereby granted, provided that the above copyright notice and this permission notice appear in all copies.
- THE SOFTWARE IS PROVIDED "AS IS" AND THE AUTHOR DISCLAIMS ALL WARRANTIES WITH REGARD TO THIS SOFTWARE INCLUDING ALL IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS. IN NO EVENT SHALL THE AUTHOR BE LIABLE FOR ANY SPECIAL, DIRECT, INDIRECT, OR CONSEQUENTIAL DAMAGES OR ANY DAMAGES WHATSOEVER RESULTING FROM LOSS OF USE, DATA OR PROFITS, WHETHER IN AN ACTION OF CONTRACT, NEGLIGENCE OR OTHER TORTIOUS ACTION, ARISING OUT OF OR IN CONNECTION WITH THE USE OR PERFORMANCE OF THIS SOFTWARE.

Laglib-1.5

copyright : (C) 2002 - 2008 by Scott Wheeler email : <u>wheeler@kde.org</u>

"The contents of this file are subject to the Mozilla Public License Version 1.1 (the "License"); you may not use this file except in compliance with the License. You may obtain a copy of the License at http://www.mozilla.org/MPL/

Software distributed under the License is distributed on an "AS IS" basis, WITHOUT WARRANTY OF ANY KIND, either express or implied. See the License for the specific language governing rights and limitations under the License.

Linyxml 2002.4.3

www.sourceforge.net/projects/tinyxml

This software is provided 'as-is', without any express or implied warranty. In no event will the authors be held liable for any damages arising from the use of this software.

Permission is granted to anyone to use this software for any purpose, including commercial applications, and to alter it and redistribute it freely, subject to the following restrictions:

- 1. The origin of this software must not be misrepresented; you must not claim that you wrote the original software. If you use this software in a product, an acknowledgment in the product documentation would be appreciated but is not required.
- 2. Altered source versions must be plainly marked as such, and must not be misrepresented as being the original software.
- **3.** This notice may not be removed or altered from any source distribution.

Front panel



Playback

Settings

Tremor

http://wiki.xiph.org/index.php/Tremor

Copyright (c) 2002, Xiph.org Foundation

Redistribution and use in source and binary forms, with or without modification, are permitted provided that the following conditions are met:

- 1. Redistributions of source code must retain the above copyright notice, this list of conditions and the following disclaimer.
- 2. Redistributions in binary form must reproduce the above copyright notice, this list of conditions and the following disclaimer in the documentation and/or other materials provided with the distribution.
- **3.** Neither the name of the Xiph.org Foundation nor the names of its contributors may be used to endorse or promote products derived from this software without specific prior written permission.

THIS SOFTWARE IS PROVIDED BY THE COPYRIGHT HOLDERS AND CONTRIBUTORS "AS IS" AND ANY EXPRESS OR IMPLIED WARRANTIES, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE ARE DISCLAIMED. IN NO EVENT SHALL THE FOUNDATION OR CONTRIBUTORS BE LIABLE FOR ANY DIRECT, INDIRECT, INCIDENTAL, SPECIAL, EXEMPLARY, OR CONSEQUENTIAL DAMAGES (INCLUDING, BUT NOT LIMITED TO, PROCUREMENT OF SUBSTITUTE GOODS OR SERVICES; LOSS OF USE, DATA, OR PROFITS; OR BUSINESS INTERRUPTION) HOWEVER CAUSED AND ON ANY THEORY OF LIABILITY, WHETHER IN CONTRACT, STRICT LIABILITY, OR TORT (INCLUDING NEGLIGENCE OR OTHERWISE) ARISING IN ANY WAY OUT OF THE USE OF THIS SOFTWARE, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGE.

🛛 zlib

http://www.zlib.net/

zlib.h -- interface of the 'zlib' general purpose compression library version 1.2.3, July 18th, 2005

Copyright (C) 1995-2004 Jean-loup Gailly and Mark Adler

This software is provided 'as-is', without any express or implied warranty. In no event will the authors be held liable for any damages arising from the use of this software.

Permission is granted to anyone to use this software for any purpose, including commercial applications, and to alter it and redistribute it freely, subject to the following restrictions:

- 1. The origin of this software must not be misrepresented; you must not claim that you wrote the original software. If you use this software in a product, an acknowledgment in the product documentation would be appreciated but is not required.
- 2. Altered source versions must be plainly marked as such, and must not be misrepresented as being the original software.
- 3. This notice may not be removed or altered from any source distribution.

Jean-loup Gailly jloup@gzip.org, Mark Adler madler@alumni.caltech.edu

The Spotify software is subject to third party licenses found here:

www.spotify.com/connect/third-party-licenses





www.marantz.com

You can find your nearest authorized distributor or dealer on our website.

mapantz[®] is a registered trademark.

3520 10618 00ASD Copyright © 2018 D&M Holdings Inc. All Rights Reserved.